

# WAVE PTX

Cloud-based Deployment  
iOS

# Standard PTT Application User Guide

Release 12.3

**DECEMBER 2023**

© 2023 Motorola Solutions, Inc. All Rights Reserved.

MN009685A01-005

# Intellectual Property and Regulatory Notices

## Copyrights

The Motorola Solutions products described in this document may include copyrighted Motorola Solutions computer programs. Laws in the United States and other countries preserve for Motorola Solutions certain exclusive rights for copyrighted computer programs. Accordingly, any copyrighted Motorola Solutions computer programs contained in the Motorola Solutions products described in this document may not be copied or reproduced in any manner without the express written permission of Motorola Solutions.

No part of this document may be reproduced, transmitted, stored in a retrieval system, or translated into any language or computer language, in any form or by any means, without the prior written permission of Motorola Solutions, Inc.

## Trademarks

MOTOROLA, MOTO, MOTOROLA SOLUTIONS, and the Stylized M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners.

## License Rights

The purchase of Motorola Solutions products shall not be deemed to grant either directly or by implication, estoppel or otherwise, any license under the copyrights, patents or patent applications of Motorola Solutions, except for the normal nonexclusive, royalty-free license to use that arises by operation of law in the sale of a product.

## Open Source Content

This product may contain Open Source software used under license. Refer to the product installation media for full Open Source Legal Notices and Attribution content.

## European Union (EU) and United Kingdom (UK) Waste of Electrical and Electronic Equipment (WEEE) Directive



The European Union's WEEE directive and the UK's WEEE regulation require that products sold into EU countries and the UK must have the crossed-out wheeled bin label on the product (or the package in some cases). As defined by the WEEE directive, this crossed-out wheeled bin label means that customers and end users in EU and UK countries should not dispose of electronic and electrical equipment or accessories in household waste.

Customers or end users in EU and UK countries should contact their local equipment supplier representative or service center for information about the waste collection system in their country.

## Disclaimer

Please note that certain features, facilities, and capabilities described in this document may not be applicable to or licensed for use on a specific system, or may be dependent upon the characteristics of a specific mobile subscriber unit or configuration of certain parameters. Please refer to your Motorola Solutions contact for further information.

© 2023 Motorola Solutions, Inc. All Rights Reserved

# Contact Us

The Centralized Managed Support Operations (CMSO) is the primary contact for technical support included in your organization's service agreement with Motorola Solutions. To enable faster response time to customer issues, Motorola Solutions provides support from multiple countries around the world.

Service agreement customers should be sure to call the CMSO in all situations listed under Customer Responsibilities in their agreement, such as:

- To confirm troubleshooting results and analysis before taking action

Your organization received support phone numbers and other contact information appropriate for your geographic region and service agreement. Use that contact information for the most efficient response. However, if needed, you can also find general support contact information on the Motorola Solutions website, by following these steps:

1. Enter [motorolasolutions.com](https://motorolasolutions.com) in your browser.
2. Ensure that your organization's country or region is displayed on the page. Clicking or tapping the name of the region provides a way to change it.
3. Select "Support" on the [motorolasolutions.com](https://motorolasolutions.com) page.

## Comments

Send questions and comments regarding user documentation to [documentation@motorolasolutions.com](mailto:documentation@motorolasolutions.com).

Provide the following information when reporting a documentation error:

- The document title and part number
- The page number or title of the section with the error
- A description of the error

Motorola Solutions offers various courses designed to assist in learning about the system. For information, go to <https://learning.motorolasolutions.com> to view the current course offerings and technology paths.

# Document History

Version	Description	Date
MN009685A01-005	<p>Updated <a href="#">User ID and Password User Login on page 27</a></p> <p>Updated <a href="#">Talkgroups on page 102</a> with the following sentence "The maximum number of is <b>250</b> or more depending on group type configuration by Administrator."</p> <p>Updated <a href="#">Minimizing a Video Call on page 151</a></p>	December 2023
MN009685A01-004	<p>Updated <a href="#">Integrated Secure Messaging on page 129</a> with the 3GPP MCDATA compliant messaging solution.</p>	September 2023
MN009685A01-003	<p>Updated <a href="#">Tones on page 54</a> section with Emergency Cancel Tone.</p> <p>Updated <a href="#">Declaring an Emergency on page 72</a> section with the following note: "If the emergency cannot be declared, the emergency fail tone is played, and a toast message is displayed."</p> <p>Updated <a href="#">Canceling Emergencies on page 74</a> section with the following information: "The emergency is canceled, a message indicating that the emergency is canceled is displayed, and an <b>Emergency Cancel</b> tone is played".</p> <p>Updated <a href="#">Viewing Active Geofences on page 80</a> section with the following information: "You can see the currently active fences, the type, the dispatcher maintaining the fence, the group name and you can see whether you are inside or outside the fence. You can see an indication that the fence tone (Bell icon) is active. If no fences are active, the following message displays: No record found".</p> <p>Updated <a href="#">Receiving an Incoming Video Call on page 155</a> section with the following note: "If you receive a video call while transmitting on a PTT call (holding the floor), you will receive a system notification to indicate the incoming video call."</p> <p>Updated hyperlinks for Broadcast Call Confirmation and Voice Message Fallback in the <a href="#">Settings on page 160</a> section.</p>	August 2023
MN009685A01-002	<p>Updated the Google and ESRI map supportability.</p>	June 2023
MN009685A01-001	<p>Initial version.</p>	November 2022

# Contents

<b>Intellectual Property and Regulatory Notices</b> .....	<b>2</b>
<b>Contact Us</b> .....	<b>3</b>
<b>Document History</b> .....	<b>4</b>
<b>List of Figures</b> .....	<b>15</b>
<b>List of Tables</b> .....	<b>17</b>
<b>List of Procedures</b> .....	<b>18</b>
<b>Chapter 1: Introduction and Key Features</b> .....	<b>22</b>
1.1 What's New in this Release?.....	23
<b>Chapter 2: Application Installation and Getting Started</b> .....	<b>24</b>
2.1 Installation Prerequisites.....	24
2.2 Downloading the PTT Application.....	24
2.3 First-Time Activation.....	24
2.3.1 Activating on an iPhone.....	25
2.3.2 Activating on an iPhone using only Wi-Fi Network.....	26
2.4 User ID and Password User Login.....	27
2.4.1 Logging in the First Time.....	27
2.4.2 Setting Your Password.....	28
2.4.3 Confirming to Remember Your Password (Private Device).....	28
2.4.4 Subsequent Login.....	28
2.4.5 Forgetting Your Password.....	29
2.4.6 Switch User for Users with User ID and Password.....	29
2.4.6.1 Accessing the Switch User Option.....	29
2.5 Tutorial.....	30
2.6 Login.....	30
2.6.1 Manually Logging into the PTT Application.....	30
2.7 Application Updates.....	30
2.8 In Application Update Notification.....	30
<b>Chapter 3: Navigate the Push-to-Talk Application</b> .....	<b>31</b>
3.1 History.....	31
3.2 Favorites.....	32
3.3 Contacts.....	33
3.4 Talkgroups.....	33
3.5 Map.....	34
3.6 Call Screen.....	35

3.7 Menu.....	36
3.7.1 Menu Options.....	36
3.8 Actions.....	36
3.9 Context Menus.....	37
3.10 PTT Button.....	40
3.10.1 External PTT Button.....	40
3.10.2 On-screen Soft PTT Button.....	40
3.11 Navigate to the Previous Screen.....	40
3.12 Scrolling.....	40
3.13 Searching.....	40
3.14 Icons.....	41
3.14.1 Actions Icons.....	41
3.14.2 Avatar Icons.....	43
3.14.3 Call Screen Icons.....	45
3.14.4 Contacts Icon.....	46
3.14.5 Emergency Icons.....	47
3.14.6 History Icons.....	47
3.14.7 Integrated Secure Messaging Icons.....	48
3.14.8 Talkgroup Icons.....	49
3.14.9 Map Icons.....	49
3.14.10 Miscellaneous Icons.....	51
3.14.11 Presence Icons.....	51
3.14.12 Tab Icons.....	52
3.14.13 Title Bar Icons.....	52
3.14.14 Video Streaming Icons.....	53
3.15 Tones.....	54
<b>Chapter 4: Network Connectivity.....</b>	<b>56</b>
4.1 PTT over 4G LTE networks.....	56
4.2 PTT over Wi-Fi.....	56
4.2.1 Switching between Cellular Data Networks and Wi-Fi Networks during a Call.....	56
4.2.2 Authenticated Wi-Fi Connections.....	57
<b>Chapter 5: User Information Display.....</b>	<b>58</b>
5.1 Viewing User Information.....	58
<b>Chapter 6: Make and Receive PTT Calls.....</b>	<b>59</b>
6.1 Making Calls.....	59
6.1.1 Making One-to-One (1:1) Calls with Automatic Call Answer.....	59
6.1.2 Making One-to-One (1:1) Calls with Manual Call Answer.....	59
6.1.3 Call a Contact that is Offline or has a Do Not Disturb (DND) Status.....	60

6.1.4 Making Talkgroup Calls.....	60
6.1.5 Making Quick Group Calls.....	61
6.1.6 Making Broadcast Calls.....	62
6.1.7 Call from Device Contacts.....	63
6.1.7.1 Placing a Call from Device Contacts.....	63
6.1.8 Calling from History.....	63
6.1.9 Calling from Missed Call Alert.....	64
6.1.10 Calling from Instant Personal Alert.....	64
6.1.11 Call Behavior when Contact or Talkgroup is Unavailable.....	64
6.1.12 Dialing a Manual Call to a PTT User.....	65
6.2 Receiving Calls.....	66
6.2.1 Receiving One-to-One (1:1) Calls .....	66
6.2.2 Receive Broadcast Talkgroup Calls.....	66
6.2.3 Broadcast Call History.....	67
6.3 Turning the Speaker On/Off.....	68
6.4 Set the PTT Call Volume.....	68
6.5 Interaction with Silent or Sound Mode.....	69
6.6 Interaction between PTT and Cellular Calls.....	69
6.7 Call Behavior in Background.....	69
6.8 Rejoin a PTT Talkgroup Call.....	70
<b>Chapter 7: Emergency Calling and Alert (Optional).....</b>	<b>71</b>
7.1 Declare an Emergency.....	71
7.1.1 Declaring an Emergency.....	72
7.2 Authorized User Remotely Declaring an Emergency on your Behalf.....	72
7.3 Receive an Emergency.....	73
7.3.1 Receiving an Emergency Call.....	73
7.3.2 Receiving an Emergency Cancel Notification.....	73
7.4 Emergency Cancellation.....	74
7.4.1 Canceling Emergencies.....	74
7.5 Authorized User.....	74
7.5.1 Declaring an Emergency on Behalf of Another User.....	74
7.5.2 Cancel an Emergency on Behalf of Another User.....	76
7.5.2.1 Canceling an Emergency from the Context Menu.....	76
7.5.2.2 Canceling an Emergency from Call Screen.....	77
7.6 Enable Emergency User Check.....	77
7.6.1 Enabling Emergency User Check from Call Screen.....	77
7.6.2 Monitor Device Location.....	78
7.6.3 Monitor Device Cellular Network Signal Strength.....	78
7.6.4 Monitor Device Wi-Fi Signal Strength.....	78

7.6.5 Monitor Device Battery Level.....	78
<b>Chapter 8: Area-Based Warning Tones.....</b>	<b>79</b>
8.1 Enter a Geofence.....	80
8.2 Exit a Geofence.....	80
8.3 Viewing Active Geofences.....	80
<b>Chapter 9: Enter a Geofence.....</b>	<b>81</b>
<b>Chapter 10: Supervisory Override.....</b>	<b>82</b>
10.1 Supervisor Talkgroup.....	82
10.2 Non-supervisor Talkgroup Members.....	82
<b>Chapter 11: Alerts.....</b>	<b>83</b>
11.1 Instant Personal Alert (IPA).....	83
11.1.1 Sending an Alert.....	83
11.1.2 Receiving an Alert.....	83
11.2 Missed Call Alert (MCA).....	84
11.2.1 Replying to a Missed Call Alert.....	84
11.3 Multiple Missed Call Alerts or Instant Personal Alerts per Caller.....	84
11.4 Set the PTT Alert Volume.....	84
<b>Chapter 12: Real-Time Presence.....</b>	<b>85</b>
12.1 My Presence.....	85
12.1.1 Setting Self Presence.....	85
12.2 PTT Contact Presence.....	86
<b>Chapter 13: History.....</b>	<b>87</b>
13.1 Access History.....	87
13.2 Search History.....	87
13.3 History Icons.....	88
13.4 Access Conversation Details.....	88
13.5 Making a PTT Call.....	88
13.6 Adding a PTT Contact (Optional).....	88
13.7 Adding a Phone Contact (Optional).....	89
13.8 Deleting History.....	89
13.9 Clearing All History.....	89
13.10 Deleting a Message.....	90
13.11 Forward a Message.....	90
13.12 Photo and Video Sending.....	90
<b>Chapter 14: Favorites.....</b>	<b>91</b>
14.1 Favorite Icons.....	92
14.2 Search Favorites.....	92
14.3 View or Edit Favorite Contacts.....	92



14.4 Adding Favorite Contacts.....	92
14.5 Removing Favorite Contacts.....	92
14.6 View or Edit Favorite Groups.....	93
14.7 Adding Favorite Groups.....	93
14.8 Removing Favorite Groups.....	93
<b>Chapter 15: Contacts.....</b>	<b>94</b>
15.1 Contact Icon.....	94
15.2 Search Contacts.....	94
15.2.1 Your Contact List.....	94
15.2.2 Searching Corporate Global Directory Contacts.....	95
15.3 View Contacts.....	95
15.3.1 Sorting the Contact List.....	95
15.3.2 Show or Hide Offline Contacts.....	96
15.3.2.1 Showing only Online Contacts.....	96
15.3.2.2 Showing all Contacts.....	96
15.4 Viewing Contact Details.....	97
15.5 Contact Additions.....	97
15.5.1 Adding a New PTT Contact Manually.....	97
15.5.2 Importing a PTT Contact from the Device's Contact List.....	98
15.5.3 Adding a New Phone Contact Manually (Optional).....	98
15.5.4 Importing a New Phone Contact from Device's Contact List (Optional).....	99
15.6 Edit Contact Details.....	99
15.6.1 Editing a Contact Name.....	100
15.6.2 Adding or Changing a Contact Avatar.....	100
15.6.3 Changing Contact Color.....	100
15.6.4 Make Contact a Favorite or Remove as a Favorite.....	100
15.7 Deleting a Contact.....	101
<b>Chapter 16: Talkgroups.....</b>	<b>102</b>
16.1 Talkgroup Icons.....	102
16.2 Search Talkgroups.....	102
16.3 View Talkgroups.....	102
16.4 Call Permissions.....	103
16.5 Dynamic Area-Based Talkgroups (Optional).....	104
16.6 Viewing Talkgroup Details.....	104
16.6.1 Broadcast Talkgroup Details (Broadcasters only).....	105
16.7 Adding a Talkgroup.....	105
16.8 Editing Talkgroup Details.....	105
16.8.1 Editing a Talkgroup Name.....	106
16.8.2 Adding One or More Members to a Talkgroup.....	106

16.8.3 Removing a Member from a Talkgroup.....	106
16.8.4 Renaming a Talkgroup Member.....	107
16.8.5 Adding or Changing a Talkgroup Avatar.....	108
16.8.6 Changing Talkgroup Color.....	108
16.8.7 Make Talkgroup a Favorite or Remove as a Favorite.....	108
16.9 Deleting a Talkgroup.....	108
<b>Chapter 17: Talkgroup Scanning.....</b>	<b>110</b>
17.1 Turning Scanning On or Off.....	110
17.2 Adding Talkgroups to Scan Lists.....	111
17.3 Removing Talkgroups from Scan Lists or Changing the Scanning Priority.....	112
<b>Chapter 18: Map.....</b>	<b>113</b>
18.1 Map Icons.....	113
18.2 Search Map.....	114
18.3 Recenter the Map.....	114
18.4 Individuals.....	114
18.4.1 Sending My Location or an Arbitrary Location to a Contact.....	114
18.4.2 Sending My Location or an Arbitrary Location to a Quick Group.....	115
18.4.3 Sending My Location or an Arbitrary Location to a Talkgroup.....	115
18.5 Supervisor with Location Capability.....	116
18.5.1 Talkgroup Member Location.....	116
18.5.1.1 Viewing Talkgroup Member Locations.....	116
18.5.1.2 Viewing Talkgroup Member Location Details.....	117
18.5.1.3 Calling a Talkgroup Member.....	118
18.5.1.4 Sharing Your Location or an Arbitrary Location to a Talkgroup with Location Capability.....	119
18.5.2 Boundary.....	120
18.5.2.1 Creating a Boundary.....	121
18.5.2.2 Recentering Boundary on the Map.....	122
18.5.2.3 Recentering the Map to your Location.....	123
18.5.2.4 Boundary Settings.....	123
18.5.3 Creating a Quick Group from the Map.....	125
18.5.3.1 Adding Members to a Quick Group.....	127
18.5.3.2 Removing Quick Group Members.....	128
<b>Chapter 19: Integrated Secure Messaging.....</b>	<b>129</b>
19.1 Integrated Secure Messaging Icons.....	130
19.2 Multimedia Content.....	130
19.2.1 Text Messages.....	130
19.2.1.1 Sending a Text Message.....	131
19.2.1.2 Selecting Quick Text.....	133

19.2.1.3 Adding Quick Text.....	134
19.2.1.4 Deleting Quick Text.....	137
19.2.1.5 Receiving a Text Message.....	138
19.2.2 Image Messaging.....	140
19.2.2.1 Saving an Image Message.....	140
19.2.3 Video Messaging.....	141
19.2.3.1 Saving a Video Message.....	141
19.2.4 Voice Messaging.....	141
19.2.4.1 Receiving a Voice Message.....	142
19.2.4.2 Sending a Voice Message from History.....	142
19.2.5 File Messaging.....	143
19.2.5.1 Send a File Message.....	143
19.2.5.2 Receive a File Message.....	143
19.2.5.3 Saving a File Message.....	143
19.2.6 Receiving a Location Message.....	144
19.3 Message Actions.....	144
19.3.1 Forwarding a Message to a Contact or Talkgroup.....	145
19.3.2 Forwarding a Message to a Quick Group.....	145
19.3.3 Replying to a Sender.....	146
19.3.4 Replying to Talkgroup (Talkgroup Messages).....	146
19.3.5 Deleting a Message.....	146
19.3.6 History Message Actions.....	147
19.3.6.1 Sending a Text Message from History.....	147
19.3.6.2 Copying a Text Message from History.....	147
19.3.6.3 Sending a Photo or a Video from History.....	148
19.3.6.4 Sending a Voice Message from History.....	148
19.3.6.5 Sending a File from History.....	149
19.3.6.6 Sharing my Location from History.....	149
<b>Chapter 20: Video Streaming (Optional).....</b>	<b>150</b>
20.1 Video Streaming Icons.....	150
20.2 Minimizing a Video Call.....	151
20.3 Making a Video Call to a Contact.....	151
20.4 Making a Video Call to a Quick Group.....	152
20.5 Making a Video Call to a Talkgroup.....	153
20.6 Receive an Incoming Video Call.....	154
20.6.1 Receiving an Incoming Video Call.....	155
20.6.2 Receiving a Video Stream Request.....	155
20.6.3 Receive an Unconfirmed Video Stream Request.....	156
<b>Chapter 21: Airplane Mode.....</b>	<b>157</b>

<b>Chapter 22: Accessories and Bluetooth Use.....</b>	<b>158</b>
22.1 Using a Wired Audio Headset.....	158
22.2 Using Bluetooth.....	158
22.2.1 Car Kit.....	158
22.2.2 External PTT Button.....	159
22.2.3 Bluetooth for PTT.....	159
22.3 Using a Remote Speaker Microphone.....	159
22.3.1 Wired.....	159
22.3.2 Bluetooth.....	159
<b>Chapter 23: Settings.....</b>	<b>160</b>
23.1 Accessing the PTT Application Settings.....	161
23.2 Important Message.....	161
23.2.1 Upgrading the PTT Application.....	161
23.3 Alert Repeat.....	162
23.3.1 Changing the Alert Repeat Setting.....	162
23.4 Alert Tone.....	162
23.4.1 Changing the Alert Tone Setting.....	162
23.5 Allow Unconfirmed Video Transmission.....	163
23.5.1 Changing the Allow Unconfirmed Video Transmission Setting.....	163
23.6 Audio Interaction.....	163
23.6.1 Changing the Audio Interaction Setting.....	163
23.7 Auto Answer Video Call.....	163
23.7.1 Changing the Auto Answer Video Call Setting.....	164
23.8 Auto Download.....	164
23.8.1 Changing the Auto Download Setting.....	164
23.9 Background Mode.....	164
23.9.1 Changing the Background Mode Setting.....	164
23.10 Broadcast Call Confirmation.....	165
23.10.1 Changing the Broadcast Call Confirmation Setting.....	165
23.11 Capacity.....	165
23.11.1 Viewing the Phone Capacity Setting.....	165
23.12 Contact Sorting.....	165
23.12.1 Changing the Contact Sorting Setting.....	166
23.13 Display Name.....	166
23.13.1 Viewing or Changing Your Display Name Setting.....	166
23.14 Emergency.....	166
23.14.1 Viewing Your Emergency Contacts Setting.....	167
23.15 Emergency Alert.....	167
23.15.1 Changing the Emergency Alert Setting.....	167

23.16 Enhanced Loudness.....	167
23.16.1 Changing the Enhanced Loudness Setting.....	167
23.17 History Sorting.....	168
23.17.1 Changing the History Sorting Setting.....	168
23.18 In Call Tones.....	168
23.18.1 Changing the In Call Tones Setting.....	168
23.19 Instant Personal Alert.....	169
23.19.1 Changing the Instant Personal Alert Setting.....	169
23.20 Location Change Accuracy.....	169
23.20.1 Changing the Location Change Accuracy Setting.....	170
23.20.2 Approximate (default).....	170
23.20.3 Changing the GPS Setting Option.....	170
23.21 Logout.....	170
23.21.1 Changing the Logout Setting.....	170
23.22 Message Alert.....	171
23.22.1 Changing the Message Alert Setting.....	171
23.23 Message Alert Tone.....	171
23.23.1 Changing the Message Alert Tone Setting.....	171
23.24 Missed Call Alert.....	172
23.24.1 Changing the Missed Call Alert Setting.....	172
23.25 My PTT Number.....	172
23.25.1 Viewing My PTT Number Setting.....	172
23.25.1.1 Missed Call Alert.....	172
23.26 Restore Defaults.....	173
23.26.1 Restoring the Defaults Settings.....	173
23.27 Use Bluetooth.....	173
23.27.1 Changing Bluetooth Setting.....	173
23.28 Vibrate Alert.....	174
23.28.1 Changing Vibrate Alert Setting.....	174
23.29 Vibrate Call.....	174
23.29.1 Changing Vibrate Call Setting.....	174
23.30 Voice Message Fallback.....	174
23.30.1 Changing the Voice Message Fallback Setting.....	174
23.31 Volume Boost.....	175
23.31.1 Changing Volume Boost Setting.....	175
<b>Chapter 24: Troubleshooting.....</b>	<b>176</b>
24.1 General.....	176
24.2 Activation Failures.....	176
24.3 Restarting an Unresponsive PTT Application.....	176

24.4 Application Asks Your to Enter an Activation Code..... 176

24.5 Application is not Visible during an Incoming Call..... 177

24.6 Call Failures..... 177

24.7 Calls are Always Heard in the Earpiece..... 177

24.8 Calls are Only Received from a Small Number of Groups..... 177

24.9 Unable to Change the Phone Number of a PTT Contact..... 178

24.10 Unable to Create/Update/Delete a Contact or Group..... 178

24.11 Unable to Hear Incoming Call..... 178

24.12 Unable to Send an Instant Personal Alert..... 178

24.13 Changing Your SIM Card..... 179

24.14 Explanation of Error Messages..... 179

    24.14.1 Loss of Data Network Connection..... 179

    24.14.2 User Busy..... 179

    24.14.3 User Unreachable..... 179

24.15 Login Failures..... 180

24.16 Presence Status Does Not Update..... 180

24.17 Quick Group Calls I Receive Are Shown in History as a One-to-One Call..... 180

24.18 Wi-Fi Connection Problems..... 180

**Chapter 25: Glossary..... 181**

    25.2 Alert Types..... 181

    25.3 Call Types..... 181

# List of Figures

Figure 1: Main Screen.....	31
Figure 2: History.....	32
Figure 3: Favorites.....	32
Figure 4: Contacts.....	33
Figure 5: Groups.....	34
Figure 6: Map.....	34
Figure 7: Call Screen.....	35
Figure 8: Place a PTT Talkgroup Call.....	60
Figure 9: Call Screen.....	61
Figure 10: PTT Broadcast Call Screen.....	62
Figure 11: History.....	63
Figure 12: Manual Dialing Screen.....	65
Figure 13: Nonbroadcaster Call History.....	67
Figure 14: Broadcaster Call History.....	67
Figure 15: Earpiece is On.....	68
Figure 16: Speaker is On.....	68
Figure 17: Call Screen - Speaker ON/OFF Button.....	68
Figure 18: Contact Context Menu.....	75
Figure 19: Emergency User Check.....	76
Figure 20: Contacts.....	86
Figure 21: History.....	87
Figure 22: Favorite Contacts.....	91
Figure 23: Contacts.....	95
Figure 24: Talkgroups.....	103
Figure 25: Talkgroup Scanning.....	111
Figure 26: Map.....	113
Figure 27: My Location.....	114
Figure 28: My Location.....	115
Figure 29: My Location.....	116
Figure 30: Groups with Location Capability.....	117
Figure 31: Talkgroup Member Location.....	117
Figure 32: View a Talkgroup Members Location Details.....	118
Figure 33: View a Talkgroup Members Location Details.....	119
Figure 34: Groups with Location Capability.....	120
Figure 35: My Location.....	120
Figure 36: Set Boundary Popover.....	121

Figure 37: Boundary Preview.....	121
Figure 38: Boundary ON.....	122
Figure 39: Set Boundary Popover.....	123
Figure 40: Map.....	126
Figure 41: Create Quick Group from Map.....	126
Figure 42: Create Quick Group from Map.....	127
Figure 43: Contact Context Menu.....	131
Figure 44: Talkgroup Context Menu.....	132
Figure 45: Text Message Box.....	132
Figure 46: Text Box.....	133
Figure 47: Edit Quick Text.....	133
Figure 48: Send Quick Text.....	134
Figure 49: Text Box.....	134
Figure 50: Select Quick Text.....	135
Figure 51: Enter Quick Text.....	135
Figure 52: Created Quick Text.....	136
Figure 53: Send Quick Text.....	136
Figure 54: Text Box.....	137
Figure 55: Edit Quick Text.....	137
Figure 56: Delete Quick Text.....	138
Figure 57: Delete Quick Text Confirmation.....	138
Figure 58: History.....	139
Figure 59: History Details.....	139
Figure 60: Transmitting a Live Video Stream to a Contact.....	152
Figure 61: Transmitting a Live Video Stream to a Quick Group.....	153
Figure 62: Transmitting a Live Video Stream to a Talkgroup.....	154



# List of Tables

Table 1: Menu Options.....	36
Table 2: Context Menus.....	37
Table 3: Actions Icons.....	41
Table 4: Unassigned Avatar Icons.....	43
Table 5: Assigned Avatar Icons.....	43
Table 6: Call Screen Icons.....	45
Table 7: Contacts Icon.....	46
Table 8: Emergency Icons.....	47
Table 9: History Icons.....	47
Table 10: Integrated Secure Messaging Icons.....	48
Table 11: Talkgroup Icons.....	49
Table 12: Map Icons.....	49
Table 13: Miscellaneous Icons.....	51
Table 14: Presence Icons.....	51
Table 15: Tab Icons.....	52
Table 16: Title Bar Icons.....	52
Table 17: Video Streaming Icons.....	53
Table 18: Tones.....	54
Table 19: Area-Based Warning Tones.....	79
Table 20: Call Permissions.....	103

# List of Procedures

Downloading the PTT Application .....	24
Activating on an iPhone .....	25
Activating on an iPhone using only Wi-Fi Network .....	26
Logging in the First Time .....	27
Setting Your Password .....	28
Confirming to Remember Your Password (Private Device) .....	28
Forgetting Your Password .....	29
Accessing the Switch User Option .....	29
Manually Logging into the PTT Application .....	30
Searching .....	40
Viewing User Information .....	58
Making One-to-One (1:1) Calls with Automatic Call Answer .....	59
Making One-to-One (1:1) Calls with Manual Call Answer .....	59
Making Talkgroup Calls .....	60
Making Quick Group Calls .....	61
Making Broadcast Calls .....	62
Placing a Call from Device Contacts .....	63
Calling from History .....	63
Calling from Missed Call Alert .....	64
Calling from Instant Personal Alert .....	64
Dialing a Manual Call to a PTT User .....	65
Receiving Calls .....	66
Declaring an Emergency .....	72
Receiving an Emergency Call .....	73
Receiving an Emergency Cancel Notification .....	73
Canceling Emergencies .....	74
Declaring an Emergency on Behalf of Another User .....	74
Canceling an Emergency from the Context Menu .....	76
Canceling an Emergency from Call Screen .....	77
Enabling Emergency User Check from Call Screen .....	77
Viewing Active Geofences .....	80
Sending an Alert .....	83
Receiving an Alert .....	83
Replying to a Missed Call Alert .....	84
Setting Self Presence .....	85
Making a PTT Call .....	88

Adding a PTT Contact (Optional) .....	88
Adding a Phone Contact (Optional) .....	89
Deleting History .....	89
Clearing All History .....	89
Deleting a Message .....	90
Adding Favorite Contacts .....	92
Removing Favorite Contacts .....	92
Adding Favorite Groups .....	93
Removing Favorite Groups .....	93
Searching Corporate Global Directory Contacts .....	95
Sorting the Contact List .....	95
Showing only Online Contacts .....	96
Showing all Contacts .....	96
Viewing Contact Details .....	97
Adding a New PTT Contact Manually .....	97
Importing a PTT Contact from the Device's Contact List .....	98
Adding a New Phone Contact Manually (Optional) .....	98
Importing a New Phone Contact from Device's Contact List (Optional) .....	99
Editing a Contact Name .....	100
Adding or Changing a Contact Avatar .....	100
Changing Contact Color .....	100
Deleting a Contact .....	101
Viewing Talkgroup Details .....	104
Adding a Talkgroup .....	105
Editing Talkgroup Details .....	105
Editing a Talkgroup Name .....	106
Adding One or More Members to a Talkgroup .....	106
Removing a Member from a Talkgroup .....	106
Renaming a Talkgroup Member .....	107
Adding or Changing a Talkgroup Avatar .....	108
Changing Talkgroup Color .....	108
Deleting a Talkgroup .....	108
Turning Scanning On or Off .....	110
Adding Talkgroups to Scan Lists .....	111
Removing Talkgroups from Scan Lists or Changing the Scanning Priority .....	112
Sending My Location or an Arbitrary Location to a Contact .....	114
Sending My Location or an Arbitrary Location to a Quick Group .....	115
Sending My Location or an Arbitrary Location to a Talkgroup .....	115
Viewing Talkgroup Member Locations .....	116

Viewing Talkgroup Member Location Details .....	117
Calling a Talkgroup Member .....	118
Sharing Your Location or an Arbitrary Location to a Talkgroup with Location Capability .....	119
Creating a Boundary .....	121
Recentering Boundary on the Map .....	122
Recentering the Map to your Location .....	123
Changing Boundary Settings .....	123
Changing Update Interval .....	124
Changing Active Boundary Time .....	124
Changing Notify Me Setting .....	124
Changing Notify Member Setting .....	125
Changing Initial Member Notification Setting .....	125
Creating a Quick Group from the Map .....	125
Adding Members to a Quick Group .....	127
Removing Quick Group Members .....	128
Sending a Text Message .....	131
Selecting Quick Text .....	133
Adding Quick Text .....	134
Deleting Quick Text .....	137
Receiving a Text Message .....	138
Saving an Image Message .....	140
Saving a Video Message .....	141
Receiving a Voice Message .....	142
Sending a Voice Message from History .....	142
Saving a File Message .....	143
Forwarding a Message to a Contact or Talkgroup .....	145
Forwarding a Message to a Quick Group .....	145
Replying to a Sender .....	146
Replying to Talkgroup (Talkgroup Messages) .....	146
Deleting a Message .....	146
Sending a Text Message from History .....	147
Copying a Text Message from History .....	147
Sending a Photo or a Video from History .....	148
Sending a Voice Message from History .....	148
Sending a File from History .....	149
Sharing my Location from History .....	149
Minimizing a Video Call .....	151
Making a Video Call to a Contact .....	151
Making a Video Call to a Quick Group .....	152

Making a Video Call to a Talkgroup .....	153
Receiving an Incoming Video Call .....	155
Receiving a Video Stream Request .....	155
Accessing the PTT Application Settings .....	161
Upgrading the PTT Application .....	161
Changing the Alert Repeat Setting .....	162
Changing the Alert Tone Setting .....	162
Changing the Allow Unconfirmed Video Transmission Setting .....	163
Changing the Audio Interaction Setting .....	163
Changing the Auto Answer Video Call Setting .....	164
Changing the Auto Download Setting .....	164
Changing the Background Mode Setting .....	164
Changing the Broadcast Call Confirmation Setting .....	165
Viewing the Phone Capacity Setting .....	165
Changing the Contact Sorting Setting .....	166
Viewing or Changing Your Display Name Setting .....	166
Viewing Your Emergency Contacts Setting .....	167
Changing the Emergency Alert Setting .....	167
Changing the Enhanced Loudness Setting .....	167
Changing the History Sorting Setting .....	168
Changing the In Call Tones Setting .....	168
Changing the Instant Personal Alert Setting .....	169
Changing the Location Change Accuracy Setting .....	170
Changing the GPS Setting Option .....	170
Changing the Logout Setting .....	170
Changing the Message Alert Setting .....	171
Changing the Message Alert Tone Setting .....	171
Changing the Missed Call Alert Setting .....	172
Viewing My PTT Number Setting .....	172
Changing the Missed Call Alert Setting .....	172
Restoring the Defaults Settings .....	173
Changing Bluetooth Setting .....	173
Changing Vibrate Alert Setting .....	174
Changing Vibrate Call Setting .....	174
Changing the Voice Message Fallback Setting .....	174
Changing Volume Boost Setting .....	175
Restarting an Unresponsive PTT Application .....	176

## Chapter 1

# Introduction and Key Features

The Push-to-Talk (PTT) application supports two modes: Standard PTT and PTT Radio. Your administrator assigns one of these modes. This document describes the Standard PTT Mode.

The Standard PTT application mode provides instant communication to individuals and talkgroups at the push of a button. Here is a brief description of the key features of Standard PTT Mode:

## Alerts

### Instant Personal Alert (IPA)

Allows you to send a message to another person asking for a callback.

### Missed Call Alert (MCA)

Shown whenever you miss an incoming PTT call because you were either in another PTT call or a regular cellular call.

For more information, see [Alerts on page 83](#).

### Dynamic Area-Based Talkgroups

Makes talkgroups dynamically available while in a geographical area.

For more information, see [Dynamic Area-Based Talkgroups \(Optional\) on page 104](#).

### Broadcast Talkgroup Calling

Allows designated talkgroup members to make high-priority one-way calls typically used for making important announcements to large talkgroups.



**NOTE:** In the PTT application, groups created by the administrator are also known as talkgroups.

For more information, see [Making Broadcast Calls on page 62](#).

### Contact and Talkgroup Management

PTT contacts and talkgroups can be centrally managed by an administrator (“administrator-managed”) or by you (“personal”).

For more information, see [Contacts on page 94](#) and [Talkgroups on page 102](#).



**NOTE:** In the PTT application, groups (either created by the subscriber or administrator) are also known as Talkgroups.

### Device ID Management

Allows login to the service with a username and password. It also allows multiple users to share a device.

For more information, see [User ID and Password User Login on page 27](#).

### Emergency Calling and Alert

Allows you to originate or receive an emergency call and receive an emergency alert.

For more information, see [Emergency Calling and Alert \(Optional\) on page 71](#).

### Favorites

You can manage your list of favorites for quick access to contacts and talkgroups.

For more information, see [Favorites on page 91](#).

### Integrated Secure Messaging

Allows a PTT user to send and receive secure text messages, multimedia content, and location information to and from other PTT users.

For more information, see [Integrated Secure Messaging on page 129](#).

### **Location Tracking**

Allows a supervisor with Location Capability, turned on by your administrator at the talkgroup level, to track talkgroup members' location.

For more information, see [Supervisor with Location Capability on page 116](#).

### **PTT Calling to Individuals and Talkgroups**

Allows instant communication to one or more people at the push of a button.

For more information, see [Making Calls on page 59](#).

### **Real-Time Presence**

Allows you to see whether your contacts are available and ready to receive calls before making a call. You can also indicate if you want to receive PTT calls to your contacts.

For more information, see [Real-Time Presence on page 85](#).

### **Supervisory Override**

Allows a supervisor to take the floor and speak at any time during a talkgroup call, even if someone else is speaking.

For more information, see [Supervisory Override on page 82](#).

### **Talkgroup Scanning with Priority**

Allows the phone of a subscriber to scan through a list of corporate talkgroups for calls. The higher priority talkgroup calls take precedence over lower priority talkgroup calls.

For more information, see [Talkgroup Scanning on page 110](#).

### **Video Streaming**

Allows you to stream your video in real-time to another user, typically a dispatcher.

For more information, see [Video Streaming \(Optional\) on page 150](#).

### **Wi-Fi support**

In addition to the broad coverage of PTT service provided by the cellular data network, you can use PTT over a home, office, or public Wi-Fi connection.

For more information, see [PTT over Wi-Fi on page 56](#).

## 1.1

# What's New in this Release?

Release 12.3 contains the following new features:

- Updated the Google and ESRI map supportability.
- Added the [Area-Based Warning Tones on page 79](#) section. These tones are added to the [Tones on page 54](#) section and Active Fences to the [Menu on page 36](#) section.
- Updated the [Emergency Calling and Alert \(Optional\) on page 71](#) section - Declare an Emergency - to include a note: You can perform an emergency initiation while in two-way call. When an emergency is declared the two-way call ends immediately.
- Updated the [Video Streaming \(Optional\) on page 150](#) section - Minimizing a Video Call - to include that a user can minimize ongoing streaming video calls to participate in other activities, for example, PTT, messaging, location, etc. The minimized video thumbnail on the PTT application can be dragged to any corner of the PTT application to allow users to perform other actions within the PTT app.
- Updated the [Video Streaming \(Optional\) on page 150](#) section - to updated screen shots which include a long talkgroup name and streamer ID which is displayed with “...” and underlined (to indicate actionable) when it cannot be displayed completely.
- Updated the [Settings on page 160](#) section - to include the Broadcast Call Confirmation setting.
- Updated the [Settings on page 160](#) section - to include the Voice Message Fallback setting.

## Chapter 2

# Application Installation and Getting Started

This section describes the steps you must take to install the Push-to-Talk (PTT) application and how to get started.

## 2.1

### Installation Prerequisites

You must ensure you have the following prerequisites before installation.

- A supported iOS smartphone .  
For more details, please check the website of your service provider.
- Wi-Fi Assist mode on your device should be turned off. Otherwise, it could interfere with the PTT operation. The setting is found in **Settings** → **Cellular** → **Wi-Fi Assist**.
- An Apple ID and iTunes account to download the application from the Apple iTunes store.
- The following link provides information about creating an Apple ID using iTunes.  
For more information, see [Creating a new Apple ID](#).

## 2.2

### Downloading the PTT Application

You can search for WAVE PTX, and download the application directly from your phone or iTunes.



**TIP:** Turn on your notifications and ensure that at least 10 notifications can be viewed in the Notification Center.

#### Procedure:

1. Search for the WAVE PTX application in the Apple App Store.
2. Download the application by touching the **GET** button and then the **INSTALL** button.  
The application downloads and installs automatically.
3. Once the download is complete, select **Open**.

## 2.3

### First-Time Activation

There are two ways to activate the PTT application. You can activate a phone using your service provider's network or Wi-Fi with an activation code.

- [Activating on an iPhone on page 25](#)
- [Activating on an iPhone using only Wi-Fi Network on page 26](#)



**NOTE:** If your administrator has provided you with a user ID and password, see [User ID and Password User Login on page 27](#).



## 2.3.1

## Activating on an iPhone

The first time you start the application after download, the application must “activate” with the PTT server. This activation process ensures that you are a PTT subscriber and that you are using a supported iPhone.

**Procedure:**

1. Tap on the **WAVE PTX** icon under **Apps** to launch the PTT application.

The **Activation Confirmation** dialog displays.

**NOTE:**

When prompted, you must **ALWAYS ALLOW** the application to access your location. The application does not login if the other options, such as **Only While Using the App**, **Use Once**, or **Don't Allow** are selected.

When prompted, you must **ALLOW** the application to access the microphone. When prompted, you must **ALLOW** the application to send you notifications. When prompted, you should **ALLOW** the application to use Bluetooth accessories.

2. Perform one of the following actions:
  - To activate to open the **Authentication Required** screen, tap **Yes**.
  - To cancel, tap **No**.
3. Tap **OK** to authenticate your subscription, an SMS must be sent. Do not modify the message contents. Press the **BACK** button to return to the app after sending the text.

Message and data rates may apply.

4. If activation fails, select **Exit** which closes the application and start over at [Step 1](#).
  - a. If your administrator has provided you with a User ID and Password, tap **Log In with Username** and continue to the [User ID and Password User Login on page 27](#) section.

The **End User License Agreement** page is displayed.

5. To activate the PTT service on your phone, read and accept the EULA.
6. If you agree to the EULA, tap **Accept** to activate the PTT service on the phone.

## 2.3.2

## Activating on an iPhone using only Wi-Fi Network

In situations where the cellular network is not available, you can activate the application over a Wi-Fi network in Airplane Mode. Your PTT service provider may allow this functionality. By default, iPhones automatically have Wi-Fi enabled.



**NOTE:** To activate over Wi-Fi, you must have an activation code provided by your administrator.

### Procedure:

1. To launch the PTT application, tap the **WAVE PTX** icon under **Apps**.

**NOTE:**

When prompted, you must **ALWAYS ALLOW** the application to access your location. The application does not login if the other options, such as **Only While Using the App**, **Use Once**, or **Don't Allow** are selected.

When prompted, you must **ALLOW** the application to access the microphone. When prompted, you must **ALLOW** the application to send you notifications. When prompted, you should **ALLOW** the application to use BT accessories.

2. Perform one of the following actions:
  - To continue the activation process, tap **Yes**.
  - To cancel the activation process, tap **No**.The **No Cellular Connection** dialog is displayed.
3. Perform one of the following actions:
  - To continue with the activation process, tap **Enter Code**.
  - To exit the activation process, tap **Exit**.
4. Enter the activation code received from your administrator.
5. Tap **OK** to activate or tap **Log In with Username**. A **Log In** screen displays.
6. If activation fails, select **Exit** which closes the application and start over at [Step 1](#).
  - a. If your administrator has provided you with a User ID and Password, tap **Log In with Username** and continue to the [User ID and Password User Login on page 27](#) section.
7. The **End User License Agreement** page is displayed.


You must read and accept the EULA to activate the PTT service on your phone.
8. To activate the PTT service on the phone if you agree to the EULA, tap **Accept**.


## 2.4

## User ID and Password User Login


There are steps that you must take to log into the Push-to-Talk (PTT) application when the PTT service is using device ID management or your network service provider is not the same as your PTT service provider.

Device ID Management increases security by requiring users to enter a user ID and password and supports the ability for multiple PTT users to share a device with another PTT user, for example, between shift workers. For more information on password requirements, see [Setting Your Password on page 28](#).

 **NOTE:** Your password may expire based on your service provider configuration.

 **NOTE:** The device ID Management feature is not available with the WAVE Commercial or WAVE Critical Communications feature set.

If your network service provider is not the same as your PTT service provider, you must select **Yes** when prompted. Failure to correctly answer this question may result in your PTT service not working correctly.

 **NOTE:** The Device ID Management supports release 9.1 PTT applications and later. It is required for cross-carrier users and tablet users.



Other than shift users, you can also use Device ID management to log into multiple devices a user may possess. For example, a tablet and phone owned by the same user. However, the PTT user can have only one active session at any point in time. Once logged in to one device, a session from another previously logged in device is deactivated.

The user ID is either an email ID or a PTT number.

## 2.4.1


### Logging in the First Time

#### Procedure:

1. Tap the **Username or email** field.
2. Using your on-screen keyboard, type the **PTT number or email**.
  -  **TIP:** Tap the **Refresh** icon (circular arrow icon) located in the upper right to clear all values entered.
3. Tap the **Password** field.
4. Enter your temporary password using your on-screen keyboard.
  -  **NOTE:** If you forgot your password, tap **Forgot Password?** link and go to [Forgetting Your Password on page 29](#).
5. Optional: On private devices, if you do not want to enter a user ID and password every time, tap the **Remember User** check box.
6. To log into the PTT application, tap the **Log In** button.
 

The **Update Password** screen is displayed.
7. Optional: If the application has been idle on the **Log In** screen for a while, you may see a timeout error. Enter your user ID and password again.

This security feature is intended to prevent unauthorized access.

 **NOTE:** Shared device session expires after 24 hours or time configured by your service provider from the first time you log in. You need to relogin each time the shared device session expires.

### 2.4.2

## Setting Your Password

During the first time login, you are prompted to enter your password. You must re-enter it each time you login.

**Prerequisites:** Ensure that your password meets the following requirements:

- At least 10 characters
- At least one lowercase letter (a-z)
- At least one uppercase letter (A-Z)
- At least one number (0-9)
- At least one of these special characters @\$%^&+=



**TIP:** Tap the **Refresh** icon (circular arrow icon) located in the upper-right to clear all values entered.

You must set your password the first time you log in. Follow this procedure to set your password to activate your account.

**Procedure:**

1. Tap the **New Password** field.
2. Type your password using your on-screen keyboard.
3. Tap the **Confirm Password** field and type your password using your on-screen keyboard.
4. To update your password, tap the **Submit** button.

### 2.4.3

## Confirming to Remember Your Password (Private Device)

When you set your username and password, you can choose to remember your username and password so that the next time you start the PTT application, it enables automatic login. This information is encrypted and stored on this device and automatically erased when another user logs in to this device.

**Procedure:**

1. Tap the **Username or email** field.
2. Using your on-screen keyboard, type your user ID or PTT number.
3. Tap the **Password** field.
4. Using your on-screen keyboard, type your password .
5. In the upper-right corner, tap **Save**.

You are logged into the PTT application.

### 2.4.4

## Subsequent Login

For each subsequent login, you need to enter your user ID and password. If the application has been idle on the **Log In** screen for a while, you may see a timeout error after entering your user ID and password. You must enter your user ID and password each time you login.

After you login, the server retrieves your contacts and talkgroups. It may take some time before your contacts and talkgroups are displayed. This behavior is normal.

If you have a user ID and password and have selected **Remember User** on the **Log In** screen, you do not need to enter your user ID and password again.

If you forget your password, see [Forgetting Your Password on page 29](#).

For more information on password requirements, see [Setting Your Password on page 28](#).

### 2.4.5

## Forgetting Your Password

Follow this procedure when you forget your password. A temporary password is automatically sent to your email address.



**NOTE:** You can get a temporary password from your administrator.

#### Procedure:

1. To return to the **Log In** screen, tap **Back to Login**.
2. Tap the **Username or email** field.
3. Using your on-screen keyboard, type your user ID or PTT number.
4. Tap **Submit**.

**Result:** An email is sent to you with a temporary password.

For more information about how to set a new password, see [Logging in the First Time on page 27](#).

### 2.4.6

## Switch User for Users with User ID and Password

If the PTT application is marked for `Private` use, there is an option to switch user where the currently logged in user is logged out and another end user can login to the same device.

Once you have selected the **Switch User** option, you are prompted for user ID and password each time you log out. The new user can choose **Remember User** mode again after successful login by selecting **Confirm Remember User**.



**NOTE:** Switch User functionality may not be available in certain cases, such as on a call, emergency call, or a device deactivation by an authorized user.

#### 2.4.6.1

### Accessing the Switch User Option

#### Procedure:

1. From the **Menu**, tap the **Switch User** option.

A message appears similar to the following: You are about to log out and re-enable username and password login. History stored only on this device will be lost. Continue?

2. Perform one of the following actions:
  - To log out, tap **Yes**.
  - To cancel, tap **No**.

## 2.5

# Tutorial

The tutorial provides helpful information about how to get started with the PTT application.

The application automatically launches the mobile browser and load the tutorial.

You can move between pages of the tutorial by swiping your finger right-to-left to move forward or left-to-right to move backward. You can also use the on-screen **Next** and **Previous** buttons shown on the edges of the screen.

## 2.6

# Login

To use the PTT service, you must connect to the PTT server. This process is called “login.” After you download and successfully register your connection with the server, the PTT application automatically starts and logs in each time you power on your phone. To make or receive PTT calls, you must log in.

It is possible for you to logout of the PTT service. While you are logged out, your presence status shows as *Offline* to others, and you cannot receive PTT calls or alerts. For more information, see [Logout on page 170](#).

### 2.6.1

## Manually Logging into the PTT Application

### Procedure:

1. Under **Apps**, tap the **WAVE** icon.  
A pop-up dialog displays to confirm that you want to login to the PTT application.
2. To login to the PTT application, tap **Yes**.

## 2.7

# Application Updates

iTunes & App Store Settings

When an update for the PTT application becomes available, your iPhone notifies you that there is an update available. When installing an update, it is recommended that you enable the **Auto-update apps** setting so that you always have the latest updates to the PTT application.

## 2.8

# In Application Update Notification

The PTT application may indicate that there is an update available.

You need to update the application; otherwise, it may not function properly. For more information, see [Important Message on page 161](#).


After updating, your PTT contacts and talkgroups are always retained. When the PTT application is updated, your settings are generally retained. In some rare cases of a major update to the application, your settings reset to their default values.

## Chapter 3


# Navigate the Push-to-Talk Application

You can navigate to the Push-to-Talk (PTT) application by using the touchscreen on your phone.

The screen consists of five major tabs: **History**, **Favorites**, **Contacts**, **Groups**, and **Map**.

 **NOTE:** Portrait mode is supported for handset and tablet devices. Landscape mode is only supported for tablet devices.

**Figure 1: Main Screen**



### 3.1

## History

The **History** screen displays all your conversation history of calls, contacts, talkgroups, alerts, messages (text, image, video, and voice). You can view your history, return a call, view messages, add contacts, delete history and messages, and forward any message to a contact or talkgroup.


The **History** screen contains two-level screens: the **Main** and **Details** screens. The **Main** screen contains a high-level view. The second-level screen contains the conversation details including a time stamp. Messages from the previous day are shown with the date stamp `YESTERDAY`. The Date/Time (12/24 hour display) format follows the device setting for internationalization.

Each top-level history entry displays the conversation type, such as `Broadcast Call`, `Group Call`, `Quick Group Call`, `Private Call`, contact name, group name or participant names for quick groups, `<message text preview>` (if a text message), `Voice Message`, `File`, `Image`, `Location`, and `Video`.

For more information on how to manage your History, see [History on page 87](#).

Also, for information on the History icons, the [History Icons on page 47](#).

**Figure 2: History**



### 3.2

## Favorites


The **Favorites** screen displays your favorite PTT contacts and talkgroups.

You can quickly start a PTT call to your favorites.

For more information on how to view, add, and remove your favorite contacts, see [Favorites on page 91](#).

For information on the Favorites icons, see [Icons on page 41](#).

**Figure 3: Favorites**





### 3.3

## Contacts

The **Contacts** tab displays your PTT contacts and allows you to search for contacts, select a contact, displays the presence for each contact, start a quick group call, start a PTT call, or send an alert or message.


If turned on by an administrator, you can also add PTT contacts and create personal PTT talkgroups.

Icons may display to indicate if you have supervisory permissions for that user .

For more information on how to view, add, edit, and delete your personal contacts, see [Contacts on page 94](#).

For information on the Contacts icons, see [Icons on page 41](#).

**Figure 4: Contacts**




### 3.4

## Talkgroups

The **Talkgroups** tab displays your talkgroups and allows you to search for talkgroups or start a PTT talkgroup call. If turned on by an administrator, you can also create, change or delete your personal PTT talkgroups here. Icons are shown next to the talkgroups which you are a broadcaster or supervisor. Icons also indicate Interop talkgroups, location tracking, and talkgroup scan priority.

For more information on Talkgroup icons and how to view, add, edit, and delete your personal talkgroups, see [Talkgroups on page 102](#) and [Icons on page 41](#).

**Figure 5: Groups**



### 3.5


## Map

The **Map** screen displays your location and allows you to send your location to others. It also displays the location of your talkgroups members for which you are a supervisor and allows you to search for talkgroups or start a PTT talkgroup call.

For more information on how to search the map, recenter the map, send your location to a contact, quick group, or talkgroup, track talkgroup members, and set the boundary of the tracked group, see [Map on page 113](#).

For information on the Map icons, see [Map Icons on page 49](#).

**Figure 6: Map**



### 3.6

## Call Screen

The **Call** screen is the main screen for communication.

You make a call, make a quick group call, turn on or off the speaker, send a text message, send your location, send an alert, send a photo, and record and send a voice message.


For more information on how to make and receive calls, see [Make and Receive PTT Calls on page 59](#).

For more information on how to send or receive streaming video, see [Video Streaming \(Optional\) on page 150](#).

For more information on how to send or receive Integrated Secure Messaging, see [Integrated Secure Messaging on page 129](#).

For information on the **Call** screen icons, see [Icons on page 41](#).

**Figure 7: Call Screen**



### 3.7

## Menu

On the **Main** screen, you can access the menu options by tapping the **Menu** icon in the upper-left-hand corner.

#### 3.7.1

### Menu Options

The following table describes the Menu options and is listed by name and description.

**Table 1: Menu Options**

Name	Description
Presence Status	Displays your presence status. Either 'Available,' 'Do Not Disturb,' or 'Offline.' Offline icon also displays your 'No Connection' presence status. For more details, see the <a href="#">Real-Time Presence on page 85</a> section.
Active Fences	Tap to access the active fences. Displays a list of active fences. For more details, see <a href="#">Area-Based Warning Tones on page 79</a> section.
Talkgroup Scan (Available, if enabled)	Tap the Talkgroup Scan toggle from <b>OFF</b> to <b>ON</b> . For more details, see the <a href="#">Talkgroup Scanning on page 110</a> section.
Manual Dial	Tap to manual dial a contact. For more details, see the <a href="#">Dialing a Manual Call to a PTT User on page 65</a> section.
Enhanced Loudness	Tap to increase the perceived audio volume of PTT calls using the speakerphone. This feature is only available on supported devices. For more details, see the <a href="#">Enhanced Loudness on page 167</a> section.
Settings	Tap to access the application settings. For more details, see the <a href="#">Settings on page 160</a> section.
Tutorial	Tap to access the application tutorial.
About	Tap to access more information on the application.

### 3.8

## Actions

The **Actions** soft buttons located at the top and the bottom of the screen let you call, alert, manually dial a phone number, add a new contact or talkgroup, and more.

For more information on **Actions**, see [Actions Icons on page 41](#).

3.9

## Context Menus

Context or pop-up menus are available throughout the application based on the features provisioned for the user. To display these menus, you can touch and hold the selected history entry, favorite, contact, talkgroup, or talkgroup details.

**Table 2: Context Menus**

Location	Description	Condition	
Call screen/History Details Camera Option	Take Photo	No conditions	
	Record Video		
	Image Gallery		
	Video Gallery		
Contacts	Contact Details	All contacts	
	Delete Contact	User-managed contacts	
	Send Text	All contacts	
	My Location	All contacts	
	Send Instant Personal Alert	All contacts	
	Send Document	All contacts	
	Camera	Take Photo	All contacts
		Record Video	All contacts
		Image Gallery	All contacts
		Video Gallery	All contacts
	Record Voice	All contacts	
	History	All contacts	
	Details	All contacts	
Contact Details	Delete Contact	User-managed contacts	
Favorite Contacts	Remove Favorite	All contacts	
	Send Text	All contacts	
	My Location	All contacts	
	Send Instant Personal Alert	All contacts	
	Send Document	All contacts	
	Camera	Take Photo	All contacts
		Record Video	All contacts
		Image Gallery	All contacts
		Video Gallery	All contacts

Location	Description	Condition	
	Record Voice	All contacts	
	History	All contacts	
	Details	All contacts	
Favorite Groups	Remove Favorite	All entries	
	Send Text	All groups	
	My Location	All groups	
	Send Instant Personal Alert	All groups	
	Send Document	All groups	
	Camera	Take Photo	All groups
		Record Video	All groups
		Image Gallery	All groups
		Video Gallery	All groups
	Record Voice	All groups	
	History	All groups	
	Details	All groups	
	Scan List	Set Priority 1	Administrator-managed group
Set Priority 2		Administrator-managed group	
Set Priority 3		Administrator-managed group	
No Priority		Administrator-managed group	
Remove		Administrator-managed group	
History	Add Contact	Manual dial call or received a call from a PTT user not in your contact list	
	Clear All	All history entries	
	Delete History	All history entries	
History Details	Forward to Contact	All messages	
	Forward to Quick Group	All messages	
	Forward to Group	All group messages	
	Reply to Sender	All messages	
	Delete Message	All messages	
	Copy Message	All text messages	
Groups	Group Details	All entries	

Location	Description	Condition
	Delete Group	User-managed group
	Send Text	All groups
	My Location	All groups except broadcast
	Send Instant Personal Alert	All groups except broadcast
	Send Document	All groups except broadcast
	Take Photo	All groups except broadcast
	Record Video	All groups except broadcast
Camera	Image Gallery	All groups except broadcast
	Video Gallery	All groups except broadcast
	Record Voice	All groups except broadcast
	Set Priority 1	Administrator-managed group
	Set Priority 2	Administrator-managed group
Scan List	Set Priority 3	Administrator-managed group
	Normal Priority	Administrator-managed group
	Remove	Administrator-managed group
Group Details	Rename Member	User-managed group
	Remove Member	User-managed group
	Delete Contact	User-managed group
	Delete Group	User-managed group

### 3.10

## PTT Button

There are two Push-to-Talk (PTT) buttons available: the external PTT button and the on-screen soft PTT button.

#### 3.10.1

### External PTT Button

A PTT accessory can be used by the PTT application. While the PTT application is not visible, you can always press this button to bring the application to the foreground of the screen. With the PTT application in the foreground, you can use this button to start a PTT call or take and release the floor during a PTT call.



**NOTE:** On iOS 12.4 or higher devices, you can only initiate while the application is open (visible). To initiate a call using a PTT accessory button, you must open the application first.

For information on the **Bluetooth Low Energy** button, see [Accessories and Bluetooth Use on page 158](#).



**NOTE:** This behavior assumes that Background Calling is turned off. For more information on Background Calling, see [Call Behavior in Background](#).

#### 3.10.2

### On-screen Soft PTT Button

Whenever you initiate or are in a PTT call, you see an on-screen **PTT** button.

You can take the floor and speak during a call by touching and holding the on-screen button. You can release the floor and allow others to speak by releasing your finger from the on-screen button.

### 3.11

## Navigate to the Previous Screen

To navigate to the previous screen, you can tap the **Back** button located on the phone. Some screens within the application also have an on-screen button to return to the previous screen.

### 3.12

## Scrolling

If you are viewing a list that has more entries than can be displayed on one screen, you can touch the list and drag your finger up or down to view the rest of the list.

### 3.13

## Searching

Searching allows you to quickly find history, favorites, contacts, talkgroups, or locations, including addresses, points of interest, and cross streets. The search results are displayed in a list for you to scroll and choose the desired result quickly.

#### **Procedure:**

1. Touch within the search bar to bring up the on-screen keyboard.

As you type, contacts or talkgroups names containing the letters or numbers entered displays automatically.



2. Tap the searched result to open it.



**NOTE:** You must be on the respective **History, Favorites, Contacts, Talkgroups, or Map** screen to search. The search function does not search outside the selected screen.

### 3.14

## Icons

The icons available throughout the application are based on the features provisioned for the user. Refer to the following sections on different type of icons:





- [Actions Icons on page 41](#)
- [Avatar Icons on page 43](#)
- [Call Screen Icons on page 45](#)
- [Contacts Icon on page 46](#)
- [Emergency Icons on page 47](#)
- [History Icons on page 47](#)
- [Integrated Secure Messaging Icons on page 48](#)
- [Talkgroup Icons on page 49](#)
- [Map Icons on page 49](#)
- [Miscellaneous Icons on page 51](#)
- [Presence Icons on page 51](#)
- [Tab Icons on page 52](#)
- [Title Bar Icons on page 52](#)
- [Video Streaming Icons on page 53](#)












#### 3.14.1

## Actions Icons

The **Action** icon buttons are located at the top and the bottom of the screen.

**Table 3: Actions Icons**

Icon	Title	Description
	<b>Add</b>	Displayed on the <b>Contacts, Favorites, Groups, and Quick Text</b> . You can add contacts, favorites, groups, or a quick text by tapping this button.
	<b>Alert</b>	You can send Instant Personal Alert (IPA) to a contact by tapping this button.
	<b>Attach File</b>	You can attach a file to send as an attachment by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Camera</b>	You can choose from taking a photo, video, or selecting a file in the gallery by tapping this button. Requires the



Icon	Title	Description
		Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Cancel</b>	You can cancel current action and go back to the previous screen by tapping this button.
	<b>Delete</b>	You can delete the contact, group, and more by tapping this button.
	<b>Details</b>	You can access the contact details by tapping this button.
	<b>Filter ON</b>	You can toggle filter <b>ON</b> to <b>OFF</b> (default) by tapping this button.
	<b>Filter OFF</b>	You can toggle filter <b>OFF</b> (default) to <b>ON</b> by tapping this button.
	<b>Gallery</b>	You can save to your device by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Location</b>	You can share your location by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Send Message</b>	You can send a text message by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Forward</b>	You can forward an image or video by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Save</b>	You can save current contact or group by tapping this button.
	<b>Voice Message</b>	You can send a recorded voice message by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.

3.14.2










## Avatar Icons















You can use the Avatar icons to understand when avatars are assigned.



**Table 4: Unassigned Avatar Icons**

Icon	Title	Description
	<b>Contact</b>	The default contact icon that is used on the <b>Contact List</b> screen when there is no avatar assigned.
	<b>Group</b>	The default group icon used on the <b>Group List</b> screen when there is no avatar assigned.

**Table 5: Assigned Avatar Icons**


Icons	Name
	<b>Airplane</b>
	<b>Book</b>
	<b>Car</b>
	<b>Construction</b>
	<b>Delivery</b>
	<b>Desktop PC</b>
	<b>Dispatcher</b>
	<b>Driver</b>
	<b>Envelope</b>

Icons	Name
	Field Service
	Flower
	Front Desk
	Housekeeping
	Laptop
	Medical
	Notepad
	PTT Phone
	Room Service
	Security
	Supervisor
	Telephone
	Tree
	Truck










Icons	Name
	Warehouse
	Worker








### 3.14.3

## Call Screen Icons

 **NOTE:** For more information on Integrated Secure Messaging icons, see the [Integrated Secure Messaging Icons on page 48](#) section.

**Table 6: Call Screen Icons**




Icon	Title	Description
	Cancel Call	You can cancel a private call by tapping this button.
	End Call	You can end the current PTT call by tapping this button.
	Call Accept	You can accept a call by tapping this button.
	Call Contact	You can call a contact by tapping this button.
	Call Favorites	You can open your favorites to make a call by tapping this button.
	Access Channels/Zones	You can open the folder channels and zones by tapping this button.
	Group Location	You can access the map for the group by tapping this button. Requires the Geofencing and Geolocation feature to be turned on by your administrator
	In-Call Add Participant	You can add participants to make a temporary group before making a PTT call by tapping this button.
	Contact/Group Details	You can access the details information of the group or contact by tapping this button.

Icon	Title	Description
	<b>Instant Personal Alert</b>	You can send IPA to the contact by tapping this button.
	<b>Listen-only</b>	Listen-only call indicator.
	<b>Idle</b>	<b>PTT</b> button Indicates idle state and the floor is available.
	<b>Floor Taken</b>	<b>PTT</b> button Indicates the floor taken state.
	<b>Acquired</b>	<b>PTT</b> button Indicates the acquired state and you are ready to speak.
	<b>Speaker ON</b>	You can toggle the Speaker from the <b>ON</b> default to <b>OFF</b> by tapping this button. When the speaker is off, PTT calls are heard through the earpiece of the phone. For more information, see <a href="#">Turning the Speaker On/Off on page 68</a> .
	<b>Speaker OFF</b>	You can button to toggle from <b>OFF</b> to <b>ON</b> by tapping this button. When the speaker is off, PTT calls are heard through the earpiece of the phone. For more information, see <a href="#">Turning the Speaker On/Off on page 68</a> .

#### 3.14.4

## Contacts Icon

Table 7: Contacts Icon





Icon	Title	Description
	<b>Cellular Call</b>	Located in the contact details. You can make a cellular call by tapping this button.
	<b>iDEN Radio</b>	iDEN radio user indicator.
	<b>Interop</b>	Interop user indicator.

For additional Contacts icons, see [Presence Icons on page 51](#).

3.14.5

## Emergency Icons




Table 8: Emergency Icons

Icon	Title	Description
	<b>Emergency</b>	You can initiate an emergency by touching and holding this button, which is located at the bottom of most screens. Requires the Emergency Services to be turned on by your administrator. For more information, see <a href="#">Emergency Calling and Alert (Optional)</a> on page 71.
	<b>Cancel Emergency State</b>	Displays when you cancel an emergency. You can cancel the emergency by swiping the slider to the right. Requires the Emergency Services to be turned on by your administrator.
	<b>Declare Emergency State</b>	Displays when you declare an emergency. You can declare an emergency by swiping the slider to the right. Requires the Emergency Services to be turned on by your administrator.
	<b>Emergency Talker</b>	Indicates when a talker is in an emergency.

3.14.6

## History Icons










Table 9: History Icons

Icon	Title	Description
	<b>History Details</b>	You can access history details for contact, quick group call, or group by tapping this button.
	<b>Unread</b>	Indicates that there is an unread message. You can read the message by tapping this button. The unread message indicator disappears when you tap the <b>History Details</b> button to reply to the message. Requires the Integrated Secure Messaging feature to be turned on by your administrator.
	<b>Voice Message</b>	Indicates the attachment is a voice message. You can play the message by tapping this button. Requires the Integrated Secure Messaging feature to be turned on by your administrator.

3.14.7

## Integrated Secure Messaging Icons

Table 10: Integrated Secure Messaging Icons










Icon	Title	Description
	Camera	You can tap to choose from taking a photo, shooting a video, or selecting from the gallery.
	File Message	You can tap to choose a file from your device to send to a contact. For more information on File Messaging, see <a href="#">File Messaging on page 143</a> .
	Instant Personal Alert	You can tap to send IPA to the contact.
	Message	You can tap to send a text message to the contact or group.
	Play	You can tap to start playback of a voice message.
	Quick text access	You can tap to access quick text list.
	Voice Message	You can tap to record a voice message.
	Record	You can press and hold to start recording a voice message.
	Send text message	You can tap to send text message.
	Share Location	You can tap to share location to the contact or group.
	Stop	You can tap to stop playback of the voice message.
	Recording Voice	You can release to stop recording a voice message.



3.14.8

## Talkgroup Icons

Table 11: Talkgroup Icons















Icon	Title	Description
	<b>Broadcast Talkgroup</b>	Broadcast Talkgroup indicator.
	<b>Boundary Active</b>	Indicates that location sharing for talkgroup members is turned on, and the boundary is active. Requires Supervisor Location Capabilities to be turned on by your administrator.
	<b>Location Sharing Group</b>	Indicates that group member locations can be viewed and no boundary is active for the group. Requires Supervisor Location Capabilities to be enabled by your administrator.
	<b>Interop Talkgroup</b>	Interop talkgroup indicator.
	<b>Scan List No Priority</b>	Scan List No Priority indicator.
	<b>Scan List Priority 1</b>	Scan List Priority 1 indicator.
	<b>Scan List Priority 2</b>	Scan List Priority 2 indicator.
	<b>Scan List Priority 3</b>	Scan List Priority 3 indicator.
	<b>Group Supervisor</b>	Supervisor group indicator.

3.14.9

## Map Icons

Table 12: Map Icons









Icon	Title	Description
	<b>Call</b>	You can tap to initiate a PTT call to the talkgroup member.

Icon	Title	Description
	<b>Talkgroup Member Location</b>	Indicates the location of a talkgroup member whose presence is unknown.
	<b>Map Recenter</b>	You can tap to recenter the map to where you are. Also, you can tap on the <b>Set Boundary Settings</b> to recenter the map to the active boundary.
	<b>Map Boundary Enable</b>	You can tap to turn on the boundary and open.
	<b>Offline Talkgroup Location</b>	A map pin that indicates the location of a talkgroup member whose presence is offline.
	<b>Available Talkgroup Location</b>	A map pin that indicates the location of a talkgroup member whose presence is available.
	<b>Center Location</b>	A map pin that indicates an arbitrary location or the intended center location of a boundary.
	<b>DND Talkgroup Location</b>	A map pin that indicates the location of a talkgroup member whose presence is DND.
	<b>Quick Group Location</b>	A map pin that indicates the location of selected members of a quick group.
	<b>My Location Mark</b>	The <b>My Location Mark</b> pin that indicates your location on the map.
	<b>Share</b>	You can tap to share the location.
	<b>Boundary Settings</b>	You can tap to access the boundary settings. For more information, see <a href="#">Boundary Settings on page 123</a> .
	<b>Tracked Group Selector</b>	You can tap to choose a talkgroup to view the location or turn on or off the boundary alerts.
	<b>Map Boundary Enable</b>	You can tap to turn on the boundary and open.
	<b>Quick Group Selector</b>	You can tap to create a quick group.

3.14.10

## Miscellaneous Icons



Table 13: Miscellaneous Icons


Icon	Description
	Check box <b>Off</b> .
	Check box <b>ON</b> .
	<b>Favorite</b> button (unselected) You can tap to toggle favorite <b>ON</b> . Indicates contact or group is not a favorite.
	<b>Favorite</b> button (selected) You can tap to toggle favorite <b>OFF</b> . Indicates contact or group is a favorite.
	<b>Radio</b> button off icon You can tap to toggle to the on state.
	<b>Radio</b> button on icon You can tap to toggle to the off state.
	<b>Clear Search text</b> button You can tap to cancel current inputted text and search action.
	<b>Search</b> icon For more information, see <a href="#">Searching on page 40</a> .

3.14.11

## Presence Icons

Table 14: Presence Icons

Icon	Title	Description
	<b>Available</b>	A PTT contact's presence status is <code>Available</code> or my presence status.
	<b>Do Not Disturb</b>	A PTT contact's presence status is <code>Do Not Disturb</code> or my presence status.







Icon	Title	Description
	Offline	A PTT contact's presence status is <i>Offline</i> or my presence status when the phone is not connected to the server.

### 3.14.12

## Tab Icons

The following table lists the tab icons listed by icon and description.



**Table 15: Tab Icons**





Icon	Description
	Contact tab.
	Favorite tab.
	Group tab with Talkgroup Scan on.
	Group tab with Talkgroup Scan off.
	History tab.
	Map tab. Requires Geolocation to be turned on by your administrator.

### 3.14.13

## Title Bar Icons

**Table 16: Title Bar Icons**








Icon	Title	Description
	Back	You can tap to go back to the previous screen.
	Cancel	You can tap to cancel the operation and return to the previous screen.

Icon	Title	Description
	<b>Details</b>	You can tap to view the details.
	<b>Edit</b>	You can tap to edit.
	<b>Drop-down</b>	You can tap to change self-presence.
	<b>Save</b>	You can tap to save the current operation.

3.14.14

## Video Streaming Icons

Table 17: Video Streaming Icons

Icon	Title	Description
	<b>Microphone ON</b>	You can tap to toggle microphone from the <b>ON</b> to <b>OFF</b> state.
	<b>Microphone OFF</b>	You can tap to toggle microphone from the <b>OFF</b> to <b>ON</b> state.
	<b>Speaker ON</b>	You can tap to toggle speaker from the <b>ON</b> to <b>OFF</b> state.
	<b>Speaker OFF</b>	You can tap to toggle speaker from <b>OFF</b> to <b>ON</b> state.
	<b>Stop Video Streaming</b>	You can tap to stop video streaming transmission.
	<b>Start Video Streaming</b>	You can tap to start broadcasting video streaming, if previously stopped.
	<b>Switch Camera</b>	You can tap to toggle camera from rear (default) to front.

### 3.15

## Tones

The PTT application plays tones to indicate various conditions. The following table lists the tones and description.

**Table 18: Tones**

Name	Description
Activation Tone	Played upon successful activation.
Alert (IPA/MCA) Tone	Played by the handset when an incoming Instant Personal Alert is received or a Missed Call has occurred. Four tones are required as this tone is user-selectable.
Area Warning Tone - Blast Tone	Played to indicate when a user is notified to evacuate the mining site. The tone is played to escalate the priority of evacuation. For iOS, the app is suspended when put into the background and cannot play the periodic tone.
Area Warning Tone - Emergency Tone	Played to indicate when a user is notified to immediately evacuate the mining site for an impending blast. For iOS, the app is suspended when put into the background and cannot play the periodic tone.
Area Warning Tone - Evacuation Tone	Played to indicate when a user is notified to immediately evacuate the mining site for an impending blast. For iOS, the app is suspended when put into the background and cannot play the periodic tone.
Attention Tone	Played to indicate a pop-up dialog message.
Emergency Alert Tone	Played when emergency alert is received.
Emergency Alert - Originator Tone	Played when an emergency alert is initiated.
Emergency Call Tone	Played upon receiving emergency call.
Emergency Cancel Tone	Played when an emergency is canceled.
Emergency Fail Tone	Played if emergency cannot be declared or if emergency call cannot originate.
Error (Floor Busy) Tone	Played to indicate the user cannot take the floor.
Floor Acquired (Grant) Tone	Played after the user presses the PTT button to indicate it is ready for talking.
Floor Free Tone	Played to listeners on a PTT call to indicate the talker has released the floor.
Floor Released Tone	Played to the user after releasing the PTT button to indicate the floor is released. (Default is OFF)
Floor Revoke Tone	Played five seconds before the floor is revoked. The same tone is also played when the actual floor is revoked.
Floor Unavailable (Bong) Tone	Played when a user tries to get a floor that is already acquired or the called party is unavailable. An appropriate visual indication is displayed for both scenarios.

Name	Description
Incoming Call (Talk Hint) Tone	Played to listeners to announce the start of a PTT call (first volley only).
Incoming Phone Call Tone	Played when there is an incoming 2-way phone call. Tone is repeated every 3 seconds.
Incoming Private PTT Call (Manual Answer) Tone	Played when there is an incoming PTT private call. Tone is repeated every 3 seconds.
Incoming Video Tone	Played when there is an incoming video alert waiting for user to accept. Alert is repeated every 5 seconds while alert is waiting for user action.
Phone Call Progress Tone	Played to caller while waiting for telephony call to answer. Tone is repeated every 3 seconds.
Success Tone	Played upon successful activation: valid key press.
Voice Message Recording Tone	Played when recording voice message (voice message fall-back).

## Chapter 4

# Network Connectivity

This section describes the network connectivity associated with the Push-to-Talk (PTT) service.

### 4.1

## PTT over 4G LTE networks

Using PTT over 4G LTE networks ensure the fastest speed, least delay, best voice quality, and best performance during PTT calls and when using PTT services.

You must use of PTT over cellular data networks less than 4G may be restricted based on a system-wide configuration. While the application is restricted, the behavior is the same as having no network connection and a `No Connection` message displays. You may be provided an audible and visual indication of loss of connection to the network based on the application settings. Upon detection of 4G, the application will reconnect to the PTT server and may give an audible indication based on the application settings. The tones are user-configurable in the application settings.



**NOTE:** Use of PTT over cellular data networks less than 3G is not recommended because the slower data rates cause a considerable amount of delay, which can cause a degradation in voice quality or even dropped calls.

### 4.2

## PTT over Wi-Fi

Using PTT over Wi-Fi can provide effective in-building coverage and leveraging Wi-Fi access points within organizations and hotspots.



**NOTE:** By default, the PTT application will use Wi-Fi when it is available.

#### 4.2.1

## Switching between Cellular Data Networks and Wi-Fi Networks during a Call

Your phone may automatically switch between the cellular data network and a Wi-Fi network depending on the availability of a Wi-Fi connection. The switching is known as a handover between networks.

If you are on a PTT call when your phone switches between the cellular data network and a Wi-Fi connection (or vice versa), your PTT call automatically reconnects after the handover. During a handover, the PTT application temporarily loses connection with the servers. When this occurs, you experience a slight loss of call audio. You are notified of this condition by two short tones. The tones are dependent on the Network Up/Down Tones setting and the Network Loss Tone Repeat Setting. Once the handover is complete, and the PTT application reconnects to the data network, your call automatically continues. The handover may take more than a few seconds. In this case, a call in progress may not automatically reconnect. If this happens, you can call back from PTT history.



#### 4.2.2

## Authenticated Wi-Fi Connections

The PTT application can be used at any Wi-Fi location provided your phone has access to the Internet through that Wi-Fi network.

In hotels or other places that provide Wi-Fi access only to patrons, some authentication, such as a password, may be required to access the Internet, even though the phone is connected to the Wi-Fi network. In this case, PTT service is unavailable and you cannot place or receive PTT calls until you either turn off Wi-Fi or launch your mobile browser and enter the password provided by the Wi-Fi service provider.

## Chapter 5

# User Information Display

User Information Display provides an avatar, display name, availability status, PTT number, and a profile name if enabled.

## 5.1

### Viewing User Information


**Procedure:**

1. In the upper-left corner of the display, select the **Main** menu located.  
The **Menu** options display.
2. Located opposite the available status, select the **Information** icon.  
The User Information displays.

## Chapter 6

# Make and Receive PTT Calls

This chapter describes how to make and receive Push-to-Talk (PTT) calls.

 **NOTE:** On iOS 12.4 or higher devices, a call can be initiated only while the application is open (visible). To start a call using a **PTT** accessory button, you must open the application first. To receive an incoming call, you must bring the application to the foreground.

## 6.1


### Making Calls

This section describes the steps to make Push-to-Talk (PTT) calls.

#### 6.1.1

### Making One-to-One (1:1) Calls with Automatic Call Answer

#### Procedure:

1. From the **Contacts**, tap the contact to select the one you want to start a PTT call.  
The **Call** screen is displayed including the name of the contact that you are calling in the Call Status.
2. Press and hold the PTT button.  
A private one-to-one PTT call starts, a chirp tone is heard and the **PTT** button changes color indicating you have taken the floor.
3. Begin speaking.  
 **NOTE:** Some corporations may automatically assign a talkgroup called `all_subscribers_group`. This talkgroup has all the PTT subscribers from your corporation.
4. To allow the other person on the call to take the floor and speak, release the PTT button.
5. To end the call, tap the **End Call** button.

#### 6.1.2


### Making One-to-One (1:1) Calls with Manual Call Answer

#### Procedure:

1. From the **Contacts**, tap the contact to select the one you want to start a PTT call.  
The **Call Screen** displays including the name of the contact that you are calling in the Call Status.
2. Press and hold the PTT button.  
The **Call Screen** changes to a ringing state. A progress tone is heard, and the **PTT** button changes color indicating the other user is being alerted. Once the call is accepted, the other user will either talk or you can press and hold the PTT button to talk.

3. Talk when you hear the chirp tone and see the **PTT** button change color indicating you have taken the floor.

If the call is rejected, the floor returns to idle state.

 **NOTE:** Some corporations may automatically assign a talkgroup called `all_subscribers_group`. This talkgroup has all the PTT subscribers from your corporation.

4. To end the call, tap the **End Call** button.

### 6.1.3


## Call a Contact that is Offline or has a Do Not Disturb (DND) Status

If the person you are trying to call has a presence status of `Offline`, you see the following error message: The contact you are trying to call is unavailable. Please try again later.

Similarly, if the person you are trying to call has a presence status of `Do Not Disturb`, you see the following message: The Contact you are trying to call is in 'Do Not Disturb' status. Please try again later.

### 6.1.4


## Making Talkgroup Calls

 **NOTE:** Some corporations may automatically assign a talkgroup called `all_subscribers_group`. This talkgroup has all the PTT subscribers from your corporation.

### Procedure:

1. From the Talkgroups, tap the talkgroup to select the one you want to start a PTT call. The **Call** screen displays the name of the talkgroup that you are calling in the Call Status.

**Figure 8: Place a PTT Talkgroup Call**



2. Press and hold the **PTT** button displayed on the screen.  
A talkgroup PTT call starts, a chirp tone is heard, and the **PTT** button changes color indicating you have taken the floor.
3. Begin speaking.
4. To take the floor and speak, release the **PTT** button to allow other members of the call.
5. To end the call, tap the **End Call** button.

### 6.1.5


## Making Quick Group Calls

You can make a quick group call after selecting your first contact to call by selecting the **Add Participants** button from the **Call** screen, and then selecting additional contacts to add to your quick group.

### Procedure:

1. From the **Contacts**, select your first contact to call.  
The **Call** screen displays.


**Figure 9: Call Screen**



2. Tap the **Add Participants** button.
3. Select up to nine contacts to add to the quick group call.
4. When completed, in the upper right tap, the **Save** button located.
5. Press and hold the **PTT** button.  
A quick group call starts, a chirp tone is heard and the **PTT** button changes color indicating you have taken the floor.
6. Begin speaking.
7. To take the floor and speak, release the **PTT** button to allow other members of the call.
8. To end the call, tap the **End Call** button.

## 6.1.6 Making Broadcast Calls


Broadcast calls make it possible to deliver important information quickly to a large talkgroup. Only designated talkgroup members, called broadcasters, may initiate a one-way high-priority call to a talkgroup with up to 500 members (based on configuration). A broadcast talkgroup call preempts any ongoing PTT call and receiving talkgroup members cannot call back or reject the call. Once a broadcaster takes the floor, the broadcaster is not preempted by another broadcaster. You only see a broadcast talkgroup if you are a designated broadcaster by your administrator.

 **NOTE:** Broadcast talkgroup calls interrupt ongoing PTT calls for the talkgroup members and they hear the call even if they have Do Not Disturb turned on. These calls also override the Do Not Disturb (DND) status if your administrator has set the talkgroup to do so.

### Procedure:

1. Tap the broadcast talkgroup you want to call.


The broadcast talkgroup is identified in the talkgroup list by the broadcast talkgroup icon.

 **NOTE:** If the Broadcast Call Confirmation setting is on, you receive the following confirmation dialog. For more information, see [Broadcast Call Confirmation on page 165](#).

A confirmation dialog is displayed with the following message: You are about to start a broadcast call to x. Continue?

2. Perform one of the following actions:
  - To initiate the call, tap **Call**.  
The **PTT Broadcast Call** screen is displayed.

**Figure 10: PTT Broadcast Call Screen**



- To cancel, tap **Not now**.
3. Press and hold the **PTT** button.  
A broadcast call starts, a chirp tone is heard, and the **PTT** button changes color indicating you have taken the floor.

4. Release the **PTT** button when you have finished speaking.
5. Begin speaking.
6. To end the call, tap the **End Call** button.


### 6.1.7

## Call from Device Contacts

You can make a call from your device contacts.

### 6.1.7.1


## Placing a Call from Device Contacts

 **NOTE:** You cannot place PTT calls when the PTT application is Offline or logged out.

### Procedure:

Navigate to the device contacts and perform one of the following actions:

- Select the PTT contact to call, and press the **PTT key**.
- Navigate to Push-to-Talk and press the **PTT key** to call the contact.

 **NOTE:** Pressing the PTT key may display multiple numbers. Select the PTT number and press the PTT key to call. To avoid multiple numbers, ensure to assign one phone number to a contact.

### 6.1.8


## Calling from History

You can make a call from History.

### Procedure:

1. Tap on **History** to view the history of calls and IPAs.

**Figure 11: History**



2. Touch on the conversation you want to call.  
The **Call** screen displays.
3. Press and hold the **PTT** button displayed on the screen.  
A PTT call starts, a chirp tone is heard and the **PTT** button changes color indicating you have taken the floor.
4. Begin speaking.
5. To take the floor and speak, release the **PTT** button to allow other members of the call.
6. To end the call, tap the **End Call** button.

### 6.1.9

## Calling from Missed Call Alert

Missed Call Alert (MCA) messages initiated an alert tone followed by a pop-up message.

For more information, see [Missed Call Alert on page 172](#).

### Procedure:

When receiving a missed call alert, perform one of the following actions:

- To place the call, tap the **Reply** button.
- To dismiss the message, tap the **Not now** button.

### 6.1.10

## Calling from Instant Personal Alert

You can make a call from an Instant Personal Alert (IPA). On receiving an IPA, you receive an alert tone and a pop-up message displays.

For more information, see [Instant Personal Alert on page 169](#).

### Procedure:

Perform one of the actions:

- To place the call, tap the **Reply** button.
- To dismiss the message, tap the **Not now** button.

### 6.1.11

## Call Behavior when Contact or Talkgroup is Unavailable

When calling a contact or talkgroup that is unavailable, the application automatically records, and sends a voice message while pressing the PTT button. The message is sent as soon as you release the PTT button. There is no review, discard, or re-record.




**NOTE:** Requires the Integrated Secure Messaging feature to be turned on by your administrator.

### One-to-One (1:1) Calls

A contact is unavailable when their presence status is *Offline* or *Do Not Disturb (DND)*, or if they are temporarily not reachable due to loss of signal.




A voice message must be three seconds or longer; otherwise, the message is not sent, and you receive an information message.

 **NOTE:** When calling a contact that is temporarily not reachable due to loss of signal, the voice message recording chirp can take up to seven seconds.

### Talkgroup Calls

When the talkgroup you are trying to call has all members unavailable, you can record and send a voice message to the entire talkgroup.

A voice message must be three seconds or longer; otherwise, the message is not sent and you receive an information message.

 **NOTE:** When all members are not available, the voice message recording chirp can take up to seven seconds if one or more members are temporarily not reachable due to loss of signal.

#### 6.1.12

## Dialing a Manual Call to a PTT User


The Manual Dial screen allows you to call a PTT contact manually.

### Procedure:


1. From the **Menu**, tap the **Manual Dial** option.

The **Manual Dialing Screen** displays.

**Figure 12: Manual Dialing Screen**



2. By using the on-screen keyboard, enter the contact number including special characters (0-9, \*, #, a-d).

 **NOTE:** If the number matches contacts, they display. If you want to call one of those contacts, touch the contact, and the number fills the numeric text field else continue initiating the call with the manual dialed PTT number.

3. Located at the right of the phone number, tap the on-screen **PTT** button.

The **Call** screen displays.

## 6.2

## Receiving Calls



**NOTE:** To receive an incoming call, on iOS 12.4 or higher devices, you must bring the application to the foreground.

**Procedure:**

1. When you receive an incoming PTT call, the application is brought to the foreground, and the PTT button changes color.

Whenever the talker releases the floor, the **PTT** button changes and the PTT button changes color and the floor is available for another talker.

2. On the screen, to continue the conversation, touch and hold the PTT button.
3. To end the call, tap the **End Call** button.

## 6.2.1

### Receiving One-to-One (1:1) Calls

When you receive an incoming PTT call, the application is brought to the foreground, and the PTT button changes color.



**NOTE:** Incoming PTT calls respond differently based on the combination of the phone settings and the PTT application settings. For more information, see the [Interaction with Silent or Sound Mode on page 69](#) section.



**NOTE:** This behavior assumes that Background Calling is turned OFF. For more details on Background Calling, see the [Call Behavior in Background](#) section.

Whenever the talker releases the floor, the PTT button changes and the PTT button changes color and the floor is available for another talker.

You can continue the conversation by touching and holding the **PTT** button on the screen.

You can end the call by tapping the **End Call** button.

## 6.2.2

### Receive Broadcast Talkgroup Calls

An incoming broadcast talkgroup call looks like any other talkgroup call but preempts other PTT calls in progress except emergency calls.

You can recognize a broadcast talkgroup call because there is a distinct tone played followed by an announcement. During the call, only the broadcaster can speak, and you cannot take the floor. These calls also override your Do Not Disturb (DND) status if your administrator has set the talkgroup to do so.

Only designated talkgroup members may make broadcast talkgroup calls. If you are not allowed to make calls to a talkgroup, you do not see it listed in the **Talkgroups** tab. If you try to call a broadcast talkgroup from history, you see a message indicating that the call cannot be completed.

### 6.2.3

## Broadcast Call History


Outgoing broadcast calls are shown in call history like other calls, but with a different icon and call type indicated.

**Figure 13: Nonbroadcaster Call History**



A summary of call delivery status for the broadcaster is shown in the **Talkgroup** tab history detail for the selected talkgroup. The number of talkgroup members who received the call is shown along with the total number of talkgroup members.

**Figure 14: Broadcaster Call History**



Calls might not be delivered to everyone because a talkgroup member may be offline, engaged in a cellular call, have a Do Not Disturb status, or listening to another broadcast call. Calls are delivered in a way such that talkgroup members may receive the call at slightly different times. Once the call delivery process is complete, the delivery status shows.

### 6.3

## Turning the Speaker On/Off

On the Call screen, there is a toggle that indicates whether the speaker is on or off for PTT calls. When the speaker is off, you can hear the PTT call audio in the earpiece of the phone. When it is on, the audio is heard through the speaker.

**Figure 15: Earpiece is On**




**Figure 16: Speaker is On**



During a PTT call, the speakerphone or earpiece volume can be increased or decreased using the volume up and down keys. The volume adjusted during a PTT call is used for subsequent calls, including cellular calls.

**Figure 17: Call Screen - Speaker ON/OFF Button**



You can turn off the speaker from the application settings. For more information, see [Call Screen Icons on page 45](#).

### 6.4

## Set the PTT Call Volume

During a PTT call, you can increase or decrease the speakerphone or earpiece volume by using the volume up and down keys. The volume adjusted during a PTT call is used for subsequent calls.

The PTT call volume that is adjusted using the earpiece also controls the corresponding volume on a cellular call.

The PTT call volume that is adjusted using the speakerphone also controls the corresponding volume on a cellular call.

## 6.5

# Interaction with Silent or Sound Mode

When the ringer of your phone is set to silent or vibrate-only, PTT calls are played over the earpiece of the phone. To hear a PTT call, you should hold the phone to your ear as during a cellular phone call.

You can temporarily switch to the loudspeaker using the on-screen speaker **ON/OFF** button for the current call. The next PTT call again uses the earpiece of the phone while the phone is in silent mode.

You can set the phone to vibrate for incoming PTT calls if the incoming Call Vibrate setting is **ON**. For more information on how to set incoming Call Vibrate, see [Vibrate Call on page 174](#).

## 6.6

# Interaction between PTT and Cellular Calls

## Answering a Regular Phone Call While on a PTT Call

If you receive an incoming regular phone call while you are in PTT call, the user is presented with a dialog to either accept or reject the call as per device behavior (not controlled by PTT application). If the user answers the cellular call, the PTT call is put in the background. PTT voice is lost during ringing, which is normal device behavior for a cellular call while on a data session.

When the regular call ends, if the PTT call is still on, it comes to the foreground. The PTT call can also end silently in the background.

If you receive an incoming regular phone call while you are in PTT group call, then the user is presented with a dialog to either accept or reject the call as per device behavior (not controlled by PTT application). If the user answers the cellular call, the PTT group call is put in the background. PTT voice is lost during ringing, that is, normal device behavior for a cellular call while on a data session.

When the regular call ends, if the PTT group call is rejoined, it comes to the foreground. The PTT group call can also end silently in the background.

## Receiving a PTT Call When on a Regular Phone Call

If you receive a PTT call while you are on a regular call, the ongoing cellular call continues, and an incoming PTT call is rejected with user busy indication. You receive a missed call alert along with an alert tone and a pop-up message is displayed as an indication that a PTT call occurred during the cellular call.

After the current regular call ends, you can make a PTT callback to the caller from the missed call alert displayed in the PTT application.

## 6.7

# Call Behavior in Background

## Incoming PTT Calls with Background Mode Turned Off

While using other applications on the phone, an incoming PTT call lights up the display, the device shows a notification from the application, and you hear an incoming call tone followed by the voice of the caller. The notification shows the name of the contact or group calling.

## Incoming PTT Calls with Background Mode Turned On

When Background Mode is turned on, and you receive an incoming PTT call, the PTT application remains in the background; however, the display does not turn on if it is off, and you hear the voice of the caller. You can bring the PTT application to the foreground to use the on-screen PTT button. For more information on Background Mode, see [Settings on page 160](#).



**TIP:** If your phone has a supported Bluetooth PTT accessory, you can press the button to take the floor while the application is in the background.



**NOTE:**

If the backlight is off, it remains off during an incoming PTT call. IPAs are not visible until you access the PTT application; however, you receive audible alerts, if turned on.

## Ongoing PTT Calls

During a PTT call, if you navigate away to another application, you can continue to hear the PTT call, but you cannot take the floor and speak until you return to the PTT application.



**TIP:** If your phone has a supported Bluetooth PTT accessory, you can press the button to take the floor while the application is in the background.

### 6.8

## Rejoin a PTT Talkgroup Call

### Rejoining a Talkgroup Call

If you leave during a PTT talkgroup call, you can rejoin it by initiating a call to that talkgroup again either from the call history or from the talkgroup list. If the call ended before you try to rejoin, you can start a new call to that talkgroup. Any late join to a PTT talkgroup by selecting a talkgroup automatically rejoins if there is an active call on the talkgroup.

### Joining a Missed Talkgroup Call

If you miss a talkgroup call, you have the option on the missed call alert to call the talkgroup directly. If the talkgroup call is still in progress, you are automatically joined to the ongoing call. Otherwise, you can start a new call.

## Chapter 7

# Emergency Calling and Alert (Optional)

Optional features may not be included in your PTT service plan.

For more information on Emergency icons, see [Emergency Icons on page 47](#).

Emergency calling and alert allows you to declare an emergency to contact or talkgroup as configured by your corporate administrator.

You can press and hold the **Emergency** button on the PTT application and swipe the slider to declare an emergency. The PTT application automatically goes to the **Call** screen. You can press the PTT button to begin an emergency call. When you declare an emergency, an emergency alert is sent out to the other users in the emergency talkgroup or the contact configured by your administrator.

On the selected device or supported accessory, you can also declare an emergency by using the **Emergency** button.

To cancel an emergency, you can press and hold the EMERGENCY button again and swipe the slider to confirm the cancellation. Your administrator may disallow your ability to cancel an emergency. In that case, an authorized user needs to cancel the emergency on your behalf.

An Authorized User can remotely declare and cancel an emergency call on behalf of the remote user.

Your administrator can configure call initiation to either automatic or manual. When set to automatic, after emergency initiation, an emergency alert is sent, and the emergency call is started automatically. There is no need to press and hold the PTT button. The floor is taken for 10 seconds. During the 10 second automatic floor hold time, pressing and releasing the PTT button has the following behavior: When you release the **PTT** button, the floor releases; if you press and continue to hold the PTT button after the 10 seconds expires, the floor will continue to be held. Your network operator may have configured this service to ignore the PTT button press and release during the automatic floor hold time. When set to manual, an emergency alert is sent. However, to initiate the emergency call, you must press and hold the PTT button.

Multiple users can declare an emergency in the same talkgroup. When a user declares an emergency in the same talkgroup, they preempt the PTT floor from another user in an emergency. Participating users in an emergency talkgroup call receive an alert from all users in an emergency and can view all members at any time except for late joiners.

Depending on how your network operator has configured the service, you may be able to use the emergency button for initiating and canceling the emergency toggle or send a repeated emergency alert after you have declared an emergency to get automatic PTT floor. A repeated emergency alert by the same user is only sent to dispatchers. If your administrator has configured automatic call initiation, each time you declare emergency your microphone will unmute for a period of 10 seconds without having to press and hold the PTT button.

For more information on who is your configured primary and secondary emergency contacts, see [Settings on page 160](#).

### 7.1

## Declare an Emergency

An emergency can be declared from any screen where there is an **Emergency** button or by using an external emergency button on the device or accessory when supported. Any PTT key pressed during automatic configuration (default 10 seconds) is ignored. You must press and hold the PTT key to continue to talk after the automatic timer is expired.

Your administrator configures the emergency destination. The destination can be a preassigned talkgroup or an individual.

You can perform an emergency initiation while in two-way call. When an emergency is declared the two-way call ends immediately.

### 7.1.1

## Declaring an Emergency

Incoming alert tones, such as IPAs, OSMs, MCAs, PTX are not played while you have declared an emergency.

#### Procedure:

1. Touch and hold the EMERGENCY button.



#### NOTE:

The **Declare emergency** slider displays.

2. To declare an emergency, swipe the slider to the right.

A message is shown and a special emergency alert tone is played to indicate that an emergency has been initiated. The **PTT Call** screen is displayed.



**NOTE:** If the emergency cannot be declared, the emergency fail tone is played, and a toast message is displayed.

3. After declaring an emergency, an emergency alert is sent.

You are now locked into the emergency call until the emergency is canceled.



**NOTE:** On iOS 12.4 or above, when an emergency call is originated with automatic call initiation enabled by your administrator, locally with PTT accessory button, the handset will initiate an emergency call, give the talk permit chirp and hold the floor for 10 seconds without sending audio. Subsequent attempts for the user in an emergency to take the floor will also be unsuccessful if using a PTT accessory button. The user must open the app to the foreground before taking the floor.

4. Press and hold the PTT button.

A chirp tone is heard, and the **PTT** button changes color indicating you have taken the floor.

5. Begin speaking.

6. To cancel an emergency, see [Emergency Cancellation on page 74](#).

### 7.2

## Authorized User Remotely Declaring an Emergency on your Behalf

An authorized user if configured by your administrator, can remotely declare an emergency on your behalf.

You see that an authorized user has declared an emergency, an emergency alert is received similar to the following: Remote emergency declared by x.

You are now locked into the emergency call until the emergency is canceled.

For more information on authorized users, see [Authorized User on page 74](#) section.



### 7.3

## Receive an Emergency

When a user declares an emergency, other users receive an alert indicating that an emergency is declared. The alert is sent to all users who are part of the talkgroup where the emergency call occurs.

Your administrator configures the talkgroup or single PTT contact that receives emergency calls. An emergency alert notifies you that another user has declared an emergency state. Generally, an emergency call follows an emergency alert on the talkgroup indicated, unless the emergency is canceled. When the application is in the background, use the notification bar to access emergency alert and emergency cancellation alert.

An emergency alert, similar to the following, indicates which user is in emergency and the talkgroup they are using: `Emergency Declared by x from x talkgroup`.

If the emergency call goes only to a single user, no talkgroup is shown in the alert.

### 7.3.1

## Receiving an Emergency Call

You receive an emergency call unless scanning is turned on and the emergency occurs on a non-scan list talkgroup.

Your administrator may also configure your application to receive the call when an emergency call starts on another talkgroup.

The recipient can leave an emergency call, make a private call, or call on another talkgroup. Incoming emergency calls, preempt other ongoing calls, except an emergency call.

### Procedure:

1. To remove the alert from appearing on the **Emergency Alert** screen, tap or touch **Dismiss**.

You can continue to use the application normally.

When the emergency originator starts a call or takes the floor during an ongoing call after declaring an emergency, you see an emergency call in progress screen: `There is a special emergency call tone played`.

2. During an emergency call, take the floor by pressing the PTT button.

You can leave the call by pressing the **End Call** button.



**NOTE:** If you leave the emergency call, you receive an emergency call from the same emergency if another call starts.

An incoming emergency call interrupts an ongoing PTT call, except another ongoing emergency call.

### 7.3.2

## Receiving an Emergency Cancel Notification

If the application is in the background, select the notification to access the emergency cancel notification. Follow this procedure when you receive an emergency cancel notification.

### Procedure:

To remove the alert from appearing on the screen, tap the **Dismiss** button.

You can continue to use the application normally.

## 7.4

# Emergency Cancellation

To end the emergency, you as the emergency originator must cancel the emergency state. An authorized user, typically a supervisor or dispatcher, may cancel the emergency on your behalf. Your administrator may disable permission for you to cancel the emergency. In this case, an authorized user must cancel the emergency.

### 7.4.1

## Canceling Emergencies

### Procedure:

1. While in an emergency, touch and hold the **EMERGENCY** button.  
The **Cancel Emergency** window displays.
2. To cancel emergency, swipe the **Cancel** slider to the right.  
Before canceling the emergency, you are asked if the emergency was a real emergency or a false alarm.  
A dialog, similar to the following, displays: Please select reason for Emergency Cancellation.
3. Touch or tap the desired option for canceling the emergency as follows:
  - If the emergency was a real emergency, tap **Valid**.
  - If the emergency was a false, tap **False**.
4. Touch or tap **Send**.

**Result:** The emergency is canceled, a message indicating that the emergency is canceled is displayed, and an **Emergency Cancel** tone is played.

## 7.5

# Authorized User

An authorized user is typically a dispatcher or supervisor which may have permissions to do the following:

- Allow or disallow remote supervision for assigned contacts.
- Remotely declare and cancel an emergency call on behalf of a remote user.
- Access user check for the remote user.
- Enable or disable PTT service.
- Activate ambient listening for the remote user.
- Activate discreet listening for the remote user.

### 7.5.1

## Declaring an Emergency on Behalf of Another User

Your administrator may give you the ability to declare an emergency for another user remotely. The authorized user touches the Emergency start.




**NOTE:** If you can remotely start an emergency for one or more users, you are called an authorized user.

While a user is in an emergency, you can view information about the user such as location, battery level, and signal strength that is sent at the beginning of the emergency call.

**Procedure:**


1. From the **Main** screen, tap or touch the **Contacts** tab.  
The **Contacts** displays.
2. Touch and hold the contact name from the **Contacts** list.  
You can declare an emergency for users your administrator has given permission.  
A **Context Menu** displays.

**Figure 18: Contact Context Menu**



3. Tap the **Declare Emergency** option.  
The **Declare Emergency** window displays.
4. To declare an emergency, swipe the **Declare** slider to the right.  
An emergency is declared and an emergency alert displays similar to the following: *Emergency Declared by you from authorized user X.*
5. Dismiss the emergency alert pop-up.
6. When another user takes the floor, an **Emergency User Check** icon displays on the your **Call** screen.
7. On the **Call** screen, tap or touch the **User Check** icon.  
The **Emergency User Check** screen displays.

**Figure 19: Emergency User Check**



8. To cancel an emergency, see [Emergency Cancellation on page 74](#) section.  
You can cancel the emergency locally or an authorized user can cancel on your behalf remotely.

### 7.5.2

## Cancel an Emergency on Behalf of Another User

You can cancel an emergency on behalf of another user from a **Contact Context Menu**.

To end the emergency, you as the emergency originator must cancel the emergency state. An authorized user, typically a supervisor or dispatcher, may cancel the emergency on your behalf. Your administrator may disable permission for you to cancel the emergency. In this case, an authorized user must cancel the emergency.

### 7.5.2.1

## Canceling an Emergency from the Context Menu

#### Procedure:

1. Touch and hold a contact from the **Contacts**.  
A **Context Menu** displays.
2. Tap the **Emergency** button.  
The emergency **Context Menu** displays.
3. Tap the **Cancel Emergency** option.  
The **Cancel Emergency** window displays.
4. To cancel emergency, swipe the **Cancel** slider to the right.  
Before canceling the emergency, you are asked if the emergency was a real emergency or a false alarm.

5. Touch or tap the desired option for canceling the emergency.
6. Touch or tap **Send**.  
The emergency is canceled, and a message is displayed that indicates that the emergency is canceled.

### 7.5.2.2

## Canceling an Emergency from Call Screen

**Prerequisites:** Perform [Enable Emergency User Check on page 77](#)

**Procedure:**

1. Tap the **Emergency** Button.  
The **Cancel Emergency** window displays.
2. Swipe the **Cancel** slider to the right to cancel emergency.  
Before canceling the emergency, you are asked if the emergency was a real emergency or a false alarm.
3. Perform the following actions:
  - Tap **Valid** when the emergency is valid.
  - Tap **False** when the emergency is false.
4. Touch or tap **Send**.  
The emergency is canceled, and a message indicating that the emergency is canceled is displayed.

## 7.6

# Enable Emergency User Check

On your device, emergency user check is enabled only during an emergency call and you tap the **Emergency User Check** icon on the **Call** screen. User Check is only available during each emergency call. If you disconnect and rejoin the call, the **User Check** icon is no longer available.

### 7.6.1

## Enabling Emergency User Check from Call Screen

**Procedure:**

1. When an emergency has been declared and is in progress.  
The **Call** screen displays.
2. Tap or touch the **Emergency User Check** icon located to the left of the PTT button.  
The **Emergency User Check** screen displays.

## 7.6.2

## Monitor Device Location

The **Emergency User Check** screen displays the user's location on a map if the location is available. The information does not update in real-time. The time is shown next to the battery level indicator when the user sent the location.

## 7.6.3

## Monitor Device Cellular Network Signal Strength

The **Emergency User Check** screen displays the current cellular network signal strength of the remote user device, if available.



**NOTE:** Signal strengths are available only for Android devices. iOS devices, signal strength for Cellular and Wi-Fi are not available.

## 7.6.4

## Monitor Device Wi-Fi Signal Strength

The **Emergency User Check** screen displays the current Wi-Fi signal strength of the remote user device, if available.



**NOTE:** Signal strengths are available only for Android devices. iOS devices, signal strength for Cellular and Wi-Fi are not available.

## 7.6.5

## Monitor Device Battery Level

The **Emergency User Check** screen displays the current battery level of the remote user device, if available.

## Chapter 8

# Area-Based Warning Tones

The Area-Based Warning Tones feature allows a dispatcher to configure a continuously playing warning tone on your device when you are within a particular area, also known as Geofence. For example, a mining company needs to inform workers of a situation where a blast is happening, an emergency exists, or evacuation is necessary.

The Area-Based Warning Tones are listed in the following table:

**Table 19: Area-Based Warning Tones**

Name	Description
Area Warning Tone - Blast Tone	Played to indicate when you are within a blast area. For iOS, the app is suspended when put into the background and cannot play the periodic tone.
Area Warning Tone - Emergency Tone	Played to indicate to when the user to follow emergency procedures. This tone is played to escalate the priority from the blast notification to a mining emergency notification. For iOS, the app is suspended when put into the background and cannot play the periodic tone.
Area Warning Tone - Evacuation Tone	Played to indicate when you are notified to immediately evacuate the mining site for an impending blast. For iOS, the app is suspended when put into the background and cannot play the periodic tone.

The dispatcher manages area-based tones. The dispatcher can change the tone type while the tone is active, in which case you will hear the tone change. The highest priority tone will play if you are in an area in which more than one area-based tone is active.



**NOTE:** The area-based tone will pause during Emergency or Broadcast calls and will resume once call ends.

You are able to initiate and receive PTT or Video calls and perform any PTT operation.

## 8.1

# Enter a Geofence

When you enter a geographical fence area based on the location of your device, you can receive a tone and you see a banner that displays the type of tone that is active and the name of the fence that the dispatcher gave it. For example, `Blast Tone Active - Blast Site 1`.

## 8.2

# Exit a Geofence

When you exit a geographical fence area based on your location, the area-based tone stops playing and you can see a message displayed on the **Call** screen. For example, `You have exited the 'Blast Site 1'`.

## 8.3

# Viewing Active Geofences

**Prerequisites:** Ensure to enable location services. If not, you may receive the `Unknown Location` message.

**Procedure:**

1. You can view any active Geofences by selecting the **Menu** → **Active Fences**.
2. From the **Menu**, tap **Active Fences**.

You can see the currently active fences, the type, the dispatcher maintaining the fence, the group name and you can see whether you are inside or outside the fence. You can see an indication that the fence tone (Bell icon) is active. If no fences are active, the following message displays: `No record found`



## Chapter 9

# Enter a Geofence

When you enter a geographical fence area based on the location of your device, you can receive a tone and you see a banner that displays the type of tone that is active and the name of the fence that the dispatcher gave it. For example, Blast Tone Active - Blast Site 1.

## Chapter 10

# Supervisory Override

A supervisory override allows a talkgroup member to be designated by an administrator as a supervisor and be able to take the floor and speak at any time during a call, even if someone else has the floor.

One or more members of a talkgroup can be designated as a supervisor. If there are two or more supervisors in the same talkgroup, each supervisor can interrupt the other(s).

### 10.1

## Supervisor Talkgroup

A talkgroup supervisor sees a supervisor icon displayed next to the name of the talkgroup and next to the word `YOU` in the status bar when they take the floor.

### 10.2

## Non-supervisor Talkgroup Members

A non-supervisor talkgroup member can identify supervisors by an icon next to the name of the supervisor.

## Chapter 11

# Alerts

This section describes the alerts used in the Push-to-Talk (PTT) application.

## 11.1

### Instant Personal Alert (IPA)

An Instant Personal Alert (IPA) is a notification that you can send to another PTT contact to request a callback or receive from a PTT contact. You can only send or receive IPAs by individual contacts.

#### 11.1.1

### Sending an Alert

#### Procedure:

1. From the **Contacts** list, select the contact.



**NOTE:** You can send alerts from **History** and **Call** screens by using the **Alert** button.

2. Touch and hold on the contact name.

The **Context Menu** displays.

3. To send the alert to the selected person, tap the **Alert** button.



**NOTE:** The `Alert Sent` message indicates that the application successfully delivered an alert request to the server. This message does not mean the person received the alert.

#### 11.1.2

### Receiving an Alert

Whenever someone else sends you an alert, the PTT application notifies you with a persistent alert dialog displayed, and an audible tone is played (subject to Silent Mode behavior).



**TIP:** Whenever you receive an alert, it shows in the call history.

#### Procedure:

Perform one of the follow actions when you receive an alert:

- To call the person back, tap the **Reply** button.  
If your phone has a **PTT** button, you can also press it to call the person back while the alert is displayed.
- To dismiss the alert without calling back, tap the **Not Now** button.

**Result:** The IPA behavior is one of the following based on the setting:

- A persistent alert dialog is displayed, and an audible tone is played (default)
- A persistent alert tone is played, but no alert dialog is displayed.
- A persistent alert dialog is displayed, but no alert tone is played.

- No alert dialog is displayed, and no alert tone is played.

For more information on the Instant Personal Alert, see [Settings on page 160](#).



**NOTE:** When you are on a cellular call or PTT call, the IPA is deferred until after the call ends and displays when PTT is idle (not in a call). Only last IPA is displayed (no queuing).

## 11.2

# Missed Call Alert (MCA)

Your phone alerts you whenever you miss a PTT call for the following reasons:

- You are on a regular cellular call when a one-to-one or talkgroup PTT call is made that includes you.
- You are already on a PTT call, and another one-to-one or talkgroup PTT call is made that includes you.
- Your phone receives a one-to-one PTT call, and you do not reply by taking the floor and speaking back. You cannot receive a missed call alert if you do not reply to a talkgroup call.
- Your self-presence is DND. In this case, the history updates silently. You will not receive a pop-up notification.

For more information on configuring the Missed Call Alert, see [Settings on page 160](#).



**NOTE:** You cannot receive a missed call alert for a one-to-one PTT call if you end the PTT call before speaking back.

### 11.2.1

## Replying to a Missed Call Alert

### Procedure:

When a Missed Call Alert is displayed, perform one of the following actions:

- To make a PTT call, tap **Reply**.
- To dismiss the message, tap **Not now**.

## 11.3

# Multiple Missed Call Alerts or Instant Personal Alerts per Caller

When you receive multiple Instant Personal Alerts (IPAs), only the latest alert shows on the display after the call ends. All the previously received IPAs are available in the PTT call history.

Similarly, when you receive multiple missed call alerts from a single caller or talkgroup, only the latest alert shows on the display. All the previously received missed call alerts are available in the PTT call history.

## 11.4

# Set the PTT Alert Volume

You can set the **PTT Alert Volume** by adjusting the phone ringer and alerts volume under the **Settings** → **Sounds** → **Ringer and Alerts**

For more information on your phone volume controls, refer to the manual of your phone.

## Chapter 12

# Real-Time Presence

This section describes the real-time presence using the Push-to-Talk (PTT) application.

With real-time presence, you can tell at a glance if the person you want to call is `Available`, `Do Not Disturb` (DND), or `Offline`. DND and offline contacts do not receive PTT calls. However, they can send and receive Integrated Secure Messages. The presence indicator is displayed next to the name of the contact. Likewise, you can tell others of your availability by selecting either `Available` or `Do Not Disturb` within the PTT application. When you turn off your phone, you are automatically marked as `Offline` to others.

## 12.1

### My Presence

You can see the My Presence or self-presence status just above the top-level tabs and in the notification bar. For more information on the icons, see [Presence Icons on page 51](#).

#### 12.1.1

### Setting Self Presence

You can set self-presence.

#### Procedure:

1. Tap on the self-presence tile. A pop-up menu displays showing you your current self-presence status.
2. Choose the presence state you want to set.
  - To set your self-presence state, tap **Available**.
  - To set your self-presence state, tap **Do Not Disturb**.

The Self-Presence icon and text updates on the Self-Presence Bar and the icon on the screen status bar.

#### Meaning of Presence

**Available** You are logged into the PTT application, ready to receive PTT calls, Instant Personal Alerts (IPA), and Integrated Secure Messages.

**Offline** You are logged out from the PTT application and cannot receive PTT calls, alerts, or Integrated Secure Messages.

**No Connection** When the PTT application cannot communicate with the PTT server, it displays **Offline** in the status bar or system notification, and your availability shows **No Connection**. For more information, refer to the [Loss of Data Network Connection on page 179](#) section.

#### Calling Restrictions

When you are in the DND state, you cannot receive PTT calls, but you can make PTT calls to other available users.

#### IPA Origination Restrictions

When you are in the DND state, you cannot send an IPA to other contacts since you cannot receive calls from others. If you try to send an alert, you see the following message: `You cannot send`


an alert while your availability is 'Do Not Disturb'. Please change your status.

## 12.2

# PTT Contact Presence

You can see the contact presence in the **Contact** list indicated by an icon next to the name of the contact. The following image shows an example:

**Figure 20: Contacts**



### Available

The PTT contact is logged into the PTT application, ready to receive PTT calls Instant Personal Alerts and Integrated Secure Messages.

### Do Not Disturb (DND)

The PTT contact is logged into the PTT application, not willing to receive PTT calls but receives Instant Personal Alerts and Integrated Secure Messages.

### Offline

The PTT contact is logged out from the PTT application, and cannot receive PTT calls, alerts, and Integrated Secure Messages.

For a description and list of all icons, see [Icons on page 41](#).

### Calling Restrictions

When a contact is in the DND state, you cannot place a PTT call to that contact. If you try to make a call to a contact with the DND status, you see the following message: The Contact you are trying to call is in 'Do Not Disturb' status. Please try again later.



**NOTE:** Depending on how your service provider has configured the service, you may see all or most of your contacts as `Online` even though some may be in a `Do Not Disturb` or `Offline` state. In this case, you may try to call any contact. If the called subscriber is unavailable, you may receive an error message. For more information, see [Call a Contact that is Offline or has a Do Not Disturb \(DND\) Status on page 60](#).

### Using Instant Personal Alerts for DND contacts

To contact a person with a DND status, you can send an Instant Personal Alert to request a callback.

## Chapter 13


# History

The **History** screen displays all your conversation history of calls, contacts, talkgroups, alerts, messages, such as text, image, video, and voice.

You can view and search your history, return a call, view messages, add contacts, delete history and messages, and forward any message to a contact or talkgroup. The **History** screen contains two-level screens: the **Main** screen and **Details** screen. The main screen contains a high-level view, while the second-level screen contains the conversation details including a time stamp. Messages from the previous day are shown with the date stamp **YESTERDAY**. The Date/Time (12/24 hour display) format follows device setting for internationalization.

Each top-level history entry displays the conversation type, such as **Broadcast Call**, **Emergency Alert**, **Group Call**, **Quick Group Call**, or **Private Call**, contact name, talkgroup name or participant names for quick groups, <message text preview> (if a text message), **Voice Message**, **File**, **Image**, **Location**, and **Video**.

**Figure 21: History**



### 13.1

## Access History

You can access **History** screen by tapping the **History** tab located at the upper left of the screen.

### 13.2

## Search History

You can use the search box to search for history.

For more information on searching on the **History** screen, see [Searching on page 40](#).

### 13.3

## History Icons

Understanding the history icons can help you access the information you need. For more information on the history icons, see [History Icons on page 47](#).

### 13.4

## Access Conversation Details

To access the conversation details, tap the **History Details** button located to the right of the entry.

From the **Conversation Details** screen, you can view history, send alerts, read, and send messages.

For more information, see [Integrated Secure Messaging on page 129](#).

For additional information on sending and receiving multimedia content, see [Integrated Secure Messaging on page 129](#).

### 13.5

## Making a PTT Call

### Procedure:

To make a PTT call, tap the **History Entry** and perform one of the following actions:

- To talk, press and hold the PTT button.
- To talk, press and hold the on-screen PTT button.

### Result:

The **Call** screen displays.

For more information, see [Calling from History on page 63](#).

### 13.6

## Adding a PTT Contact (Optional)

If enabled by your administrator, you can add a contact from your **History** list if the contact is not already in your **Contact** list.

For more information, see [Contact Additions on page 97](#).

### Procedure:

1. From the top-level screen, tap and hold the HISTORY ENTRY.  
A **Context Menu** displays.
2. Tap the **Add Contact** option.  
The **New Contact** screen displays.



## 13.7

# Adding a Phone Contact (Optional)

If enabled by your administrator, you can add a outgoing VoIP contact from your **History** list if the contact is not already in your **Contact** list.

### Procedure:

1. From the top-level screen, tap and hold the **HISTORY ENTRY**.  
A **Context Menu** displays.
2. Tap the **Add as Phone Contact** option.  
The **New Contact** screen displays.

## 13.8

# Deleting History

You can delete any history entry.

### Procedure:

1. From the top-level screen, tap and hold the **History Entry**.  
A **Context Menu** displays.
2. Tap the **Delete History** option.  
The following confirmation message displays: The History for this contact or group will be removed. Continue?
3. Perform one of the following actions:
  - To delete, tap **Yes**.
  - To cancel, tap **No**.

## 13.9

# Clearing All History

You can clear all history entries.

### Procedure:

1. From the top-level screen, tap and hold a history entry.  
A **Context Menu** displays.
2. Tap the **Clear All** option.

The following confirmation message displays,

You are about to clear all the history. All your prior history with all groups and contacts will be deleted. Are you sure?

3. Perform one of the following actions:
  - To delete, tap **Yes**.

- To cancel, tap **No**.

### 13.10

## Deleting a Message

You can delete a message to a contact on the **History Details** screen.

### Procedure:

1. Tap the **History Details** button.
2. Tap and hold the history entry.  
A **Context Menu** displays.
3. Tap the **Delete Message** option.  
A delete confirmation message displays.
4. Perform one of the following actions:
  - To delete, tap **Yes**.
  - To cancel, tap **No**.

### 13.11

## Forward a Message

You can forward messages. For more information, see [Integrated Secure Messaging on page 129](#).

### 13.12

## Photo and Video Sending

You can send photos and videos. For more information, see [Integrated Secure Messaging on page 129](#).

## Chapter 14


# Favorites

The Push-to-Talk (PTT) favorite contacts and favorite groups are separate from the group list on the phone.

The maximum number of favorite contacts allowed on your device is **300**.

The maximum number of favorite groups allowed on your device is **50**.

**Figure 22: Favorite Contacts**



## 14.1

# Favorite Icons

The favorite icons can help you locate information you need. For more information on the Favorites icons, see [Icons on page 41](#).

## 14.2

# Search Favorites

You can use the search box to search for favorites.

For more information on searching favorites, see [Searching on page 40](#).

## 14.3

# View or Edit Favorite Contacts

The **Favorite Contacts** screen shows a list of all your favorite PTT contacts, as well as their current presence status. You can view or edit favorite contacts by using the **Contact Details** screen.



**NOTE:** You can also access your favorites from any **Call** screen. The Favorites icon is located in the your right-hand of the **Call** screen.

## 14.4

# Adding Favorite Contacts

### Procedure:

1. To open the **Add Favorites Contacts** screen, from the **Favorite Contacts** screen, tap **Add** on the action bar.



**NOTE:** You can add contacts to **Favorites** from the **Contacts List**.

2. Scroll and select one or more contacts to add as a favorite.
3. To save your favorite and open the **Favorite Contacts** screen, on the action bar, tap **Save**.

## 14.5

# Removing Favorite Contacts

### Procedure:

1. From the **Favorites Contacts** screen, on the action bar, tap the **Remove**.  
The **Remove Favorites** screen displays.
2. Select the contacts to remove.
3. On the action bar, tap **Save**.

A confirmation message displays the following:

You are about to remove n contact from favorites. Are you sure?

4. Perform one of the actions:

- To remove the contact from favorites, tap **Yes**.
- To cancel to the action, tap **No**.

## 14.6

# View or Edit Favorite Groups

The **Favorite Groups** screen shows a list of all your favorite PTT groups. You can view or edit favorite groups by using the **Group Details** screen.

## 14.7

# Adding Favorite Groups

### Procedure:

1. From the **Favorite Groups** screen, on the action bar, tap **Add** and select one or more groups.

The **Add Favorites** screen displays.



**NOTE:** You can also add talkgroups from the **Talkgroups List**.

2. To save the group, on the action bar, tap **Save**.

The group is shown in the **Favorites** tab under **Groups**.

## 14.8

# Removing Favorite Groups

The list of personal favorite groups is shown on the **Favorite Groups** screen.

### Procedure:

1. From the **Favorites Groups** screen, on the action bar, tap **Remove**.

The **Remove Favorite** option displays.

2. Select one or more favorite to remove.

3. To remove the group as a favorite, on the action bar, tap **Save**.

A confirmation message displays the following: You are about to remove n group from favorites. Are you sure?

4. Perform one of the following actions:

- To continue, tap **Yes**.  
The group is removed from the **Favorites Groups** screen.
- To cancel, tap **No**.  
The action is canceled.

## Chapter 15

# Contacts

This section describes Push-to-Talk (PTT) contacts using the PTT application.

The PTT contacts are separate from the **Contacts** on the phone. There are two types of contacts: those that are managed by an administrator and those that are managed on the phone by the user.

## Administrator-Managed Contacts

Your administrator manages PTT contacts. Administrator-managed contacts cannot be deleted or changed from within the PTT application.

## Personal Contacts

Personal contacts are imported from the Contacts in the phone or entered manually. You manage personal contacts within the PTT application. You do not have the ability to create contacts if your administrator has restricted this feature.

## Maximum Number of Allowed Contacts

The maximum number of Administrator-Managed contacts allowed on your phone is **1000**.

The maximum number of personal contacts allowed on your phone is **300**.

### 15.1

## Contact Icon

The contacts icon can help you locate the information you need.

For more information on the Contacts icon, see [Contacts Icon on page 46](#).

### 15.2

## Search Contacts

You can use the search box to search for your contacts or contacts within your corporate global directory.

#### 15.2.1

## Your Contact List

Your contact list contains corporate contacts and personal contacts. Your administrator manages corporate contacts and you manage personal contacts. These contacts display the user name and their presence status. To search for your contacts, you can touch within the search bar to bring up the on-screen keyboard. As you type, contacts names containing the letters or numbers entered automatically display.

## 15.2.2

# Searching Corporate Global Directory Contacts

Corporate global directory contacts contain all contacts within your corporation. These contacts display the user name and number. No presence status is shown. You can use the search for contacts in the global directory as follows:

### Procedure:

1. Within the **Contacts** list, touch the **Your Contact List** drop-down menu.
2. From the pop-up, select the **Global Directory** option.
3. Touch within the search bar to bring up the on-screen keyboard. Type a minimum of three characters of the contact you are searching for into the search field.
4. Tap the **Search** icon.



**NOTE:** If enabled by your administrator, you can also add a contact by touching and holding the CONTACT.


The contacts names containing the letters or numbers entered display.

## 15.3

# View Contacts

The **Contacts** tab shows your personal PTT contacts and contacts added by your administrator. You can view and sort the contacts based on alphabetical order or based on the availability of the contacts from the application settings. You can toggle the favorite state of each contact.

Figure 23: Contacts



### 15.3.1

# Sorting the Contact List

Normally you can see all your PTT contacts listed in alphabetical order when you view the contact list. When the **Contact Sorting** setting option is changed to *By Availability, Available, and Do Not Disturb*,

they are sorted alphabetically first followed by *Offline*. The **Contacts** list updates each time a contact changes from online to offline or vice versa.

**Procedure:**

1. From within the **Menu**, tap the **Settings** option.
2. Scroll down and tap the **Contacts Sorting** setting.  
The **Contact Sorting Settings Options** displays.
3. Perform one of the following actions:
  - Select **By Alphabetical**.  
Contacts are sorted by alphabetically.
  - Select **By Availability**.  
Contacts are sorted by availability.
4. Located on the top of the screen, tap **Back**.  
The **Contacts** list is sorted according to your selection.

### 15.3.2

## Show or Hide Offline Contacts

Normally you can see all your PTT contacts when you view the contact list. You have the option to hide offline contacts and show only contacts whose presence status is *Available* or *Do Not Disturb*. While showing only online contacts, the Contacts list update each time a contact changes from online to offline or vice versa.



**TIP:** If all your contacts are currently offline, you see the message, *No Online Contacts* displayed. If you wish to see all your contacts, follow the steps later in this section that describes how to show all contacts.

### 15.3.2.1

## Showing only Online Contacts

If you want, you can show only online contacts.

**Procedure:**

- While showing the contacts list, tap the **Hide Offline** button located on the bottom of the screen.  
The contact list shows only the contacts that are either *Available* or *Do Not Disturb*, .

### 15.3.2.2

## Showing all Contacts

If you want, you can show all contacts.

**Procedure:**

- While showing only the online contacts in the contacts list, tap the **Show Offline** button at the bottom of the screen.  
The contact list shows all the contacts, including those that are *Available* or *Do Not Disturb*, *Offline*.



## 15.4

# Viewing Contact Details

### Procedure:

1. Select a contact from the **Contacts**, touch and hold.



**TIP:** You can also access the **Contact Details** from the **Call** screen by tapping the **Details** button located at the top of the screen.

A **Context Menu** displays.

2. Tap the **Details** option on the **Context Menu**.

The **Contact Details** screen displays.



**NOTE:** To edit the contact details, see [Edit Contact Details on page 99](#).

## 15.5

# Contact Additions

You can add PTT contacts and add phone contacts in the following ways:

- Adding a personal PTT contact manually.  
For more information, see [Adding a New PTT Contact Manually on page 97](#).
- Adding a personal PTT contact by importing.  
For more information, see [Importing a PTT Contact from the Device's Contact List on page 98](#).
- Adding an administrator-managed contact from corporate global directory.  
For more information, see [Searching Corporate Global Directory Contacts on page 95](#).
- Adding a PTT contact from history.  
For more information, see [Adding a PTT Contact \(Optional\) on page 88](#).
- Adding a phone contact from history.  
For more information, see [Adding a Phone Contact \(Optional\) on page 89](#).
- Adding a new phone contact manually.  
For more information, see [Adding a New Phone Contact Manually \(Optional\) on page 98](#).
- Adding an outgoing phone contact by importing.  
For more information, see [Importing a New Phone Contact from Device's Contact List \(Optional\) on page 99](#).

### 15.5.1

## Adding a New PTT Contact Manually

If enabled by your administrator, you can add personal PTT contacts by manually entering the contact information.

To view contacts, see [View Contacts on page 95](#).

### Procedure:

1. Located at the bottom of the screen, tap **Add**.

A **Context Menu** displays.

2. To add the contact details manually, select the **New PTT Contact** option.

The **New Contact** screen displays.

3. Type a PTT number and tap **Save**.

You can also assign the contact with an avatar, a unique color, and can mark it as a favorite.



**TIP:** You can also add a contact as a favorite from the **Favorites** tab. For more information on Favorites, see [Favorites on page 91](#).

After saving, the contact appears in the contact list.

### 15.5.2

## Importing a PTT Contact from the Device's Contact List

If enabled by your administrator, you can add a personal PTT contact by importing from your device contact list.

To view contacts, see [View Contacts on page 95](#).

#### Procedure:

1. At the bottom of the screen, tap **Add**.

A **Context Menu** displays.

2. To add a PTT contact from your phone contact list, select the **Import PTT Contact** option.



**NOTE:** The first time you try to import a contact, you may be asked to allow the application permission to access the contact list.

The **Select Contact** screen displays.

3. Select a contact from **Contacts**.

You can also assign the contact with an avatar, a unique color, and can mark it as favorite.

The **New Contact** screen displays.

4. To save the new contact, tap **Save**.

The contact appears in the **PTT Contacts** list.

### 15.5.3

## Adding a New Phone Contact Manually (Optional)

If enabled by your administrator, you can add personal contacts by manually entering the contact information.

#### Procedure:

1. At the bottom of the screen, tap **Add**.

A **Context Menu** displays.

2. Tap the **New Phone Contact** option.


3. Type the new contact name.

4. Navigate down to the **Phone Number**.

5. Type a phone number.

6. To save the contact, tap the **Save** option.

You can also assign the contact with an avatar, a unique color, and can mark it as a favorite.

 **TIP:** You can also add a contact as a favorite from the **Favorites** tab. For more information on Favorites, see [Favorites on page 91](#).

#### 15.5.4

## Importing a New Phone Contact from Device's Contact List (Optional)


If enabled by your administrator, you can add an outgoing VoIP contact from your device contact list that you can use to make an outgoing VoIP call from within the application. This feature is optional and may not be available from your service provider.

### Procedure:

1. At the bottom of the screen, tap the **Add**.


A **Context Menu** displays.

2. To add a contact from your phone contact list, select the **Import Phone Contact** option.

 **NOTE:** The first time you try to import a contact, you may be asked to allow the application permission to access the contact list.

3. Select a contact from **Contacts**.

The **New Contact** screen displays.

 **NOTE:** You can also assign the contact with an avatar, a unique color, and can mark it as a favorite.

4. To save the new contact, tap **Save**.

The contact appears in the **PTT Contacts** list.

#### 15.6

## Edit Contact Details

You can only edit contacts that you create yourself. An administrator-managed contact name cannot be edited. However, you can add or change an avatar, add or change a color, and add a contact to favorites.

To view the **Contact Details**, see [View Contacts on page 95](#).


From the **Contact Details** screen, you can perform any of the following tasks listed within this section:

- [Editing a Contact Name on page 100](#)
- [Adding or Changing a Contact Avatar on page 100](#)
- [Changing Contact Color on page 100](#)
- [Make Contact a Favorite or Remove as a Favorite on page 100](#)

### 15.6.1

## Editing a Contact Name


### Procedure:

1. Tap the contact name field.  
 **TIP:** A contact name with an underline indicates that you can edit the field. Administrator-managed contacts cannot be edited.
2. Type the contact name by using the on-screen keyboard.
3. When finished, tap **Save** or continue to change other contact details.

### 15.6.2

## Adding or Changing a Contact Avatar

### Procedure:

1. Tap the **Avatar** option.  
For a list of all avatars available and their definitions, see [Avatar Icons on page 43](#).  
The **Select Avatar** screen displays.
2. Select an avatar from the list.  
You can also take a photo or select an image from your phone's gallery using the buttons at the bottom of the screen.  
 **NOTE:** The first time you try to take a photo, you may be asked to allow the application permission to access the gallery.
3. On the **Contact Details** screen, tap the **Save**.  
The selected avatar is assigned to the contact and displayed next to the contact name.

### 15.6.3

## Changing Contact Color

### Procedure:

1. Select a color from the list.
2. In the **Contact Details** screen, tap the **Save**.

**Result:** The selected color is assigned to the contact.

### 15.6.4

## Make Contact a Favorite or Remove as a Favorite

You can add contacts to the favorites list for the contacts that you created and contacts that are administrator-managed. You can add contacts by using the **Contact Details** screen. Additionally, you can make the contact a favorite or remove it from the **Favorites**.

Favorites can also be added using the **Favorites** tab. For information, see [Favorites on page 91](#).

## 15.7

# Deleting a Contact

You can only delete contacts that you create yourself. An administrator-managed contact cannot be deleted.

### Procedure:

1. From the Contact Details, tap the **Delete** option located at the bottom of the screen.
2. Perform one of the following actions:
  - To delete, tap **Yes**. The contact is removed from the Contacts list.
  - To cancel without deleting the contact, tap **No**.



**NOTE:** If you are removing a contact which is also a favorite, you see the following confirmation message

The contact x is a favorite. Deleting it will result in deleting the Favorite also? Continue?.

## Chapter 16

# Talkgroups

This section describes the Push-to-Talk (PTT) talkgroups by using the PTT application.

The PTT talkgroups are separate from the **Contacts** on the phone. There are two types of talkgroups: those that are managed by an administrator and those that are managed by the user on the phone.

## Administrator-Managed Talkgroups

Your administrator manages PTT talkgroups. Administrator-managed talkgroups cannot be deleted or changed from within the PTT application.

## Personal Talkgroups

Personal talkgroups are created from the PTT Contacts list. You manage personal talkgroups within the PTT application. You may not have the ability to create personal talkgroups if your administrator has restricted this feature.

## Maximum Number of Allowed Talkgroups

The maximum number of Administrator-Managed talkgroups allowed on your phone is **100**.

The maximum number of is **250** or more depending on group type configuration by Administrator.

The maximum number of personal talkgroups allowed on your phone is **30**.

The maximum number of members per personal talkgroup allowed on your phone is **30**.

### 16.1

## Talkgroup Icons

Talkgroup icons can help you locate the information you need.

For more information on the Talkgroup icons, see [Talkgroup Icons on page 49](#).

### 16.2

## Search Talkgroups

You can use the search box to search for talkgroups.

For more information on searching for talkgroups, see [Searching on page 40](#).


### 16.3

## View Talkgroups

The **Talkgroups** tab shows a list of all your personal talkgroups and talkgroups added by an administrator. Icons are shown next to the talkgroups, which are a broadcaster, supervisor, an Interop talkgroup, location

tracking, and talkgroup scan priority. You can toggle the favorite state of the talkgroup from the **Talkgroup List**.

**Figure 24: Talkgroups**



## 16.4

# Call Permissions

There are three types of call permissions can be assigned by an administrator to a talkgroup member as follows.

**Table 20: Call Permissions**

Function	Permission	Description
<b>In Call</b>	Listen and Talk	The PTT user is allowed to listen to the PTT call, as well as to transmit or talk to the active PTT call. <i>Listen and Talk</i> is the default permission to all the talkgroup members.
	Listen Only	The PTT user is only allowed to listen to the PTT call but not allowed to transmit or talk to the active PTT call.
<b>Call Initiation</b>	Allow	The PTT user is allowed to initiate a new PTT call to the predefined talkgroup. The PTT user is also allowed to rejoin to the call that is missed due to network issues, busy in another call, and other reasons. <i>Allow</i> is the default permission for all talkgroup members.
	Do not Allow	The PTT user is not allowed to initiate new PTT call or rejoin existing active PTT call.
<b>Call Receiving</b>	Allow	The PTT user is configured to receive all the calls on the predefined talkgroup that user is a member. The PTT user is paged

Function	Permission	Description
		for all the calls that are initiated on the talkgroup by other members. There is no retry for paging if the user missed the call for any reason. <code>Allow</code> is the default permission to all the talkgroup members.
	<code>Do not Allow</code>	The PTT user is not allowed to receive any incoming PTT calls. The PTT user is not paged for any calls that are initiated on that talkgroup by other members.

## 16.5

# Dynamic Area-Based Talkgroups (Optional)

Optional features may not be included in your PTT service plan.

Dynamic area-based talkgroups are setup and managed by a dispatch user. It is available to members dynamically while the user is in a geographical area, as defined by a dispatch user. As talkgroup members enter a geographic area, the talkgroup is shared and shown in the top of the channel list. The member list cannot be viewed by talkgroup members. Members are allowed PTT call origination and messaging within the talkgroup. Members receive notifications upon entering and exiting the talkgroup. Area-based talkgroups are in addition to the maximum number of configured talkgroups for the device.

You receive calls for area-based talkgroups when talkgroup scanning is turned off or on. Dynamic area-based talkgroup calls are received while they are active and your selected talkgroup is not in an active call.



**NOTE:** PTT users leaving the area while on a call, do not automatically drop. Similarly, when entering the area, if there is an existing call, PTT users are not added to the call but start receiving new calls after entering the area.

## 16.6

# Viewing Talkgroup Details

You can view talkgroup details from the **Talkgroups** screen.

### Procedure:

1. Select a talkgroup from the **Talkgroups**, touch and hold.  
A **Context Menu** displays.
2. Tap the **Details** option in the menu.  
The **Talkgroup Details** screen appears.



### 16.6.1

## Broadcast Talkgroup Details (Broadcasters only)

Broadcast talkgroups are managed by your administrator and can have a large number of members. Talkgroup members cannot be viewed, but a count of talkgroup members is provided while viewing talkgroup details.

### 16.7

## Adding a Talkgroup

You can create your personal talkgroups unless restricted by an administrator.

### Procedure:

1. From the **Groups** tab, tap the **Add** button located at the bottom of the screen to add the talkgroup details manually.

The New Group screen displays.



**NOTE:** A talkgroup can also be created from the history entry for a quick group call by go to the history list, find the quick group and tap and hold on the quick group history entry and selecting the Add Group option.

2. Tap the **Name** text box to enter a talkgroup name using the on-screen keyboard.
3. Tap on **Add Members**.

The Select Group Members list displays.

4. Select members from the Select Group Members screen and tap the **Save** button located at the top of the screen.



**TIP:** You can only add contacts already in your contacts list as talkgroup members. If you do not find the name of the talkgroup member you want to add, you may need to create a contact first. See the [Contact Additions on page 97](#) section for more information on adding contacts.

5. The talkgroup can also be assigned with an avatar, a unique color, and add as a favorite.



**TIP:** You can also add a talkgroup as a favorite from the Favorites tab. For more information on Favorites, see the [Favorites on page 91](#) section.

6. Tap the **Save** button when finished to save the new talkgroup.

The talkgroup appears in the talkgroup list.

### 16.8

## Editing Talkgroup Details

You can only edit groups that you create yourself. An administrator-managed talkgroup name cannot be edited. However, you can add or change an avatar, add or change a color, and add a talkgroup to favorites.

To view the **Group Details**, see [Viewing Talkgroup Details on page 104](#).

### Procedure:

From the **Group Details** screen, you can perform any of the following tasks listed within this section:

- [Editing a Talkgroup Name on page 106](#)


- [Adding One or More Members to a Talkgroup on page 106](#)
- [Removing a Member from a Talkgroup on page 106](#)
- [Renaming a Talkgroup Member on page 107](#)
- [Adding or Changing a Talkgroup Avatar on page 108](#)
- [Changing Talkgroup Color on page 108](#)
- [Make Talkgroup a Favorite or Remove as a Favorite on page 108](#)

### 16.8.1

## Editing a Talkgroup Name

You can edit your personal talkgroups but not administrator-managed talkgroups.

### Procedure:

1. Tap on the **Group name** field.  
 **TIP:** A talkgroup name with an underline indicates that the field can be edited. administrator-managed talkgroups cannot be edited.
2. Type the talkgroup name using the on-screen keyboard.
3. Tap **Save** button, otherwise, continue.

### 16.8.2

## Adding One or More Members to a Talkgroup

You can add one or more members to your talkgroups but not to administrator-managed talkgroups.

### Procedure:

1. Tap **Add Members** button to add contacts to the talkgroup.  
The **Select Group Members** screen displays.
2. Select one or more contacts to add to the talkgroup.
3. Tap **Save** button located on the top of the screen.
4. If finished, tap **Save** button on the **Group Details** screen and a 'Group updated' message displays, otherwise, continue.


### 16.8.3

## Removing a Member from a Talkgroup

You can only remove a member from a talkgroup that you created. Talkgroups that are administrator assigned cannot be edited.

### When and where to use:

### Procedure:

1. Touch and hold the member to remove.  
A Context Menu displays.  
 **TIP:** A talkgroup name with an underline indicates a personal talkgroup and therefore, can be edited. administrator-managed talkgroups cannot be edited.

2. Tap **Remove Member** option.

A confirmation dialog displays,

This group member will be removed from the group. Continue?

3. Perform one of the following actions:

- Select **Yes** if you want to remove the member.
- **No** if you want to cancel.

4. Repeat [step 1](#) through [step 3](#) for other talkgroup members you want to remove.



**NOTE:** When you remove the last member of a talkgroup, the talkgroup is deleted upon saving the changes. A confirmation dialog shows when you remove the last member to let you know this happens.

5. After removing the talkgroup member(s), tap the **Back** button located on the top of the screen or phone **Back** button to return to the Group Details screen.
6. If finished, tap the **Save** button located on the top of the screen and a `Group updated message` displays, otherwise, continue.

#### 16.8.4

## Renaming a Talkgroup Member

Talkgroup member names are set when the talkgroup is created. Changing a contact name in the PTT Contacts list will not change the name of a talkgroup member. Follow the instructions in this section to rename a talkgroup member.

### When and where to use:

#### Procedure:

1. Touch and hold the member to rename.

A Context Menu displays.



**TIP:** A talkgroup name with an underline indicates a personal talkgroup and therefore, can be edited. Administrator-managed talkgroups cannot be edited.

2. Tap **Rename Member** option.

A confirmation dialog is displayed.

3. Edit the name.

4. Perform one of the following actions:

- Tap **Save** to save the edits.
- Tap **Cancel** to start over.

5. Tap the **Back** button located on the top of the screen to return to the **Group Details** screen.

6. If finished, tap the **Save** button on the top of the screen to save, and a `Group updated message` displays, otherwise, continue.

### 16.8.5

## Adding or Changing a Talkgroup Avatar

You can edit the talkgroup avatar for the talkgroups that you created yourself and talkgroups that are administrator-managed.

#### Procedure:

1. Tap the **Avatar** option. For a list of all avatars available and their definitions, see the [Avatar Icons on page 43](#) section.

The **Select Avatar** screen displays.

2. Select an avatar from the list.

You can also take a photo or select an image from your phone's gallery using the buttons at the bottom of the screen.



**NOTE:** The first time you try to take a photo, you may be asked to allow the application permission to access the gallery.

3. If finished, tap the **Save** button on the **Group Details** screen, and the selected avatar is assigned to the talkgroup, otherwise, continue.

### 16.8.6

## Changing Talkgroup Color

You can edit the talkgroup colors for the talkgroups that you created yourself and talkgroups that are administrator-managed.

#### Procedure:

1. Select a color from the list.
2. On the **Group Details** screen, tap **Save**, otherwise, continue.

The selected color is assigned to the talkgroup.

### 16.8.7

## Make Talkgroup a Favorite or Remove as a Favorite

You can add talkgroups to the favorites list for the talkgroups that you created yourself and talkgroups that are administrator-managed. Talkgroups can be added using the **Group Details** screen.

Favorites can also be added using the **Favorites** tab. For more information, see [Favorites on page 91](#).

### 16.9

## Deleting a Talkgroup

You can only delete personal talkgroups you have created. Administrator-managed talkgroups cannot be removed.

#### Procedure:

1. From the **Group Details**, located at the bottom of the screen, tap **Delete**.
2. Perform one of the following actions:
  - To delete the talkgroup, tap **Yes**.

The talkgroup is removed from the **Talkgroups** list.



**NOTE:**

If you are removing a talkgroup, which is also a favorite, you can see the following confirmation message:

The group x is a favorite, deleting it will result in deleting the favorite also, are you sure?

- To cancel without deleting the talkgroup, tap **No**.
- 3. To delete the talkgroup, tap **Yes**.

The talkgroup is deleted from the **Talkgroups** list.

## Chapter 17

# Talkgroup Scanning

This section describes Talkgroup Scanning using the Push-to-Talk (PTT) application and is organized as follows:

- [Turning Scanning On or Off on page 110](#)
- [Adding Talkgroups to Scan Lists on page 111](#)
- [Removing Talkgroups from Scan Lists or Changing the Scanning Priority on page 112](#)

Talkgroup Scanning allows the phone of a subscriber to scan through the scan list of corporate talkgroups for calls and up to three talkgroups that can be assigned as priority (1–3) talkgroups. The higher priority talkgroup calls take precedence over lower priority talkgroup calls. Talkgroups that are not in the scan lists do not barge in when Scanning is on.

While you have Talkgroup Scanning turned on, you can see the following behavior:

- Calls from the scanned talkgroup are received normally. When the current scanned talkgroup call ends, you automatically hear the next active scanned talkgroup call in progress. You do not get missed call alerts for talkgroup calls while scanning is turned on.
- Quick Group calls are received normally. A missed call alert is provided if you are busy on another Push-to-Talk (PTT) call or a cellular call.
- One-to-one calls are received normally. A missed call alert is provided if you are busy on another PTT call or a cellular call.
- All call types can be originated: one-to-one, Quick Group, and talkgroup calls.
- Normal call rejoin occurs for originated talkgroup calls.



**NOTE:** You cannot receive Missed Call Alerts for talkgroup calls while scanning, so calling a talkgroup may result in a call rejoin.

### 17.1

## Turning Scanning On or Off

To turn on Talkgroup Scan, you can tap the **Talkgroup Scan** toggle on the menu from the **OFF** state to the **ON** state.


### Procedure:


- To turn on Talkgroup Scan, tap the **Talkgroup Scan** toggle on the menu from the **OFF** state to the **ON** state.

When Talkgroup Scan is turned **ON**, a scan list icon shows on the **Talkgroup** tab row, and during a call, the title bar shows the priority of the talkgroup. Also, if any talkgroups have priorities that you have assigned, the priority (1-3) is displayed on the talkgroup button. When Talkgroup Scan is turned off, the Scan List icon disappears from the **Call Status** on the **Main** screen, and all assigned priorities disappear.

The talkgroup list shows in priority order at the top followed by the rest of the talkgroups in alphabetical order.

**Figure 25: Talkgroup Scanning**



 **NOTE:** When Talkgroup Scan is ON, pressing a PTT key accessory ends the current call if active and allow you to originate a call on the selected talkgroup.

- To turn off Talkgroup Scan, tap the **Talkgroup Scan** toggle on the menu from the **ON** state to the **OFF** state.

## 17.2


# Adding Talkgroups to Scan Lists

You can add talkgroups to scan lists.

### Procedure:

1. Touch and hold on the talkgroup that you want to add to the scan list.  
A Context Menu is shown.

2. Tap the **Scan List** option.  
The scan list priority options display.

 **NOTE:** Only corporate groups given by your administrator can be scanned.

3. Tap the priority option you want to assign to the talkgroup or select **Normal Priority** if you want the talkgroup to be of normal priority (in other words, not a priority scan talkgroup).  
If you choose a priority that is already being used by another talkgroup, a message displays, *A group with priority 1 already exists. Make the group priority 1?*
4. Perform one of the following actions:
  - Select **Yes** to assign the existing priority to the current talkgroup.

- Select **No** to assign the talkgroup a new priority.

Once you assign a priority to a talkgroup, a priority icon appears next to the scanned talkgroup.



**NOTE:** Choosing a priority used by another talkgroup makes the previous priority talkgroup stay in the scan list with normal priority.

### 17.3

## Removing Talkgroups from Scan Lists or Changing the Scanning Priority

You can remove talkgroups from scan lists or change the scanning priority.

#### Procedure:

1. From the **Groups** tab, touch and hold on the talkgroup that you want to remove or change the scanning priority.
2. Tap the **Scan List** option.  
A pop-up menu appears.
3. You can reassign the priority by touching a priority option.
  - To make the talkgroup normal priority, tap **Normal Priority**.
  - To remove the talkgroup from the scan list, tap **Remove**.

If you choose a priority that is already being used by another talkgroup, a message similar to the following displays:

A group with priority 1 already exists. Make the group priority 1?



**NOTE:** Choosing a priority used by another talkgroup makes the previous priority talkgroup stay in the scan list with normal priority.

4. Perform one of the following actions:
  - Select **Yes** to assign the existing priority to the current talkgroup.
  - Select **No** to assign the talkgroup a new priority. The previously Priority 1 assigned talkgroup is moved to No priority talkgroup.



## Chapter 18


# Map

This section describes the Push-to-Talk (PTT) Map and share their location or send an arbitrary location. The map is available to all individuals. The map is accessible when you select a contact or talkgroup. However, a talkgroup supervisor that has Location Capability turned on by your administrator can view talkgroup members' location on the map.

This section is organized as follows:

- [Map Icons on page 113](#)
- [Search Map on page 114](#)
- [Recenter the Map on page 114](#)
- [Individuals on page 114](#)
  - [Sending My Location or an Arbitrary Location to a Contact on page 114](#)
  - [Sending My Location or an Arbitrary Location to a Quick Group on page 115](#)
  - [Sending My Location or an Arbitrary Location to a Talkgroup on page 115](#)
- [Supervisor with Location Capability on page 116](#)
  - [Talkgroup Member Location on page 116](#)
  - [Boundary on page 120](#)
  - [Creating a Quick Group from the Map on page 125](#)

**Figure 26: Map**



### 18.1

## Map Icons

Map icons can help you locate information you need.

For more information on the map icons, see [Map Icons on page 49](#).

## 18.2

# Search Map

You can use the search box to search for addresses or places.

For more information on searching in the map, see [Map Icons on page 49](#).

## 18.3

# Recenter the Map

You can recenter the map to your current location. The **My Location** button shows whenever the map is not centered on your current location at the default zoom. When recentering the map, the zoom level is set to the default zoom.

You can tap the **My Location** button located on the map. The map returns to the center.

## 18.4

# Individuals

The map display allows an individual to check their current location on the map and share their location or send an arbitrary location. You can share your location with a contact, quick group, or talkgroup. You can only share your location or some other location.



**TIP:** You can also share your location from the **Call** screen by tapping the **Map Pin** located at the bottom of the screen. The **My Location** screen displays. You can share your location, by tapping **Share Location**.

### 18.4.1


# Sending My Location or an Arbitrary Location to a Contact

## Procedure:

1. Tap the **My Location Pin** (Blue).

The **My Location** displays.

**Figure 27: My Location**



2. Perform one of the following actions:
  - Move the map.
  - Use a location search to find an arbitrary location.

3. Tap the **Share** button to share my location.  
Share my location menu displays.
4. Choose the **Send to Contact** option.  
The **Send to Contact** displays.
5. Tap the contact to select the one you want to share your location.  
The following message displays: `Location Sent`


#### 18.4.2

## Sending My Location or an Arbitrary Location to a Quick Group

### Procedure:

1. Tap the **My Location Pin** (Blue).  
The **My Location** displays.

**Figure 28: My Location**



2. Perform one of the following actions:
  - Move the map.
  - Use a location search to find an arbitrary location.
3. Tap the **Share** button to share my location.  
Share my location menu displays.
4. Choose the **Send to Quick Group** option.  
The **Send to Quick Group** displays
5. Tap the two or more contacts to select the one you want to share your location.  
The following message displays: `Location Sent`


#### 18.4.3

## Sending My Location or an Arbitrary Location to a Talkgroup

### Procedure:

1. Tap the **My Location Pin** (Blue).  
The **My Location** displays.

**Figure 29: My Location**



2. To share my location, tap the **Share** button.  
The **Share My Location** menu displays.
3. Choose the **Send to Group** option.  
The **Send Location to Group** displays.
4. Tap the talkgroup to select the one you want to share your location.  
The following message displays: **Location Sent**.

## 18.5

# Supervisor with Location Capability

The supervisor can share their location, not share the location of talkgroup members, or send an arbitrary location.

A supervisor can also create a boundary for a talkgroup, receive notifications when members enter or leave the boundary, view talkgroup presence of members, and call a talkgroup member. Multiple supervisors in a talkgroup can have Location Capability.



**TIP:** As a supervisor, you can also access the map from the **Groups** tab by tapping the talkgroup, which has a map pin. The **Call** screen displays. To access the map, you can tap **Talkgroup Location**.

### 18.5.1

## Talkgroup Member Location

A supervisor can view the current talkgroup member location on the map with automatic refresh of the location. Location Capability must be turned on by your administrator at the talkgroup level. Multiple supervisors per talkgroup are allowed to have Location Capability.


#### 18.5.1.1

### Viewing Talkgroup Member Locations

#### Procedure:

1. From within the **Map** tab, tap **Tracked Group Selector**.  
The **Tracked Group Selector** button is turned off for anyone who is not a supervisor with Location Capability privilege.  
A pop-up menu listing all groups you have permission to locate is displayed.


**Figure 30: Groups with Location Capability**



2. Tap the talkgroup to locate the talkgroup member location.

The map displays with all members of the selected talkgroup and their location.

**Figure 31: Talkgroup Member Location**



### 18.5.1.2

## Viewing Talkgroup Member Location Details


**Prerequisites:** You must complete the procedure in [Viewing Talkgroup Member Locations](#) on page 116.


**Procedure:**

Tap any **Pin**.

The name of the member and location displays.

**Figure 32: View a Talkgroup Members Location Details**



 **TIP:** Tap the pin again or x or anywhere on the map to dismiss.

18.5.1.3


## Calling a Talkgroup Member

 **TIP:** You can also access the map from the **Groups** tab by tapping the talkgroup, which has a map pin. The **Call** screen displays.

**Procedure:**

1. To access the map, tap the **Talkgroup Location**.
2. Follow the procedure in [Viewing Talkgroup Member Location Details on page 117](#).
3. Tap any **Pin**.  
The talkgroup members **Location Details** screen displays with the name of the member and location.

**Figure 33: View a Talkgroup Members Location Details**



**4. Tap Call.**

The **Call** screen displays.

**18.5.1.4**

## Sharing Your Location or an Arbitrary Location to a Talkgroup with Location Capability


Move the map or search the map for a location. The pin turns orange and details show **Pin Location**. You can tap **Share**.

**Procedure:**

**1. Tap Tracked Group Selector.**


The list of talkgroups with **Location Capability** pop-up displays.

**Figure 34: Groups with Location Capability**



2. Choose a talkgroup to view talkgroup member locations from the list.
3. Tap the **My Location Pin** (Blue).  
To send an arbitrary location, move the map or search for a location.  
The **My Location** displays.

**Figure 35: My Location**



4. To share your location, tap **Share**.  
The pin location is sent to the talkgroup.

### 18.5.2

## Boundary

Allows a PTT supervisor to create a boundary for a talkgroup and receive notifications when members enter or leave the boundary. Members can optionally receive notifications when they enter or leave. You can also refresh the location and modify an existing boundary set for a talkgroup. The **Active Boundary Time** setting controls how long a boundary is active.

This section is organized as follows:

- [Creating a Boundary on page 121](#)
- [Recentering Boundary on the Map on page 122](#)
- [Recentering the Map to your Location on page 123](#)



- [Boundary Settings on page 123](#)
  - [Changing Boundary Settings on page 123](#)
  - [Changing Update Interval on page 124](#)
  - [Changing Active Boundary Time on page 124](#)
  - [Changing Notify Me Setting on page 124](#)
  - [Changing Notify Me Setting on page 124](#)
  - [Changing Notify Member Setting on page 125](#)
  - [Changing Initial Member Notification Setting on page 125](#)


### 18.5.2.1

## Creating a Boundary

### Procedure:


1. From within the **Map** tab, tap **Tracked Group Selector**.  
The list of talkgroups displays.
2. Choose a talkgroup to view talkgroup member locations from the list.  
The **Set Boundary** pop-over displays.

**Figure 36: Set Boundary Popover**



3. Tap **Set Boundary**.  
The **Set Boundary** pop-over displays along with a boundary preview (blue circle).

**Figure 37: Boundary Preview**



4. Set the boundary size by zooming in or out.  
You can see the boundary radius in the pop-over.
5. Set the boundary center by moving the map or searching.
6. Tap the **Set Boundary** toggle to turn **ON** the boundary.


If you are setting a boundary at your current location as shown by the My Location Pin (Blue), you can set the boundary type. If you set a boundary at some other location, then boundary stays at that location.

The following confirmation message displays: A boundary will be created around your current location. Do you want the boundary center to move with you or stay here?

7. Select one of the following boundary types:
  - **Stay here:** The **Stay here** boundary type is created at an arbitrary location and a static boundary with center selected.
  - **Follow me:** The **Follow me** boundary type is created at your current location, and the boundary moves as you move.

The Fence boundary on status message displays and the map is updated with the boundary **ON**.

**Figure 38: Boundary ON**



### 18.5.2.2

## Recentering Boundary on the Map

When the boundary is **ON** (active), you can recenter the map with the boundary visible.

#### Procedure:

- In the **Set Boundary** pop-over, to recenter the boundary on the map, tap **My Location**.

### 18.5.2.3

## Recentering the Map to your Location

When the boundary is **ON** (active), you can recenter the map to your location.

### Procedure:


On the lower left side of the map, tap the **My Location** button located.

**Result:** The map recenters to my location while the boundary is off and the map recenters to boundary center while the boundary is on.

### 18.5.2.4

## Boundary Settings

All **Boundary** settings are shown in the default state. You can change the **Boundary** settings while the boundary is inactive.

 **NOTE:** Changing the **Boundary** settings requires you to turn off the boundary. You can change the **Boundary** settings while the boundary is inactive. To turn off the boundary, you can tap the **Set Boundary** toggle to the **OFF** state.

This section contains the following boundary settings:

- [Changing Boundary Settings on page 123](#)
- [Changing Update Interval on page 124](#)
- [Changing Active Boundary Time on page 124](#)
- [Changing Notify Me Setting on page 124](#)
- [Changing Notify Member Setting on page 125](#)
- [Changing Initial Member Notification Setting on page 125](#)

### 18.5.2.4.1

## Changing Boundary Settings


All **Boundary** settings can be changed in the map set boundary settings.

### Procedure:

1. From within the **Map**, tap **Map Boundary Enable**.

The **Set Boundary** pop-over displays.

**Figure 39: Set Boundary Popover**



2. Tap the **Settings** button.

The **Boundary Settings** displays.

3. Find the settings you want to change and follow the instructions.

#### 18.5.2.4.2

### Changing Update Interval

This setting allows you to set how often each talkgroup member location reports their location. Range: 1 to 60 minutes.



**NOTE:** Smaller intervals shorten the battery life for talkgroup members.

#### Procedure:

1. From the **Boundary Settings** screen, scroll to and tap the **Update Interval** settings.  
The **Update Interval Settings Options** displays.
2. Tap the **minutes** text box.
3. To set how often the talkgroup member location is updated, type a number in the range from 1 to 60 minutes using the on-screen keyboard.
4. Located in the upper-left screen to return to the map, tap **Back**.

#### 18.5.2.4.3

### Changing Active Boundary Time

This setting allows you to set how long the boundary is active. The boundary automatically turns off after the boundary time has expired. Range: 1 hour to 7 days.

#### Procedure:

1. From the **Boundary Settings** screen, scroll to and tap the **Active Boundary Time** settings.  
The **Active Boundary Time Settings Options** displays.
2. To set how long the boundary is active, tap the **Days** text box.  
The time must be up to seven days.
3. To set how long the boundary is active, tap the **Hours** text box.  
The time must be up to 168 hours.



**NOTE:** You cannot exceed a maximum total of seven days or 168 hours combined.

4. To return to the map, located in the upper-left screen, tap **Back**.

#### 18.5.2.4.4

### Changing Notify Me Setting

This setting allows you to set if you, as the boundary owner, are notified when a talkgroup member crosses the boundary when the boundary is on.



**NOTE:** Boundary alerts are simple notifications and are included in history.

#### Procedure:

1. From the **Boundary Settings** screen, scroll to the **Notify Me** settings.
2. To toggle the state of the setting, tap the **On/Off**.

#### 18.5.2.4.5

### Changing Notify Member Setting

This setting allows you to set if a talkgroup member is automatically sent a notification when entering and leaving the defined boundary when the boundary is active.

#### Procedure:

1. From the **Boundary Settings** screen, scroll to the **Notify Member** settings.
2. To toggle the state of the setting, tap **On/Off**.
3. Continue with [Changing Initial Member Notification Setting on page 125](#).

#### 18.5.2.4.6

### Changing Initial Member Notification Setting

This setting allows you to set if talkgroup members automatically receive an initial notification when a boundary is created for those inside or outside the boundary.

**Prerequisites:** The **Notify Member** setting must be turned on to use this setting. For more information, see [Changing Notify Member Setting on page 125](#)

#### Procedure:

1. Scroll to and tap the **Initial Member Notification** settings.  
The **Initial Member Notification Setting Options** displays.
2. Perform one of the following actions:
  - To send the first notification to members outside the boundary, tap **Outside Boundary**.
  - To send the first notification to members inside the boundary, tap **Inside Boundary**.
3. Tap **OK**.

#### 18.5.3


### Creating a Quick Group from the Map

You can create a Quick Group by selecting members from the map. This action allows you to choose members based on their location. You can also add other members from your contacts.

#### Procedure:

1. From the map, tap the **Tracked Group Selector** button on the action bar.

**Figure 40: Map**



2. On the action bar, tap **Quick Group**.
3. Zoom in until you view all the contacts that you want to select.




**TIP:** You can also tap any group member to select them and add them to the member list.




**NOTE:** A Quick Group can have up to 10 members. If you have more than 10 members in view, you cannot select all at once. You can zoom in so that there are less than 10 members in view, select all or select the members individually,

**Figure 41: Create Quick Group from Map**



4. Tap the **Select All in View** for a Mobile Quick Group.  
All selected contact pins turn purple.

**Figure 42: Create Quick Group from Map**



5. After selecting the group members, in the title bar, tap the **Save**.  
The **Call** screen displays.
6. Press and hold the PTT button.  
A Quick Group Call is started, a chirp tone is heard and the **PTT** button changes color, indicating you have taken the floor.
7. To allow the other members of the group to take the floor and speak, release the **PTT** button.
8. To end the call, tap the **End Call**.

#### 18.5.3.1

### Adding Members to a Quick Group

**Prerequisites:** You must follow the procedure in [Creating a Quick Group from the Map on page 125](#).

**Procedure:**

1. Tap or touch **Add Members**.  
The **Add Members** screen displays.
2. Select the additional members to add from the **Group Members** or **Contacts**.
3. Tap or touch **Save**.

### 18.5.3.2

## Removing Quick Group Members

### Procedure:

1. Tap or touch the **Quick Group List** button.  
The **Quick Group List** displays.
2. Tap or touch the members to remove.
3. Tap or touch **Save**.  
The **Quick Group Call** screen displays.



## Chapter 19

# Integrated Secure Messaging

This section describes Push-to-Talk (PTT) Integrated Secure Messaging.

This section is organized as follows:

- [Integrated Secure Messaging Icons on page 130](#)
- [Multimedia Content on page 130](#)
  - [Text Messages on page 130](#)
  - [Image Messaging on page 140](#)
  - [Video Messaging on page 141](#)
  - [Voice Messaging on page 141](#)
  - [File Messaging on page 143](#)
  - [Receiving a Location Message on page 144](#)
- [Message Actions on page 144](#)

3GPP MCDATA compliant Integrated Secure Messaging allows you to send and receive secure text messages, multimedia content, and location information to and from other PTT users.

Messages are delivered to recipients while they are online. If a recipient is offline, then messages wait to be delivered for up to a week until the recipient logs in and becomes online. After a message notification is received for multimedia messages, you have up to 30 days to download the image, video, voice message, or file.

For MCPTT users, messages are only delivered to recipients who are affiliated to the group. Delivery of messages while offline does not apply.



**NOTE:** Release 12.3 introduces the 3GPP MCDATA compliant messaging solution. Users upgrading from previous release versions go under migration – one-time, one-way migration – when logged in for the first time to the 12.3 version of the application. All existing messages that are downloaded to the device up to 20,000 within two years and all messages stored in the cloud for shared device users are migrated. Previously unread messages are marked read during the migration.



**NOTE:** The notification time for messages to be delivered may vary depending on the service provider. The time a multimedia message is available for download is set by the service provider.

Multimedia content can include text, images, videos, voice, and files. Location messages allow you to send and receive location information.



**NOTE:** You can send messages to other users if you have the feature enabled. However, your administrator may disable your ability to send and receive text, text and multimedia, or location messages.

Your network operator may not allow a user to save any incoming message attachments to the local device memory; therefore, the SAVE button would not be visible.

While drafting a message if the PTT application is interrupted by another application or by an incoming PTT call, the user can continue with composing the message after the user returns to the PTT application or when the PTT call ends.

When you send messages, you see the status of the message. The message status shows one of the following:

**Pending**

Indicates that the message is waiting to be sent. Any messages that are created while the network connection is not available are preserved until the network connection is restored and then sent.

**Sent**

Indicates that the message was sent from your device.

**Delivered**

For 1:1 messages only, indicates that the message was delivered to the recipient. This status does not mean that the user downloaded any multimedia, however 3GPP MCDATA messaging marks messages as delivered when multimedia attachment is downloaded.

**Failed**

Indicates that the message could not be sent. This failure can happen if the recipient is not allowed to receive messages or if there was a problem sending the message from your device.



**NOTE:** There is no delivery status for talkgroup messages.

## 19.1

## Integrated Secure Messaging Icons

You can use the integrated secure messaging icons to locate the information you need.

For more information on the Integrated Secure Messaging icons, see [Integrated Secure Messaging Icons on page 48](#).

## 19.2

## Multimedia Content

Multimedia content includes files as a message attachment. All multimedia content is automatically compressed before sending. Multimedia messages are also shown in threaded history along with call history.



**NOTE:** The multimedia attachment size configuration includes the messaging overhead. For example, with 20 MB of size configuration, actual multimedia that can be sent are approximately 17-18 MB in size.

The maximum multimedia attachment size that can be transferred (originated or received) is 5 MB using cellular and 20 MB using Wi-Fi. If file size is exceeded, you receive an error message.



**NOTE:** The multimedia attachment size configuration includes the messaging overhead. For example, with 20 MB of size configuration, actual multimedia that can be sent will be approximately 17-18 MB in size.

## 19.2.1

## Text Messages

Text messages let you send a text to other PTT users, even if they are offline. You can reply to the sender and reply all for talkgroup messages. Messages can be forwarded to other PTT users, and delivery receipts allow the sender to see that a message was delivered.

Broadcasters can send a one-way text message to other broadcast talkgroup members. Broadcast talkgroup members cannot reply or send text messages to the talkgroup.

Text messages also show in threaded history along with call history and are sent by selecting a contact or a talkgroup.

You can also perform any of the following text message actions:


- [Sending a Text Message on page 131](#)

- [Selecting Quick Text on page 133](#)
- [Adding Quick Text on page 134](#)
- [Deleting Quick Text on page 137](#)
- [Deleting a Message on page 90](#)
- [Receiving a Text Message on page 138](#)

### 19.2.1.1

## Sending a Text Message

You can send text messages by using the **Call** screen for a selected contact, a selected talkgroup, or a contact or talkgroup context menu.


 **TIP:** Alternatively, you can send messages from the **History**.

### Procedure:


1. Perform one of the following actions:
  - Select a contact from the **Contacts List** and touch and hold.
  - Select a talkgroup from the **Talkgroup List** and tap and hold.

A **Context Menu** displays.

**Figure 43: Contact Context Menu**



**Figure 44: Talkgroup Context Menu**




2. To initiate a text message, on the **Context Menu**, select the **Message** button.
3. Type your message using the on-screen keyboard.
4. Located to the right of the message box, tap **Send**.

You can also add **Quick Text**. For more information, see [Adding Quick Text on page 134](#).

**Figure 45: Text Message Box**



 **NOTE:** While drafting a text message and tapping the **Back** button, a confirmation message display the following: `Message has not been sent.` You can either tap **Yes** to discard or **No** to cancel.

5. Your text message displays in the history details.

### 19.2.1.2

## Selecting Quick Text

Quick text is a feature that lets you save the text you can use to respond to messages quickly. You can add up to 20 messages.

### Procedure:

1. Tap the **Message** button.



**TIP:** To create a quick text, see [Adding Quick Text on page 134](#).

The text box displays.


2. Located in the text box, tap the **Quick Text Access** button.

**Figure 46: Text Box**



The **Select Quick Text** displays.


**Figure 47: Edit Quick Text**



3. Tap the desired quick text.

The selected quick text is added to your message, and the message entry box displays again.

**Figure 48: Send Quick Text**



4. To send the text, tap the **Send Text Message** button.

### 19.2.1.3


## Adding Quick Text

Quick text is a feature that lets you save the text you can use to respond to messages quickly. You can add up to 20 messages.

### Procedure:


1. Tap the **Message** button.  
The text box displays.

**Figure 49: Text Box**




2. Located in the text box, tap the **Quick Text Access** button.  
The **Select Quick Text** screen displays.

**Figure 50: Select Quick Text**




3. Tap the **Add Quick Text** button.  
The **Enter Quick Text** screen displays.

**Figure 51: Enter Quick Text**




4. Type the quick text to use.
5. Perform one of the following actions:
  - To save the quick text, tap the **Save** button.

**Figure 52: Created Quick Text**



- To cancel the operation, tap the **Cancel** button.  
The following message displays: *Your entered quick text will be cleared. Do you wish to continue?*
6. If finished, tap **Save**.
  7. Tap the newly created quick text.  
The selected quick text is added to your message, and the message entry box displays again.

**Figure 53: Send Quick Text**



8. To send the text, tap the **Send Text Message** button.




#### 19.2.1.4

## Deleting Quick Text

### Procedure:


1. Tap the **Message** button.  
The text box displays.

**Figure 54: Text Box**




2. Located in the text box, tap the **Quick Text Access** button.  
The **Select Quick Text** screen displays.

**Figure 55: Edit Quick Text**




3. Located in the upper right of the screen, tap the **Edit** button.  
The **Select Quick Text** screen displays.

**Figure 56: Delete Quick Text**



4. To delete, next to the quick text, tap the **X**.  
A confirmation dialog displays.

**Figure 57: Delete Quick Text Confirmation**



5. Perform one of the following actions:
  - To delete quick text, tap **Yes**.
  - To cancel action, tap **No**.
6. Tap **Save**.

### 19.2.1.5


## Receiving a Text Message

When you receive a text message, you receive a system notification showing the name of the sender and a preview of the text message. You can tap the notification, and the PTT application opens the history for that sender or talkgroup. You can reply to the sender and reply to all for talkgroup messages or forward them to other PTT users. Text messages are shown in threaded history along with call history.

### Procedure:

1. Perform one of the following actions:
  - Tap the system notification for the message.
  - From the **History** screen, scroll down and locate any unread messages to read. Unread messages are indicated by an unread message indicator (dot). The unread message indicator disappears when you tap the **History Details** button to reply to the message.


**Figure 58: History**



2. Tap the **History Details** button to read the message content.

**Result:** The **History Details** displays.

**Figure 59: History Details**



**TIP:** You can also reply to the sender and reply all (for talkgroup messages) and forward the message to other PTT users.

You can also perform any of the following message actions:

- [Forwarding a Message to a Contact or Talkgroup on page 145](#)
- [Forwarding a Message to a Quick Group on page 145](#)
- [Replying to a Sender on page 146](#)

- [Replying to Talkgroup \(Talkgroup Messages\) on page 146](#)
- [Sharing my Location from History on page 149](#)
- [Sending a Photo or a Video from History on page 148](#)
- [Sending a Voice Message from History on page 148](#)
- [Sending a Text Message from History on page 147](#)
- [Sending a File from History on page 149](#)
- [Deleting a Message on page 90](#)
- [Copying a Text Message from History on page 147](#)

### 19.2.2

## Image Messaging

When you receive an image message, a notification displays. Thumbnails are shown for photos, and the automatic download of attachments is based on the application settings. The recipient can reply to the sender and reply to all for talkgroup messages. You can forward messages to other PTT users, and delivery receipts allow you to see if the message was delivered.

You can also perform any of the following message actions:

- [Saving an Image Message on page 140](#)
- [Forwarding a Message to a Contact or Talkgroup on page 145](#)
- [Forwarding a Message to a Quick Group on page 145](#)
- [Replying to a Sender on page 146](#)
- [Replying to Talkgroup \(Talkgroup Messages\) on page 146](#)
- [Deleting a Message on page 90](#)

### 19.2.2.1

## Saving an Image Message

You can save a received image from any history entry on the **Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation that contains the image you want to save and tap the **History Details** button.
2. Tap the **Image**.  
The **Photo Preview** screen displays.
3. To save to the device PTT application album in the **Gallery**, tap the **Gallery** button.
4. Perform any of the following actions:
  - To forward the image to a contact, quick group, or talkgroup, tap the **Forward** button.
  - To view the name, sender, date, size, and resolution, tap the **Details** button.
  - To delete the image, tap the **Delete** button.

### 19.2.3

## Video Messaging

When you receive a video message, a notification displays. Thumbnails are shown for videos, and the automatic download of attachments is based on the application settings. The recipient can reply to the sender and reply to all for talkgroup messages. You can forward messages to other PTT users, and delivery receipts allow you to see if the message was delivered.

You can also perform any of the following message actions:

- [Saving a Video Message on page 141](#)
- [Forwarding a Message to a Contact or Talkgroup on page 145](#)
- [Forwarding a Message to a Quick Group on page 145](#)
- [Replying to a Sender on page 146](#)
- [Replying to Talkgroup \(Talkgroup Messages\) on page 146](#)
- [Deleting a Message on page 90](#)

### 19.2.3.1

## Saving a Video Message

You can save a received video message from any history entry on the **Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation that contains the video you want to save and tap the **History Details** button.
2. Tap the **Video**.  
The **Video Preview** screen displays.
3. To save to the device to the **Gallery**, tap the **Gallery** button.
4. Perform any of the following actions:
  - To play the video, tap the **Play** button.
  - To forward the video to a contact, quick group, or talkgroup, tap the **Forward** button.
  - To view the name, sender, date, size, and duration, tap the **Details** button.
  - To delete the video, tap the **Delete** button.

### 19.2.4

## Voice Messaging

A notification displays when a user receives a voice message. You can reply to the sender and reply to all for talkgroup messages. You can forward messages to other PTT users, and delivery receipts allow you to see if the message was delivered. Automatic download of attachments is based on the user settings.

#### 19.2.4.1

### Receiving a Voice Message

You can play a received voice message by tapping the message. The **Audio preview** screen displays. Tap the **Play** option to play the voice message.

#### Procedure:

1. Tap the **Play** button to play the voice message.



**NOTE:** If the message is not downloaded, tap the message and wait for the download, then tap again to display the **Audio Preview** screen.

The **Audio Preview** screen displays.

2. Optional: Perform any of the following message actions:
  - [Forwarding a Message to a Contact or Talkgroup on page 145](#)
  - [Forwarding a Message to a Quick Group on page 145](#)
  - [Replying to a Sender on page 146](#)
  - [Replying to Talkgroup \(Talkgroup Messages\) on page 146](#)
  - [Deleting a Message on page 90](#)



**NOTE:** You cannot save a received voice message on an iOS device.

#### 19.2.4.2

### Sending a Voice Message from History

You can send a voice message by recording and sending from within the PTT application. When you decide to send a voice message, you can record, preview, rerecord, erase, and send the voice message. Also, you can record a voice message from any history entry on the **History Details** screen from the **History** tab.

#### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. Located in the actions, tap the **Voice Message** button.  
A **Ready Record** screen displays.
3. Press and hold the RECORD button and begin speaking your voice message.
4. When complete, release the RECORD button.
5. To review your message, tap the **Playback** button.
6. Perform one of the following actions:
  - Located in the upper-right, tap the **Save** button.
  - To open a **Discard Confirmation** message, in upper-left, tap **Cancel** button.
7. Perform one of the following actions:
8. Perform one of the follow actions:
  - To discard voice message, tap **Yes**.
  - To return to the recorded message and the message is sent, tap **No**.

## 19.2.5

# File Messaging

A notification displays when a user receives a file message. The recipient can reply to the sender and reply to all for talkgroup messages. You can forward messages to other PTT users, and delivery receipts allow you to see if the message was delivered. The automatic download of attachments is based on the application settings.

### 19.2.5.1

## Send a File Message

You can send a file message from within the PTT application. File messages support Microsoft Office files and PDF.

To send a file message, see [Sending a File from History on page 149](#).

### 19.2.5.2

## Receive a File Message

You can view a received file message by tapping the message. The **File Preview** screen displays. You can tap the **File** icon, located in the center of the screen to view, and the built-in file viewer opens.



**TIP:** If the message is not downloaded, tap the message and wait for the download and tap again to display to **File Preview** screen.

You can also perform any of the following message actions:

- [Forwarding a Message to a Contact or Talkgroup on page 145](#)
- [Forwarding a Message to a Quick Group on page 145](#)
- [Replying to a Sender on page 146](#)
- [Replying to Talkgroup \(Talkgroup Messages\) on page 146](#)
- [Deleting a Message on page 90](#)

### 19.2.5.3

## Saving a File Message

You can save a received file from any history entry on the **Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation that contains the file you want to save and tap the **History Details** button.
2. Tap the **File**.  
The **File Preview** screen displays.
3. Located in the center of the screen to view, tap the **File** icon.  
The built-in file viewer opens.
4. Tap the **Share** icon and choose an option for sending the document, such as any installed application.

5. Tap **Save to Files** or browse a location on where to save the file.



**TIP:** Use the **File Manager** application to access the saved files.



**NOTE:** You can access files from your device storage or other installed applications, such as Apple iCloud, Dropbox, and Google Drive, and more. For more information, see the device user manual.

6. Perform any of the following actions:

- Located in the center of the screen to view, tap the **File** icon. The built-in file viewer opens.
- To forward the voice message to a contact, quick group, or talkgroup, tap the **Forward** button.
- To view the name, sender, date, and size, tap the **Details** button.
- To delete the voice message, tap the **Delete** button.

### 19.2.6

## Receiving a Location Message

When a user receives a location message, a notification displays. The recipient can reply to the sender and reply to all for talkgroup messages. You can forward messages to other PTT users, and delivery receipts allow you to see if the message was delivered. Location messages can also show in threaded history, along with the call history.

If you want to share your location on the map within the PTT application, you can select the location **Pin** icon. Your device provides the location.



**NOTE:** Location services must be turned on in the device and the application must be granted permission to use Location Services.

### Location Message Delivery

If you want to share your location, see [Sharing my Location from History on page 149](#).

### Receive a Location Message

You can view a received location message by tapping the message. The **Map** screen displays.

You can also perform any of the following message actions:

- [Forwarding a Message to a Contact or Talkgroup on page 145](#)
- [Forwarding a Message to a Quick Group on page 145](#)
- [Deleting a Message on page 90](#)

### 19.3

## Message Actions

You can send messages to offline users, who receives the messages the next time they become online. You can also send messages to any history entry.

Additionally, you can perform any of the following message actions:

- [Forwarding a Message to a Contact or Talkgroup on page 145](#)
- [Forwarding a Message to a Quick Group on page 145](#)
- [Replying to a Sender on page 146](#)
- [Replying to Talkgroup \(Talkgroup Messages\) on page 146](#)



- [Sharing my Location from History on page 149](#)
- [Sending a Photo or a Video from History on page 148](#)
- [Sending a Voice Message from History on page 148](#)
- [Sending a Text Message from History on page 147](#)
- [Sending a File from History on page 149](#)
- [Deleting a Message on page 90](#)
- [Copying a Text Message from History on page 147](#)

### 19.3.1

## Forwarding a Message to a Contact or Talkgroup

You can forward a message to a contact on the **History Details** from the **History** tab.

#### Procedure:

1. From the **History**, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. Tap and hold the message entry you want to forward.  
A **Context Menu** displays.
3. Perform one of the following actions:
  - To open the **Select Contact to Message** screen, tap the **Forward to Contact** option.
  - To open the **Select Group to Message** screen, tap the **Forward to Group** option.
4. Tap the contact or talkgroup to select.  
The message is copied into the text field.
5. Tap **Send Message** button.  
The message is sent to the contact or talkgroup.

### 19.3.2

## Forwarding a Message to a Quick Group

You can forward a message to a Quick Group on the **History Details** from the **History** tab.

#### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. Tap and hold the history entry.  
A **Context Menu** displays.
3. To open the **Select Contacts to Message** screen, tap the **Forward to Quick Group** option.
4. Tap one or more contacts.
5. Located in the upper right, tap the **Save** button.  
The message is copied into the text field.

6. Tap **Send Message** button.  
The message is sent to the Quick Group.
7. Perform one of the following actions:
  - To continue, select **OK**.  
The message is sent to the contact or talkgroup.
  - To cancel, select **No**.

### 19.3.3

## Replying to a Sender

You can reply to sender for a talkgroup on the Details screen from the History.

#### Procedure:

1. From the History, find the conversation that contains the message you want to reply and tap the **History Details** button.
2. Tap and hold the history entry to open a **Context Menu**.
3. To open the **Group** screen, tap the **Reply to Group** option.
4. Enter the text using the on-screen keyboard.
5. Tap **Send Message** button.  
The message is sent to the talkgroup.

### 19.3.4

## Replying to Talkgroup (Talkgroup Messages)

You can reply to a talkgroup on the **Details** screen from the **History** tab.

#### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to reply and tap the **History Details** button.
2. Tap and hold the history entry to open a **Context Menu**.
3. To open the **Group** screen, tap the **Reply to Group** option.
4. Enter the text using the on-screen keyboard.
5. Tap **Send Message** button.  
The message is sent to the talkgroup.

### 19.3.5

## Deleting a Message

You can delete a message on the **History Details** screen.

#### Procedure:

1. Navigate to the history details, and tap the message.  
The following confirmation message: `Delete message?`
2. Perform one of the following actions:

- To delete, select **Yes**.
- To cancel, select **No**.

### 19.3.6

## History Message Actions

You can send messages to any history entry.

You can also perform any of the following message actions:

- [Sending a Text Message from History on page 147](#)
- [Copying a Text Message from History on page 147](#)
- [Sending a Photo or a Video from History on page 148](#)
- [Sending a Voice Message from History on page 148](#)
- [Sending a File from History on page 149](#)
- [Sharing my Location from History on page 149](#)

#### 19.3.6.1

### Sending a Text Message from History

You can send a text message from the **History Details** screen.

#### Procedure:

1. From the **History** tab, find the conversation and tap the **History Details** button.
2. Tap in the **Enter Text** field.  
An on-screen keyboard displays.
3. Enter the message using the on-screen keyboard.
4. Tap **Send Message** button.  
The message is sent to the talkgroup.

#### 19.3.6.2

### Copying a Text Message from History

You can copy a text message and send to a contact on the **History Details** screen from the **History** tab..

#### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. Tap and hold the history entry.  
A **Context Menu** displays.
3. Tap the **Copy Message** option. The message is copied to the clipboard.
4. Paste the message into any message and send.

### 19.3.6.3

## Sending a Photo or a Video from History

You can send a photo or a video from any history entry on the **Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. Tap the **Camera** button located in the actions to open the **Context Menu**.
3. Select any of the following options:
  - Tap the **Take a photo**.  
The camera displays and allows you to take a photo.
  - Tap **Gallery**.  
The gallery displays and allows you to select any photo in the gallery.
  - Tap **Record a Video**.  
The video displays and allows you to record a video.
4. Tap **OK**.  
A send confirmation message displays.
5. Perform one of the following actions:
  - To send, tap **Yes**.
  - To cancel, tap **No**.

### 19.3.6.4

## Sending a Voice Message from History

You can send a voice message by recording and sending from within the PTT application. When you decide to send a voice message, you can record, preview, rerecord, erase, and send the voice message. Also, you can record a voice message from any history entry on the **History Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. Located in the actions, tap the **Voice Message** button.  
A **Ready Record** screen displays.
3. Press and hold the **RECORD** button and begin speaking your voice message.
4. When complete, release the **RECORD** button.
5. To review your message, tap the **Playback** button.
6. Perform one of the following actions:
  - Located in the upper-right, tap the **Save** button.
  - To open a **Discard Confirmation** message, in upper-left, tap **Cancel** button.
7. Perform one of the following actions:
8. Perform one of the follow actions:
  - To discard voice message, tap **Yes**.
  - To return to the recorded message and the message is sent, tap **No**.

### 19.3.6.5

## Sending a File from History

You can send a file from any history entry on the **History Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation for a contact or talkgroup to which you want to send a file and tap the **History Details** button.
2. Tap the **Attach File** button located in the **Action Bar**.



**TIP:** You can also send a file from the **Call** screen by tapping the **Send Text** button. On the text **Message History** screen, you find the **Attach File** button.



### NOTE:

You can access files from your device storage or other installed applications such as Apple iCloud, Dropbox, and Google Drive, etc.

3. Navigate to the location of the file to attach and tap.

A send confirmation message displays.

4. Perform one of the following actions:

- To send, tap **OK**.
- To cancel, tap **Cancel**.

### 19.3.6.6

## Sharing my Location from History

You can share my location from any history entry on the **Details** screen from the **History** tab.

### Procedure:

1. From the **History** tab, find the conversation that contains the message you want to forward and tap the **History Details** button.
2. To open the **My Location** screen, tap the **Location** button located in the actions.
3. Tap the **Share** button on the **My Locations** screen.

The location is sent.

## Chapter 20

# Video Streaming (Optional)

Optional features may not be included in your PTT service plan.

Video streaming feature allows you to send a one-way, live streaming video with audio to another PTT user, dispatcher, or a corporate talkgroup.

Recipients can be any PTT contact or corporate talkgroup assigned to you capable of receiving video calls. To receive group video, your administrator must enable the feature. Only a limited number of participants can receive a group video stream. Anyone with the video feature can originate a live video stream.

You can stream video from the device integrated camera(s) and choose which camera to broadcast. Each video session allows you to stream, and each participant can have a single active video call at a time.

When streaming video to a talkgroup, the video stream is available to any talkgroup member that has group video receive permission and begins streaming as soon as the first recipient accepts the invitation.

Talkgroup members may leave and rejoin a video call at any time.

During a private (1:1) video call, if the recipient of the call leaves the video session, it ends.



**NOTE:** Incoming video calls are not delivered to users in Do Not Disturb. You cannot send a live stream to a broadcast talkgroup.

You must bring the application to the foreground to send video and see the preview.



**TIP:** Keep the **Video Call** screen in the foreground; otherwise, the camera video transmission becomes blank even though you can hear audio.

For more information on video call settings, see [Settings on page 160](#).

This section is organized as follows:

- [Video Streaming Icons on page 150](#)
- [Minimizing a Video Call on page 151](#)
- [Making a Video Call to a Contact on page 151](#)
- [Making a Video Call to a Quick Group on page 152](#)
- [Making a Video Call to a Talkgroup on page 153](#)
- [Receive an Incoming Video Call on page 154](#)

## 20.1

### Video Streaming Icons

For more information on Video Streaming icons, see [Video Streaming Icons on page 53](#).

## 20.2

# Minimizing a Video Call

A user can minimize ongoing streaming video calls to participate in other activities, such as PTT, messaging, location, and more. The minimized video thumbnail on the PTT application can be dragged to any corner of the PTT application to allow users to perform other actions within the PTT application.

### Procedure:

1. To drag the thumbnail, first touch and hold the thumbnail before dragging.



**NOTE:** While dragging the thumbnail, you will see the thumbnail frame in its previous position until you have finished dragging. This is expected behavior.

The **Video Call** screen is minimized.

2. Tap the **Video Call screen** again to return to full size.

## 20.3

# Making a Video Call to a Contact

### Procedure:

1. Tap **Contacts** to display the PTT Contacts list.



**NOTE:** Your administrator assigns PTT contacts.

You can mix PTT call audio and video audio, or PTT call audio can have priority. For information on PTT audio, see [Changing the Audio Interaction Setting on page 163](#).

2. Tap on the contact to select the one you want to start a video call.

The **Call** screen displays the name of the contact that you are calling in the Call Status, and the **Contacts** button is selected, and active.

3. Located at the bottom of the screen, tap the **Video** icon.

**Figure 60: Transmitting a Live Video Stream to a Contact**




A private one-to-one video call is started, dialing, then ringing the contact. When the contact accepts the incoming video call, the video call begins.

4. Optional: To mute or unmute the microphone audio sent with the live video stream, tap the **Microphone** icon.
5. Optional: To switch your camera from the rear camera (default) to front camera, at the top of the screen, tap **Change Camera**.
6. When it cannot be displayed completely, a video with a long Contact name and Streamer ID displays with ... and is underlined. To see the full name, tap the **Contact** name or **Streamer ID**.  
A pop-up message on the screen disappears after three seconds.
7. To end the video call transmission, tap **End Call**.

## 20.4


# Making a Video Call to a Quick Group

### Procedure:

1. From the **Contacts**, select your first contact to call.  
 **NOTE:** You can mix PTT call audio and video audio, or PTT call audio can have priority. For information on PTT audio, see [Changing the Audio Interaction Setting on page 163](#).  
The **Call** screen displays.
2. Tap the **Add Participants** button.  
The **Select Contacts** screen displays.
3. Select up to nine contacts to add to the quick group call.
4. When completed, located in the upper right, tap **Save**.
5. Located at the bottom of the screen, tap the **Video** icon.



**Figure 61: Transmitting a Live Video Stream to a Quick Group**



A quick group video call is started, dialing, then ringing the group. When the first contact accepts the incoming video call, the video call begins.

6. To mute or unmute the microphone audio sent with the live video stream, tap the **Microphone** icon.
7. To switch your camera from the rear camera (default) to front camera, at the top of the screen, tap **Change Camera**.
8. When it cannot be displayed completely, a video with a long Quick Group Call and Streamer ID displays with ... and is underlined. To see the full name, tap the **Contact** name or **Streamer ID**.  
A pop-up message on the screen disappears after three seconds.
9. To end the video call transmission, tap **End Call**.

## 20.5

# Making a Video Call to a Talkgroup

### Procedure:

1. Ensure that the talkgroup you want to communicate with is selected.

The talkgroup that you select is the talkgroup you call.



**NOTE:** Corporate talkgroup size is limited to 15 talkgroup members receiving the call. You can mix PTT call audio and video audio, or PTT call audio can have priority. For information on PTT audio, see [Changing the Audio Interaction Setting on page 163](#).



**TIP:** If you try to select another talkgroup, your selection changes to the newly selected talkgroup. You can only select one talkgroup at a time.

2. Located at the bottom of the screen, tap the **Video** icon.



**NOTE:** Some corporations may automatically assign a talkgroup called `all_subscribers_group`; this talkgroup has all the PTT subscribers from your corporation.

**Figure 62: Transmitting a Live Video Stream to a Talkgroup**



A talkgroup video call is started, dialing, then ringing the talkgroup. When the first member accepts the incoming video call, the video call begins.

3. To mute or unmute the microphone audio sent with the live video stream, tap the **Microphone** icon.
4. To switch your camera from the rear camera (default) to front camera, tap the **Change Camera** button at the top of the screen.
5. When it cannot be displayed completely, a video with a long Talkgroup name and Streamer ID displays with ... and is underlined. To see the full name, tap the **Contact** name or **Streamer ID**.  
A pop-up message on the screen disappears after three seconds.
6. To end the video call transmission, tap **End Call**.

## 20.6

# Receive an Incoming Video Call

You can receive incoming video calls from a private 1:1 or talkgroup. To receive a talkgroup video call, your administrator must enable you to receive group video calls. You can originate a talkgroup video even if you cannot receive talkgroup video calls. As long as you have the video streaming feature enabled, you can receive private 1:1 and Quick Group video calls. You can manually accept or decline calls that you receive based on the **Auto Answer Video Call** setting.

For more information on the **Auto Answer Video Call** settings, see [Settings on page 160](#).

You can receive an incoming video call from any talkgroup you are assigned. Unlike talkgroup PTT voice calls, video calls are received regardless of your selected talkgroup or talkgroup scanning mode.



**NOTE:** You can mix PTT call audio and video audio, or PTT call audio can have priority. For information on PTT audio, see [Changing the Audio Interaction Setting on page 163](#).

### 20.6.1

## Receiving an Incoming Video Call

When you receive a video call, your device begins to alert.

### Procedure:

1. Perform one of the following actions:

- To accept the call, from the Incoming Video Call Request, select **Accept**.
- To reject the call, from the Incoming Video Call Request, select **Decline**.  
When declined, a missed video call entry is added to your conversation history.



**NOTE:** Incoming video calls respond differently based on the combination of the phone settings and the PTT application settings. For more information, see [Interaction with Silent or Sound Mode on page 69](#).

If you receive a video call while transmitting on a PTT call (holding the floor), you will receive a system notification to indicate the incoming video call.

2. To mute or unmute the microphone audio sent with the live video stream, tap the **Microphone** icon.
3. To switch your camera from the rear cam (default) to front cam, tap the **Change Camera** button at the top right-hand of the screen.
4. When it cannot be displayed completely, a video with a long Contact name and Streamer ID displays with ... and is underlined. To see the full name, tap the **Contact** name or **Streamer ID**.  
A pop-up message on the screen disappears after three seconds.
5. To end the video call transmission, tap **End Call**.

### 20.6.2

## Receiving a Video Stream Request

A dispatcher may request that you live stream video. If you accept the request, the video is sent as a private 1:1 video call to the dispatcher. When you receive an incoming video stream request, you can manually accept or decline based on the **Auto Answer Video Call** setting.

For more information on the **Auto Answer Video Call** settings, see [Changing the Audio Interaction Setting on page 163](#).

### Procedure:

1. When you receive a video stream request, perform one of the actions:

- To answer the call, select **Accept**.  
Accepting the request immediately starts a video session to the dispatcher.
- To reject the call, select **Decline**.

2. To mute or unmute the microphone audio sent with the live video stream, tap the **Microphone** icon.
3. To switch your camera from the rear cam (default) to front cam, at the top right-hand of the screen, tap **Change Camera**.
4. When it cannot be displayed completely, a video with a long Contact name and Streamer ID displays with ... and is underlined. To see the full name, tap the **Contact** name or **Streamer ID**.  
A pop-up message on the screen disappears after three seconds.
5. To end the video call transmission, tap **End Call**.

### 20.6.3

## Receive an Unconfirmed Video Stream Request

There may be a situation where a dispatcher wants to initiate a video automatically. Before this function can be used, your administrator must enable it for the dispatcher.

When you receive an unconfirmed video stream request, the call is automatically accepted. For more information on the **Allow Unconfirmed Video Transmission** settings, see [Settings on page 160](#).



**NOTE:** Unconfirmed video pull is not supported with iOS 12.4 and later.

## Chapter 21

# Airplane Mode

Your phone provides a special mode called Airplane Mode, which disables ability of the phone to communicate over cellular, Wi-Fi, and Bluetooth connections. When you turn on Airplane Mode, you disconnect from the Push-to-Talk (PTT) service.

When you have Airplane Mode enabled on your phone:

- You cannot receive PTT calls or messages.
- You cannot receive alerts from others.
- Other users can see you as offline in their PTT contact list and cannot call or send you an alert.

## Chapter 22

# Accessories and Bluetooth Use

This section describes using accessories and Bluetooth associated with the Push-to-Talk (PTT) application and is organized as follows:

- [Using a Wired Audio Headset on page 158](#)
- [Using Bluetooth on page 158](#)
- [Using a Remote Speaker Microphone on page 159](#)

## 22.1

### Using a Wired Audio Headset

You can use a headset plugged into your phone for Push-to-Talk (PTT) calls.

Whenever you connect the headset, PTT calls are heard automatically over the headset instead of the loudspeaker. You must still use the **PTT** button on the phone to take the floor to speak, even if your headset has a multimedia control button on it. When you disconnect the headset, the loudspeaker again is used for PTT calls.

## 22.2

### Using Bluetooth

By default, whenever your phone connects to a compatible Bluetooth device, the PTT application uses that Bluetooth device for calls. If you turn off or unpair your Bluetooth device, the PTT call automatically switches to the loudspeaker.

The PTT application supports the following Bluetooth profiles:

- Hands-Free (HFP)
- Headset (HSP)
- Advanced Audio Distribution Profile (A2DP)

When using PTT over Bluetooth, you must use the **PTT** button on the phone to take the floor and speak.

## 22.2.1

### Car Kit

Many cars allow you to connect your phone to the car audio system using Bluetooth.

You should check the owner manual for your car to see if your phone is compatible. Once you connect your phone to the audio system of your car, PTT calls also use the Bluetooth audio.

You must use the **PTT** button on the phone to take the floor.

### 22.2.2

## External PTT Button

You can use a compatible **Bluetooth Smart (Low Energy Bluetooth) PTT** button with your PTT service. This button can be used in addition to the on-screen PTT button.

### 22.2.3

## Bluetooth for PTT

If your phone can connect to your car audio system and you receive regular cellular calls, PTT calls also work. In the rare circumstance that there is a compatibility problem using PTT with your car audio, but you still want to use Bluetooth for regular cellular calls, you can turn off PTT over Bluetooth from within PTT application settings.

For more information on how to turn off Bluetooth, see [Use Bluetooth on page 173](#).

### 22.3

## Using a Remote Speaker Microphone

A Remote Speaker Microphone (RSM) is an accessory made especially for handling PTT calls. The RSM has a loudspeaker and **PTT** button built-in which lets you remotely control the PTT application on your phone.

There are two types of RSMs:

- Those that connect by wire to the headset connector of the phone.
- Those that use Bluetooth.

### 22.3.1

## Wired

A wired RSM connects to the USB-C connector of the phone. The RSM has a loudspeaker and microphone, along with a **PTT** button.

The **PTT** button allows you to take the floor during a PTT call and speak. The **PTT** button on the RSM works just like the **PTT** button on the phone. Depending on the RSM, there may also be a connection for you to use a headset with the RSM.

You should check the RSM owner manual for information specific to the accessory. With a wired RSM, you control the loudspeaker volume using the volume keys on the phone and using the volume buttons on the RSM.



**NOTE:** The PTT application must be in the foreground to take the floor using the wired accessory.

### 22.3.2

## Bluetooth

A Bluetooth-connected RSM gives you all the features of a wired RSM without being tethered by a cord. In addition to having a loudspeaker and **PTT** button, a Bluetooth RSM also has a volume control. You do not use the volume buttons on your phone to control the volume, but rather the volume control on the RSM itself.

A Bluetooth RSM must be paired to your phone before it can be used. For instructions on how to pair the RSM with your phone, see the documentation that comes with the RSM.

## Chapter 23

# Settings

This section describes the settings within the Push-to-Talk (PTT) application and is organized as follows:

- [Accessing the PTT Application Settings on page 161](#)
- [Important Message on page 161](#)
- [Alert Repeat on page 162](#)
- [Alert Tone on page 162](#)
- [Allow Unconfirmed Video Transmission on page 163](#)
- [Audio Interaction on page 163](#)
- [Auto Answer Video Call on page 163](#)
- [Auto Download on page 164](#)
- [Broadcast Call Confirmation on page 165](#)
- [Background Mode on page 164](#)
- [Capacity on page 165](#)
- [Contact Sorting on page 165](#)
- [Display Name on page 166](#)
- [Emergency on page 166](#)
- [Enhanced Loudness on page 167](#)
- [History Sorting on page 168](#)
- [In Call Tones on page 168](#)
- [Instant Personal Alert on page 169](#)
- [Location Change Accuracy on page 169](#)
- [Logout on page 170](#)
- [Message Alert on page 171](#)
- [Missed Call Alert on page 172](#)
- [My PTT Number on page 172](#)
- [Network Loss Tone Repeat](#)
- [Network Up/Down Tones](#)
- [Restore Defaults on page 173](#)
- [Use Bluetooth on page 173](#)
- [Voice Message Fallback on page 174](#)
- [Vibrate Alert on page 174](#)
- [Volume Boost on page 175](#)



## 23.1

# Accessing the PTT Application Settings

You can change all settings, except for the **Boundary** settings in the PTT application settings.

### Procedure:

1. From within the [Menu on page 36](#), tap the **Settings** option.



**NOTE:**

For more information on how to change the **Boundary** settings, see the [Boundary Settings on page 123](#) section.

The **Menu** icon is in the upper-left-hand corner of the **Main** screen.

2. Find the settings you want to change and follow the instructions.



**NOTE:** All settings show in the default state.

## 23.2

# Important Message

Notifications are sent periodically to ensure that the application is up-to-date with the most current software.

When an update is available, you receive a message when you login to the PTT application. Important Message notifications show with a yellow star on the **Menu** settings option, and the **Important Message** settings. If there are no important message notifications available, you do not receive a message nor see the setting.

For more information, see [Application Updates on page 30](#).

### 23.2.1

## Upgrading the PTT Application

### Procedure:

1. From the **Settings** screen, scroll to and tap the **Important Message** setting.
2. From the **Important Message Notification**, perform one of the following actions:



**NOTE:** The **Important Message Notifications** may vary in content.

- To download the latest application, tap the **Upgrade** button to be directed to the Apple App Store.
- To dismiss the notification, tap the **Dismiss** button.

## 23.3

# Alert Repeat

The **Alert Repeat** setting affects how often you are reminded that you have Instant Personal Alerts and Missed Call Alerts waiting.

### 23.3.1

## Changing the Alert Repeat Setting

You can change your **Alert Repeat** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap on the **Alert Repeat** setting.
2. To select how often you want your alerts to repeat, perform one of the following actions:
  - To have alerts play once when you receive the alert, select **Once (default)**.
  - To have alerts play every 20 seconds for 10 minutes, select **Repeat**.
  - To have alerts play every 20 seconds until you clear the alert, select **Continuous**.



**NOTE:** This option drains the battery faster than the other options.

3. Tap **OK**.

## 23.4

# Alert Tone


The **Alert Tone** setting allows you to select the missed call alert and Instant Personal Alert tone from a list of choices. The tone is played when you select it.

### 23.4.1

## Changing the Alert Tone Setting

You can change your **Alert Tone** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **Alert Tone** setting.
  -  **TIP:** When you preview an alert tone, it does not play even if the phone ringer is silent.

2. Select the desired alert tone.



**NOTE:** A **Device Tone** option shows additional tones are available from your device.

3. Perform one of the following actions:
  - To select the tone, tap **Select**.
  - To go back to the previous screen, tap **Cancel**.
4. Tap **OK**.

## 23.5

# Allow Unconfirmed Video Transmission

When turned on, the **Allow Unconfirmed Video Transmission** setting allows an authorized dispatcher to start sending video from this device without your confirmation automatically. When turned off, an authorized user cannot send video from your device automatically without you accepting or declining the video session. This setting requires the Streaming Video feature to be turned on. It is an optional feature and may not be included in your PTT service plan.



**NOTE:** This feature is not supported for iOS 12.4 and above.

## 23.5.1

# Changing the Allow Unconfirmed Video Transmission Setting

You can change your **Allow Unconfirmed Video Transmission** setting as needed.

### Procedure:

1. From the **Settings**, scroll to the **Allow Unconfirmed Video Transmission** setting.
2. To toggle the state of the setting, tap the **On/Off** switch.

## 23.6

# Audio Interaction

The **Audio Interaction** setting sets the audio interaction for PTT and video calls. You can mix both PTT call audio and video audio, or PTT call audio can have priority. When PTT Preemption is set, the PTT audio preempts the video audio. Audio interaction is set to **Mix** by default. This setting requires the Streaming Video feature to be turned on. It is an optional feature and may not be included in your PTT service plan.

## 23.6.1

# Changing the Audio Interaction Setting

You can change your **Audio Interaction** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **Audio Interaction** setting.
2. Select one of the following desired audio interaction setting options:
  - To preempt the video audio while a PTT call member has the floor, select the **PTT Preemption** option.
  - To mix both the PTT audio and video audio, select the **Mix** option.
3. Tap **OK**.

## 23.7

# Auto Answer Video Call

When you turn on the **Auto Answer Video Call** setting, video calls are automatically accepted and played. When you turn off this setting, an incoming video session alert provides you the option to accept or decline

the video session. This setting requires the Streaming Video feature to be turned on. It is an optional feature and may not be included in your PTT service plan.

### 23.7.1

## Changing the Auto Answer Video Call Setting

You can change your **Auto Answer Video Call** setting as needed.

### Procedure:

1. From the **Settings**, scroll to the **Auto Answer Video Call** setting.
2. To toggle the state of the setting, tap the **On/Off** switch.

### 23.8

## Auto Download

When you turn on the **Auto Download** setting, message attachments automatically download to the **PTT Call History**. When you turn off this setting, you must manually download by tapping the message attachment. This feature is turned off by default. Requires the Integrated Secure Messaging feature to be turned on by your administrator.

### 23.8.1

## Changing the Auto Download Setting

You can change your **Auto Download** setting as needed.

### Procedure:

1. From the **Settings**, scroll to the **Auto Download** setting.
2. To toggle the state of the setting, tap the **On/Off** switch.

### 23.9

## Background Mode

The **Background Mode** setting allows you to choose if an incoming call shows a notification. By pressing a supported Bluetooth PTT accessory takes the floor while the application is in the background. You must bring the PTT application to the foreground to use the on-screen **PTT** button. This feature is turned off by default.

For more information, see [Call Behavior in Background](#).

### 23.9.1

## Changing the Background Mode Setting

You can change your **Background Mode** setting as needed.

### Procedure:

1. From the **Settings**, scroll to the **Background Mode** setting.
2. To toggle the state of the setting, tap the **On/Off** switch.



**NOTE:** When the PTT application is in the background, a wired accessory **PTT** button does not work.

## 23.10

# Broadcast Call Confirmation

The **Broadcast Call Confirmation** setting allows you to enable or disable a broadcast call confirmation dialog before initiation of broadcast call.

## 23.10.1

# Changing the Broadcast Call Confirmation Setting

You can change your **Broadcast Call Confirmation** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **Broadcast Call Confirmation** setting.
2. Perform one of the following actions:
  - To have a confirmation dialog (pop-up) displayed before the initiation of a broadcast call, tap **ON**.
  - To have a confirmation dialog (pop-up) not displayed and have the initiation of a broadcast call be instantaneous, tap **OFF**.

## 23.11

# Capacity

The **Capacity** setting allows you to view how many PTT contacts, talkgroups, and favorites store on your phone. These numbers include both personal and administrator-managed.

To see the maximum capacity for your phone, you can refer to the table in [Contacts on page 94](#), [Talkgroups on page 102](#), and [Favorites on page 91](#).

Also, you can dismiss the pop-up displayed by pressing the BACK button on the title bar.

## 23.11.1

# Viewing the Phone Capacity Setting

You can view your **Phone Capacity** setting as needed.

### Procedure:

From the **Settings**, scroll to and tap the **Capacity** setting.

**Result:** The **Capacity** screen displays.

## 23.12

# Contact Sorting

With the **Contact Sorting** setting, you can choose to view your contacts in a sorted manner.

There are two contact sorting options: sorting according to the alphabetical order of your contacts (default) or sorting according to the availability of your contacts. When contacts are sorted by availability, online contacts show first alphabetical, followed by offline contacts alphabetical. Online contacts include contacts who are **Available** and **Do Not Disturb**. The contact list updates each time a contact changes from online to offline or vice versa.

### 23.12.1

## Changing the Contact Sorting Setting

You can change the **Contact Sorting** setting as needed.

#### Procedure:

1. From the **Settings**, scroll to and tap the **Contacts Sorting** setting.
2. Perform one of the following actions:
  - To sort the contacts alphabetically, tap the **By Alphabetical** option.
  - To sort the contacts by availability, tap the **By Availability** option.
3. Tap **OK**.

### 23.13

## Display Name

The **Display Name** setting allows you to view the name that others, including the corporate administrator, see in their contact list. The administrator may change your name at any time.

### 23.13.1

## Viewing or Changing Your Display Name Setting

You can view or change your display name as needed.

#### Procedure:

1. From the **Settings**, scroll to and tap the **Display Name** setting.  
Your current name displays.
2. To dismiss the display name window or continue to set your display name, tap the **Cancel** button.
3. To clear the display name, tap the **Clear Text** button.
4. Type your display name using the on-screen keyboard.
5. To save the display name, tap the **Save** button.

### 23.14

## Emergency

The **Emergency** setting is an optional feature and may not be included in your PTT service plan.

The **Emergency** settings allow you to view a preset list of your primary and secondary emergency contact and talkgroup. This setting is displayed when your emergency destination is assigned by your administrator and not by the user and requires Emergency Services to be turned on by your administrator.



**NOTE:** You cannot change your emergency contacts set by your administrator.

### 23.14.1

## Viewing Your Emergency Contacts Setting

You can view your **Emergency Contacts** setting as needed.

### Procedure:

From the **Settings**, scroll to and tap the **Emergency** settings.

### 23.15

## Emergency Alert

The **Emergency Alert** setting allows you to control new emergency alert notifications and to select the behavior of incoming emergency alerts.

Emergency alerts are received when another user declares emergency. **Emergency Alert** setting options include, **Tone and Display** (default), **Tone Only**, **Display Only**, or **Off** that provides no alert dialog and no alert tone.

This feature requires that the Emergency Services feature is turned on by your administrator.

### 23.15.1

## Changing the Emergency Alert Setting

You can change the **Emergency Alert** setting as needed.

### Procedure:

1. From the **Settings**, scroll to the **Emergency Alert** setting.
2. Select one of the following desired emergency alert options:
  - To have a persistent alert dialog display, an audible tone play, and the alert added to history, select **Tone and Display** (default).
  - To have an audible alert tone play, and the alert added to history, select **Tone Only**.
  - To have a persistent alert dialog display, no alert tone play, and the alert added to history, select **Display Only**.
  - To have no alert dialog display, no alert tone play, and the alert added to history, select **Off**.
3. Tap **OK**.

### 23.16

## Enhanced Loudness

When you turn on the **Enhanced Loudness** setting, the perceived audio volume of PTT calls increases using the speakerphone. This feature is only available on supported devices.

### 23.16.1

## Changing the Enhanced Loudness Setting

You can change the **Enhanced Loudness** setting as needed.

### Procedure:

1. From the **Settings**, scroll to the **Enhanced Loudness** setting.

2. To toggle the state of the setting, tap the **On/Off** switch.

## 23.17

# History Sorting

With the **History Sorting** setting, you can view your history in a sorted manner.

The following are the two **History Sorting** setting options that you can select from:

- Sorting from oldest to newest (default), which displays your history with the newest entries at the bottom of the history list.
- Sorting from newest to oldest, which displays the newest entries in the top of the history list.



**NOTE:** This feature applies to conversation details. The first-level history always shows the newest conversations at the top of the list.

## 23.17.1

# Changing the History Sorting Setting

You can change the **History Sorting** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **History Sorting** setting.  
The **History Sorting** screen displays.
2. Perform one of the following actions:
  - To sort the history from newest to oldest entries, tap **Newest to oldest**.
  - To sort the history from oldest to newest entries, tap **Oldest to newest**.
3. Tap **OK**.

## 23.18

# In Call Tones

When you turn on the **In Call Tones** setting, tones play during a PTT call. However, when you turn off the **In Call Tones** setting, the tones do not play during a PTT call.

## 23.18.1

# Changing the In Call Tones Setting

You can change the **In Call Tones** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **In Call Tones** setting.
2. Select any of the following **In Call Tones** setting behavior options:
  - To have a tone play when you receive a PTT call, select **Incoming Call Tone**.  
The default selection is set to **ON**.
  - To hear a specific tone when the floor is granted or acquired, select **Floor Grant Tone**.  
This tone also indicates you can speak. The default selection is set to **ON**.
  - To hear a specific tone when the floor is free, select **Floor Free Tone**.



The default selection is set to **ON**.

- To hear a specific tone when the user who has the floor releases the floor, select **Floor Release Tone**.

The default selection is set to **OFF**.



**NOTE:** The Floor Release Tone is played when the user who has the floor releases the floor. The tone is the same as the Floor Free Tone. This floor tone condition is not supported in clients before release 8.3.

- To hear a specific tone when the floor is busy, select **Floor Error/Busy Tone**.

The default selection is set to **ON**.

- To hear a specific tone when you receive a voice message, select **Voice Message Tone**.

The default selection is set to **ON**.

## 23.19

# Instant Personal Alert

The **Instant Personal Alert** setting allows you to select the instant personal alert from a list of choices, such as **Tone and Display** (default), **Tone Only**, **Display Only**, or **Off** that provides no alert dialog and no alert tone.

### 23.19.1

## Changing the Instant Personal Alert Setting

You can change the **Instant Personal Alert** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **Instant Personal Alert** setting.
2. Select any of the following **Instant Personal Alert** setting options:
  - To have a persistent alert dialog display, an audible tone play (subject to Silent Mode behavior), and the alert added to history, select **Tone and Display** (default).
  - To have an audible alert tone play (subject to Silent Mode behavior), and the alert added to history, select **Tone Only**.
  - To have a persistent alert dialog display, no alert tone play, and the alert added to history, select **Display Only**.
  - To have no alert dialog display, no alert tone play, and the alert added to history, select **Off**.
3. Tap **OK**.

## 23.20

# Location Change Accuracy

The **Location Change Accuracy** setting changes the timeliness and accuracy of reporting the location of the device.

By default, the setting option is set to *Approximate*, which provides less accurate location and has less impact on battery life. If more accurate location changes are needed, you can select the **GPS** option, which reports location more accurately but reduces battery life. When you select the **GPS** option, an informational message displays to remind you that you may experience decreased battery life.

### 23.20.1

## Changing the Location Change Accuracy Setting

You can change the **Location Change Accuracy** setting as needed.

### Procedure:

1. From the **Settings**, scroll to and tap the **Location Change Accuracy** setting.
2. Select any of the following **Location Change Accuracy** setting options:
  - To provides less accurate location reporting and drain the battery less, select **Approximate**.
  - To have location changes detected by using GPS, select **GPS**.

Use this setting when location changes should be reported on a more timely and accurate basis



**NOTE:** Setting the mode to GPS results in decreased battery life.

3. Tap **OK**.

### 23.20.2

## Approximate (default)

The **Approximate** option for the **Location Change Accuracy** setting provides less accurate location reporting and drains the battery less.

### 23.20.3

## Changing the GPS Setting Option

Location changes are detected using GPS. You should use this setting when location changes should be reported on a more timely and accurate basis.



**NOTE:** Setting location change accuracy mode to GPS results in decreased battery life.

### Procedure:

- Tap **OK**.

### 23.21

## Logout

While you are logged out, you show as “Offline” to others, and you cannot receive PTT calls, alerts, or secure messages.

If you log out before powering off your phone, you remain logged out after your phone is powered on again. To send or receive PTT calls, you need to login. See the [Login on page 30](#) section for details on how to login.

### 23.21.1

## Changing the Logout Setting

You can change the **Logout** setting as needed.

### Procedure:

1. From the Settings, scroll to and tap the **Logout** setting.
2. Tap **Logout**, a Logout confirmation appears.

3. Perform one of the following actions:
  - Tap **Yes** to turn on.
  - Tap **No** to turn off.

## 23.22

# Message Alert

This setting allows you to control new message alert notifications.

To turn on/turn off Message Alert for PTT messages, switch ON the setting to turn on Message Alert or switch to OFF mode to switch off the Message Alert at the Message Alert setting. Requires the Integrated Secure Messaging feature to be turned on by your administrator.

## 23.22.1

# Changing the Message Alert Setting

You can change the **Message Alert** setting as needed.

### Procedure:

1. From the Settings, scroll to the **Message Alert** setting.
2. Tap the **On/Off** switch to toggle the state of the setting.

## 23.23

# Message Alert Tone

This setting allows you to select the missed call alert and Instant Personal Alert tone from a list of choices. The tone plays when you select it. Requires the Integrated Secure Messaging feature to be turned on by your administrator.

## 23.23.1

# Changing the Message Alert Tone Setting

You can change the **Message Alert Tone** setting as needed.

### Procedure:

1. From the Settings, scroll to and tap the **Message Alert Tone** setting.



**TIP:** When you preview a message alert tone, it plays on the speaker even if the phone ringer is silent.

2. Select the desired alert tone.
3. Tap **OK**.

## 23.24

# Missed Call Alert

This setting allows you to select the **Missed Call Alert** (MCA) from a list of choices to provide either a Tone and Display (default), Tone Only, Display Only, or Off which provides no alert dialog and no alert tone.

### 23.24.1

## Changing the Missed Call Alert Setting

You can change the **Missed Call Alert** setting as needed.

### Procedure:

1. From the Settings, scroll to and tap the **Missed Call Alert** setting.
2. Select the desired missed call alert option as follows:
  - **Tone and Display** (default)—A persistent alert dialog displays, an audible tone plays (subject to Silent Mode behavior), and the alert is added to history.
  - **Tone Only**—An audible alert tone plays (subject to Silent Mode behavior), and the alert is added to history.
  - **Display Only**—A persistent alert dialog displays, no alert tone plays, and the alert is added to history.
  - **Off**—No alert dialog displays, no alert tone plays, and the alert is added to history.
3. Tap **OK**.

## 23.25

# My PTT Number

This number displays your registered PTT number to other contacts.

### 23.25.1

## Viewing My PTT Number Setting

### Procedure:

1. From the Settings, scroll to the **My PTT Number** setting.

#### 23.25.1.1

### Missed Call Alert

This setting allows you to select the **Missed Call Alert** (MCA) from a list of choices to provide either a Tone and Display (default), Tone Only, Display Only, or Off which provides no alert dialog and no alert tone.

#### 23.25.1.1.1

### Changing the Missed Call Alert Setting

You can change the **Missed Call Alert** setting as needed.

### Procedure:

1. From the Settings, scroll to and tap the **Missed Call Alert** setting.
2. Select the desired missed call alert option as follows:

- **Tone and Display** (default)—A persistent alert dialog displays, an audible tone plays (subject to Silent Mode behavior), and the alert is added to history.
  - **Tone Only**—An audible alert tone plays (subject to Silent Mode behavior), and the alert is added to history.
  - **Display Only**—A persistent alert dialog displays, no alert tone plays, and the alert is added to history.
  - **Off**—No alert dialog displays, no alert tone plays, and the alert is added to history.
3. Tap **OK**.

## 23.26

# Restore Defaults

You can restore all the PTT application settings to their defaults using the **Restore Defaults** setting. When you choose this setting, you are reminded that the restore cannot be undone and asked to confirm the action.

## 23.26.1

# Restoring the Defaults Settings

You can change the **Default** settings as needed.

### Procedure:

1. From the Settings, scroll to and tap the **Restore Defaults** setting.
2. Tap **Yes** to restore all application settings to their default values or **No** to cancel.

## 23.27

# Use Bluetooth

To turn on/turn off Bluetooth device usage for PTT calls, switch ON the setting to turn on Bluetooth or switch to OFF mode to switch off the Bluetooth at the **Bluetooth** setting. This setting is turned on by default.

## 23.27.1

# Changing Bluetooth Setting

You can change the **Bluetooth** setting as needed.

### Procedure:

1. From the Settings, scroll to the **Bluetooth** setting.
2. Tap the **On/Off** switch to toggle the state of the setting.

## 23.28

# Vibrate Alert

When the Vibrate Alert setting is ON, the phone vibrates for new alerts. This setting applies to Instant Personal Alerts and Missed Call Alerts and is turned on by default.

### 23.28.1

## Changing Vibrate Alert Setting

You can change the **Vibrate Alert** setting as needed.

#### Procedure:

1. From the Settings, scroll to the **Vibrate Alert** setting.
2. Tap the **On/Off** switch to toggle the state of the setting.

## 23.29

# Vibrate Call

When the incoming Call Vibrate setting is ON, the phone vibrates for incoming PTT calls. This setting is turned off by default.



**NOTE:** When the phone ringer is set to Silent only it overrides this setting.

### 23.29.1

## Changing Vibrate Call Setting

You can change the **Virate Call** setting as needed.

#### Procedure:

1. From the Settings, scroll to the **Vibrate Call** setting.
2. Tap the **On/Off** switch to toggle the state of the setting.

## 23.30

# Voice Message Fallback

This setting is for the Voice Message Fallback feature that allows the Voice message to be turned off when needed.

### 23.30.1

## Changing the Voice Message Fallback Setting

You can change the **Voice Message Fallback** setting as needed.

#### Procedure:

1. From the Settings, scroll to and tap the **Broadcast Call Confirmation** setting.
2. Select the following options:
  - Tap **ON** (Default) Private and Group PTT call will automatically initiate the Voice message screen if the destination is unavailable.

- Tap **OFF** Private and Talkgroup PTT calls show an error message if the destination is unavailable.

## 23.31

# Volume Boost

The Volume Boost setting increases PTT call volume and Integrated Secure Messages (Voice messages and video messages) while the device is in speakerphone mode.

Volume Boost does not affect application tones, PTT call volume in accessories, including headsets or RSMs. The volume is not boosted when the speakerphone is turned off.



**NOTE:**

On iOS 13.1, when the PTT app is in the background, and the Volume Boost setting is set to anything other than the default, no audio is heard during an incoming PTT call.

Boosting volume may decrease sound quality.

Volume Boost setting is available on supported devices.

## 23.31.1

# Changing Volume Boost Setting

You can change the **Volume Boost** setting as needed.

**Procedure:**

1. From the Settings, scroll to and tap the **Volume Boost** setting.
2. Adjust the control to indicate the desired percentage of volume boost.
3. Tap **OK**.

## Chapter 24

# Troubleshooting

This section describes the steps you must take to troubleshoot the Push-to-Talk (PTT) application and is organized as follows:

## 24.1

### General

Whenever you are having issues, it is recommended to update your PTT application.

## 24.2

### Activation Failures

The first time you start the application after download, the application must “activate” with the PTT server.

This activation process ensures that you are a PTT subscriber and that you are using a supported iPhone. If a problem occurs during the activation process, you receive an error message. The following error messages may be observed:

`Data connection is unavailable.`

You must ensure that your phone is not in Airplane Mode and you connect to the cellular data network. See the owner’s manual for your phone to understand the icons shown in the status bar at the top of the screen that indicates data connection is available.

`This service requires a supported phone. Would you like to subscribe now?`

You must have a PTT subscription before you can successfully begin using PTT service.

## 24.3

### Restarting an Unresponsive PTT Application

In rare cases, the PTT application may suddenly stop working (application freeze). If this happens, you can recover by following these instructions:

**Procedure:**

1. Quick double-tap the Home button on your phone.
2. Drag the image of the PTT application upwards to stop the application.
3. Restart the PTT Application again.

## 24.4

### Application Asks Your to Enter an Activation Code

When you start the application for the first time, you are asked to activate the application.

This activation process ensures that you are a PTT subscriber and that you are using a supported phone. During activation, you must be located in an area with good cellular coverage. Some corporations allow activation of the application over a Wi-Fi network using an activation code. Your administrator typically provides the activation code. If you do not have an activation code, please move to an area with good cellular coverage and try activating again.



## 24.5

# Application is not Visible during an Incoming Call

Check the Background Mode setting to ensure it is not turned on.

For more details, see the [Changing the Background Mode Setting on page 164](#) section.

## 24.6

# Call Failures

A PTT call may not be completed for several reasons:

- The person you are calling has an “Offline” or “Do Not Disturb” status. The PTT application does not allow you to make a call to someone with either status.
- The person you are calling is busy, either on another PTT call or a cellular call. Please see the [User Busy on page 179](#) section for more information.
- Your phone loses connection with the data network or PTT server. Please see the [Loss of Data Network Connection on page 179](#) section for more information.
- The person you are trying to call has temporarily not reachable. Please see the [User Unreachable on page 179](#) section for more information.

## 24.7

# Calls are Always Heard in the Earpiece

If you are hearing PTT calls through the earpiece instead of the loudspeaker, the speakerphone ON/OFF setting may be set to OFF.

You can change this setting in the application settings, or during a call. To turn on the speakerphone, tap the on-screen speakerphone button to ensure it is ON (shown by the green indicator on the button). More details are found in [Call Screen Icons on page 45](#).

Another reason may be because your phone ringer is set to silent. Ensure that your phone is not in Silent and check that Privacy Mode is not set to Earpiece. See the [Interaction with Silent or Sound Mode on page 69](#) section for more information about interaction with your phone’s silent mode.

## 24.8

# Calls are Only Received from a Small Number of Groups

If you are receiving calls from only a couple of groups, you may have turned the ‘Talkgroup Scanning’ on and are listening to only the groups in the scan list.

More details can be found in [Talkgroup Scanning on page 110](#).

## 24.9

# Unable to Change the Phone Number of a PTT Contact

While the name, avatar, color, and favorite status of a contact can be changed, phone numbers cannot be changed.

If you need to change a contact's phone number, you need to delete the contact and add it again with the new phone number. Please see the [Contacts on page 94](#) section for details on deleting and adding PTT contacts. Contacts that are managed by an administrator cannot be renamed or deleted.

## 24.10

# Unable to Create/Update/Delete a Contact or Group

There are two reasons why you might not be able to create, modify, or delete a contact or group:

### **Administrator-Managed Contacts and Groups**

You cannot change or delete contacts or groups that are managed by an administrator. Please refer to the [Contacts on page 94](#) section and the [Talkgroups on page 102](#) section for more details on administrator-managed contacts and groups. You need to contact your PTT administrator to make any changes.

### **Corporate-Only Subscriber**

Your PTT administrator may have your PTT service restricted to have only corporate contacts and groups. Which means that only your PTT administrator can add, change, or remove contacts and groups on your phone. Even though you cannot change or remove contacts or groups, you can still make them favorites, add avatars, or set colors.

## 24.11

# Unable to Hear Incoming Call

If you cannot hear an incoming PTT call, your loudspeaker volume may be turned down, or your phone may be in silent mode.

Please see the [Turning the Speaker On/Off on page 68](#) section to set the PTT call volume. See the [Interaction with Silent or Sound Mode on page 69](#) section for more information about interaction with your phone's silent mode.

## 24.12

# Unable to Send an Instant Personal Alert

If your phone is currently in "Do Not Disturb" (DND) status, you cannot send an Instant Personal Alert (IPA).

You are not able to receive a callback while in DND, so the PTT application does not allow you to send an alert. Please change your presence status to "Available." See the [My Presence on page 85](#) section for details on how to set your presence status.

## 24.13

# Changing Your SIM Card

Your phone may contain a SIM card that lets you move your phone number from one phone to another phone compatible with your mobile phone service and SIM card.

If you replace the SIM card in your phone with another that has a different phone number, the PTT application automatically erases your PTT history and favorites and restores the contacts and talkgroups associated with the new number (if any exist). After changing the SIM card, the next time you start the PTT application, you are asked to “activate” or re-register your phone with the PTT server to ensure that you subscribe to PTT service. Please see the [First-Time Activation on page 24](#) section for information about registering your phone with the PTT service.

## 24.14

# Explanation of Error Messages

### 24.14.1

## Loss of Data Network Connection

If the PTT application cannot communicate with the PTT server, it displays `Offline` in the status bar or system notification, and your availability shows `No Connection`.

For more information, refer to the [My Presence on page 85](#) section.

You cannot receive PTT calls or alerts, and you appear as `Offline` to others after some time. You should ensure that you have a good signal on your phone. If you perform any action that requires connection to the PTT server (e.g., outgoing call, change self-availability, contact/group add/modify/delete, etc.) a `Connection is unavailable` message is displayed for a few seconds. When the connection restores, you receive the `Connection is restored` message.

To see if you have access to the data network, you should try to access a website using your mobile browser. You may also switch on Wi-Fi if a Wi-Fi network is in range.

If you want to reconnect only to the cellular data network, then turn off Wi-Fi in the settings. See the [Menu on page 36](#) settings section for more information.

### 24.14.2

## User Busy

When you make a one-to-one PTT call to another person, and they are either engaged in another PTT call or a regular cellular call, you see a message indicating that the person is busy.

If you receive this message, you can try your call later, or send an alert. See the [Sending an Alert on page 83](#) section for details.

### 24.14.3

## User Unreachable

In rare cases, a contact might be shown as `Available` in your contact list, but might be temporarily outside the range of service coverage. In this case, your PTT call cannot go through. The called person's status updates to `Offline` until they reconnect to PTT service. If this happens, you should wait for their status to be shown as `Available` and try your call again.

## 24.15

# Login Failures

Login to the PTT service may fail if the phone is in Airplane Mode or if you do not have a data connection. Please check the data connection and try to log in again later.

## 24.16

# Presence Status Does Not Update

If you attempt to change your presence status from `Available` to `Do Not Disturb` or vice versa, and you do not see your status updated, there may be a communication problem between your phone and the PTT server.

Logging out and logging in again should solve the problem. To log out, see the setting [Logout on page 170](#).

## 24.17

# Quick Group Calls I Receive Are Shown in History as a One-to-One Call

When you receive a Quick Group call, you notice that the call history shows a call received from the originator of the call, which is normal.

You cannot call Quick Group that was created by someone else. Any Quick Group calls that you make shows in the call history with the names of the participants. You can call that group again from your history. For more details on Quick Groups, please refer to the [Making Quick Group Calls on page 61](#) section.

## 24.18

# Wi-Fi Connection Problems

Using the PTT application over Wi-Fi requires that the phone can access the Internet through the Wi-Fi connection. While your phone is connected to Wi-Fi if the PTT application gives you the message `Data connection is unavailable` then ensure that the Wi-Fi service provider does not require a user name and password and that the Wi-Fi application setting is turned on.

In rare circumstances, the PTT application may not be able to connect to the PTT server over Wi-Fi. In this case, you should turn off the Wi-Fi setting in the PTT application or turn off the Wi-Fi connection on your phone to use PTT.

Please refer to the [PTT over Wi-Fi on page 56](#) section.

## Chapter 25

# Glossary

This section provides a list of terms used with the Push-to-Talk (PTT) application.

### Authorized User

An authorized user is typically a dispatcher or supervisor which may have permissions do the following:

- Allow or disallow remote supervision for assigned contacts
- Remotely declare and cancel an emergency call on behalf of a remote user
- Access user check for the remote user
- Enable or disable PTT service
- Activate ambient listening for the remote user
- Activate discreet listening for the remote user

### 25.2

## Alert Types

Alert type notify the user of alerts

The following alerts types are supported:

**Instant Personal Alert (IPA)** An Instant Personal Alert allows you to request a callback from another subscriber. For more details, see the [Calling from Instant Personal Alert on page 64](#) section.

**Missed Call Alert (MCA)** A Missed Call Alert (MCA) alerts you whenever you miss a PTT call. For more details, see the [Missed Call Alert on page 172](#) section.

### 25.3

## Call Types

There are various call types.

**Broadcast Call** A high-priority call where only designated talkgroup members, called broadcasters, may initiate broadcast talkgroup calls. For more details, see the [Making Broadcast Calls on page 62](#) section.

**Emergency Call (Contact or Talkgroup)** The highest-priority call that preempts other PTT calls. See the [Emergency Calling and Alert \(Optional\) on page 71](#) section for more details on how to make an emergency call to a contact or talkgroup.

**Private Call (One-to-One Call)** A private call (also known as a one-to-one call) is a call between you and one other person. For more details, see the [Making One-to-One \(1:1\) Calls with Automatic Call Answer on page 59](#) section.

**Talkgroup Call** A talkgroup call is a call to a group of people. For more details, see the [Talkgroups on page 102](#) section.

## Quick Group Call

A quick group call allows you to make a PTT call to up to 10 people without first creating a talkgroup, which is handy if you want to call a small group of people quickly that are not already in a group. For more details, see the [Making Quick Group Calls on page 61](#) section.

You can create a group from a quick group call in your call history unless your administrator has restricted your phone from adding new groups.

## Display Name

Your display name is shown to others during a PTT call and in their PTT call history. You can change your display name from within the PTT application settings unless restricted by your administrator. For more details, see the [Restore Defaults on page 173](#) section.

## Floor Control

While in a PTT call, only one person can speak at a time. The person speaking is said to “have the floor.” The following terms are used throughout this document:

- [Floor Acquired](#)
- [Idle Floor](#)
- [Floor Unavailable](#)

**Floor Acquired** When you take the floor by pressing the PTT button, the on-screen PTT button changes, and you hear a “chirp. This chirp indicates that you have the floor and can speak while you press the PTT button. When you stop talking, you should release the PTT button.

**Idle Floor** While no one is speaking, the floor is “idle” and available for anyone to take. The screen changes color and shows the message, “No one is speaking...” If you want to speak, you must wait until the floor is idle, then you can press the PTT button to acquire the floor.

**Floor Unavailable** Whenever someone else is speaking, you see the speaker’s name and the on-screen PTT button changes. You cannot take the floor while someone else is speaking, you get a bong tone, or floor deny. If you are speaking and a supervisor takes the floor, you hear a tone and the on-screen PTT button changes.



**NOTE:** If the call is a group call and you are a supervisor for the group, whenever you press the PTT button, the floor is revoked from the person speaking including another supervisor and you can speak after acquiring the floor. For more details, see the [Supervisory Override on page 82](#) section.

## Talkgroup

A group is a type of PTT contact that connects you to multiple people at once. For more details, see the [Talkgroups on page 102](#) section.

## Integrated Secure Messaging

Integrated Secure Messaging allows a PTT subscriber to send and receive secure text messages, multimedia content, and location information to and from other PTT subscribers. For more details, see the [Integrated Secure Messaging](#) section.

## Supervisory Override

A supervisory override allows a group member to be designated by an administrator as a supervisor and be able to take the floor and speak at any time during a call, even if someone else has the floor. One or more members of a group can be designated as a supervisor. If there are two or more supervisors in the same

group, each supervisor can interrupt the other(s). For more details, see the [Supervisory Override on page 82](#) section.

### **Talkgroup Scanning**

Talkgroup Scanning allows a users phone to scan through a list of corporate talkgroups for calls and up to three talkgroups can be assigned as priority (1–3) talkgroups. The higher priority talkgroup calls take precedence over lower priority talkgroup calls. Talkgroups that are not in the scan lists do not barge in when Scanning is ON. For more details, see the [Talkgroup Scanning on page 110](#) section.

### **Video Streaming**

Allows you to stream your video in real-time to another user, typically a dispatcher. For more details, see the [Video Streaming \(Optional\) on page 150](#) section.